

N O T I C E

THIS DOCUMENT HAS BEEN REPRODUCED FROM
MICROFICHE. ALTHOUGH IT IS RECOGNIZED THAT
CERTAIN PORTIONS ARE ILLEGIBLE, IT IS BEING RELEASED
IN THE INTEREST OF MAKING AVAILABLE AS MUCH
INFORMATION AS POSSIBLE

(NASA-CR-163253) COMPUTER PREDICTION OF
LARGE REFLECTOR ANTENNA RADIATION PROPERTIES
(North Carolina State Univ.) 169 p
HC A08/MF A01

N80-27556

CSCL 17I

Unclass

G3/32 28014



DEPARTMENT OF ELECTRICAL ENGINEERING
NORTH CAROLINA STATE UNIVERSITY
RALEIGH, NORTH CAROLINA

COMPUTER PREDICTION OF LARGE
REFLECTOR ANTENNA RADIATION PROPERTIES

by

ALAN BOTULA

DEPARTMENT OF ELECTRICAL ENGINEERING
NORTH CAROLINA STATE UNIVERSITY
Raleigh, North Carolina

July 1980

This research was supported by the National Aeronautics and Space
Administration through grant NSG 1588.

ABSTRACT

BOTULA, ALAN BERNARD. Computer Prediction of Large Reflector Antenna Radiation Properties. (Under the direction of JAMES FRANK KAUFFMAN.)

A program for calculating reflector antenna radiation patterns has been rewritten and extended to include a new class of reflector surfaces. The original program, developed jointly by North Carolina State University and NASA, was capable of computing patterns for reflectors with smooth analytic surfaces. The revised version allows the reflector to be composed of a number of panels, removing the restriction that the surface must be smooth. These individual panels, however, are subject to the restrictions originally imposed upon the entire surface; that is, they must be analytic surfaces.

The theoretical foundation for the program is as follows: Geometrical optics techniques are used to trace rays from a feed antenna to the reflector surface and back to a mathematical plane just in front of the reflector. The resulting tangential electric field distribution, assumed to be the only source of forward radiation, is integrated numerically to calculate the radiation pattern for a desired set of angles. When the reflector is composed of more than one panel, each panel is treated as a separate antenna, the ray-tracing procedure and integration being repeated for each panel. The results of the individual aperture plane integrations are stored and summed to yield the relative electric field strength over the angles of interest.

An example and several test cases are included to demonstrate the use of the program and verify the new method of computation.

TABLE OF CONTENTS

	Page
1. INTRODUCTION	1
2. THEORETICAL DEVELOPMENT	3
2.1 Review of Theory	3
2.2 Review of the Original Program	13
2.3 Numerical Techniques for the Revised Program	16
3. THE STRUCTURE OF REFLECTR	24
3.1 Overview	24
3.2 NPUT	30
3.3 APRTUR and APRIN	31
3.4 FILL	34
3.5 QUANTZ	37
3.6 INTGRT	45
3.7 Main Procedure	48
4. OUTPUT CONTROL AND PROGRAM OPTIONS	54
4.1 Introduction	54
4.2 Printing Options	54
4.3 Plotting Options	55
4.4 Disk Storage Options	56
5. THE SUPPORT CODE	57
5.1 Introduction	57
5.2 PLOT4	57
5.3 IO	60
5.4 Utility Routines	61
6. EXAMPLE AND FIRST TEST CASE	67
6.1 Introduction	67
6.2 Description of the Problem	68
6.3 General Input File	70
6.4 First Configuration	71
6.5 Second Configuration	76
6.6 Third Configuration	79
6.7 Results	79
7. SEGMENTED SPHERICAL REFLECTOR TEST CASE	87
7.1 Description of the Antenna	87
7.2 Computation and Results	87

8. CONCLUSIONS	92
LIST OF REFERENCES	93
APPENDIX A - DEVELOPMENT OF THE APERTURE PLANE INTEGRALS	94
APPENDIX B - DEVELOPMENT OF RAY BACKTRACING EQUATIONS	100
APPENDIX C - ADDITION OF PARABOLIC CYLINDERS	102
APPENDIX D - LISTING OF THE CODE FOR REFLECTR	106
APPENDIX E - OUTPUT FOR THE EXAMPLE	122

1. INTRODUCTION

This thesis reports the work done to extend the capabilities of the computer algorithm, REFLECTR, a Fortran program developed jointly by North Carolina State University and the National Aeronautics and Space Administration to compute reflector antenna radiation patterns.

The original program was published in the IEEE Transactions on Antennas and Propagation in 1976 [1]. At this stage, it was capable only of computing patterns for paraboloidal reflectors. It was called PREFPAT, an acronym for Paraboloidal REFlector PATterns. The geometrical formulation was later changed to provide the calculated co- and cross-polarized fields which would actually be measured on an antenna range. This revised version appeared later that year in a North Carolina State University report [2]. Between 1976 and 1978, the program was extended to include ellipsoidal and spherical surfaces. It also received its present name, REFLECTR. A report on these changes was published by NASA in May of 1978 by Dr. Pradeep K. Agrawal [3]. Dr. Agrawal continued to improve the program, adding the ability to analyze planar reflectors in addition to the other surfaces [4].

The objective of the work reported herein is to generalize REFLECTR to make it capable of computing patterns for more complex surfaces; in particular, reflectors constructed from several panels or sections. The strategy for the algorithm is to represent each panel as a separate antenna and superpose their radiation patterns to find the total secondary pattern for the configuration. Among the consequences of this work were the automation of several operations formerly

done manually, the addition of equations for parabolic cylinders to allow analysis of deployable gored reflectors, a numerical technique for aperture boundary definition, and improved output formatting with more control over output operations.

This latest version of REFLECTR is written in standard Fortran-G using no compiler-specific advantages. With the exception of the plotting package, it should run on any Fortran compiler with little change. A complete description of how to organize an input file for the program for several reflector configurations is provided in Section 6.

The increase in the generality of the algorithm has not caused a substantial increase in computer time. In fact, the revised version requires only about six percent more time than the old program when making a pattern computation for a given single-panel reflector.

2. THEORETICAL DEVELOPMENT

2.1 Review of Theory


The new and old versions of REFLECTR share a common theoretical core. Before either program is discussed individually, this basic theory will be reviewed.

The approach taken in this algorithm is to assume that the reflector is in the far field of the feed antenna and to use geometrical optics ray tracing to compute the electric field over a planar aperture just in front of the reflector surface. The tangential field over this aperture is assumed to be the only source of forward radiation and is integrated to yield the composite radiation pattern of the antenna. Edge diffraction effects are neglected.


A reflector antenna is described in terms of two cartesian coordinate systems, the reference (unprimed) system and the feed (primed) system. These are shown in relation to a typical reflector antenna in Figure 1. The feed system is used to describe the feed antenna radiation pattern. The reflector geometry, the location of the aperture plane, and the overall radiation pattern are described in the reference system. In general, these coordinate systems are related by a rotation and a translation, each with three orthogonal components.

The majority of the operations in the algorithm are performed in the reference coordinate system. The reflector surface is described by a function of the reference coordinates x , y , and z . Five types of surfaces are presently available to the program: planes, spheres, ellipsoids, paraboloids, and parabolic cylinders. Other second-order

REFLECTOR
SURFACE



REFERENCE
SYSTEM



FEED
SYSTEM




FIG. 1. COORDINATE SYSTEMS

polynomial functions may be added with little difficulty. The composite radiation pattern is expressed in a spherical coordinate system which is based on the reference cartesian coordinates. Convention is followed in that the theta angle is the polar angle measured from the positive z-axis and phi is the angle in the xy plane increasing from the positive x-axis to the positive y-axis.

The feed system allows the feed antenna radiation pattern to be described independently of its location or orientation. The phase center of the feed antenna is assumed to be at the origin of its coordinate system and the antenna points in the negative x' direction. Its radiation pattern is described in a spherical coordinate system, which is based on the feed cartesian coordinates using the same convention as the reference spherical system. The feed coordinate angles are denoted θ' and ϕ' to differentiate between these and the reference system angles. Field strength and phase information for a given set of ray angles is obtained by evaluating a known function, which represents an assumed feed pattern, or by interpolating from measured data. Because the feed antenna points in the negative x' direction, the main beam will be oriented at $\phi' = 180^\circ$ instead of $\phi' = 0^\circ$. Hence, the radiation pattern must be shifted in the phi coordinate by 180° before it is used in the program.

Once a ray is generated in the feed system, it must be expressed in the reference system. The transformation is performed by a three-dimensional rotation matrix $[A]$. A derivation of the rotation matrix appears in [2].

The rotation matrix is computed from the three angles used to define the rotations required to make the feed system parallel to the reference system. These angles will be called ALPHA, BETA, and GAMMA. Figure 2, taken from Agrawal [3], shows these angles as they relate to the feed coordinate axes. ALPHA is a rotation about the z' -axis. It could be considered the azimuthal aiming angle for the feed antenna. BETA is a rotation about the x' -axis, providing a means for effectively rotating the reflector. GAMMA is a rotation about the y' -axis. This angle is commonly used to define the feed pointing angle for offset reflectors. All angles are defined to be positive if the rotation is counter-clockwise when looking in the negative direction along the axis of rotation.

The reflector is illuminated by a raster scan of rays over the angles it subtends. As computer storage is presently allocated, as many as 2750 rays, defined by their angles theta and phi, may be created for this purpose. This limitation may be removed by increasing the dimensions of the P array (See Appendix D). For reasons explained later, the outermost rays are intended to miss the reflector.

For purposes of illustration, a single ray will be traced through the series of operations resulting in the calculation of a point on the aperture plane. The ray begins as a set of angles θ' and ϕ' in the feed system. The appropriate θ' - and ϕ' -polarized electric field strengths and the initial phase are taken from the feed antenna pattern. This constitutes five pieces of information associated with a given ray. A unit vector, \hat{s}_i , in the direction of the ray is computed using the familiar relations




FIG. 2. FEED ROTATION ANGLES

$$\hat{s}_1 = s_x \hat{x} + s_y \hat{y} + s_z \hat{z}$$

$$s_x = \sin \theta' \cos \phi'$$

$$s_y = \sin \theta' \sin \phi'$$

$$s_z = \cos \theta'$$

The θ' and ϕ' components of the field are similarly resolved to their rectangular components. Recall that the feed system is translated with respect to the reference system. The reference origin is known as a point in the feed system and this coordinate triplet may be thought of as the translation vector $\vec{O'O}$ expressed in the feed system (See Figure 1). The point where the ray strikes the reflector surface is defined by the vector \vec{V} as shown in Figure 3. Thus,

$$\vec{V} = r \hat{s}_1 - \vec{O'O}$$

where r is the distance to the intersection point from the feed origin. To find \vec{V} , the vectors \hat{s}_1 and $\vec{O'O}$ must be expressed in the reference coordinate system. The transformation into the reference system is accomplished by forming a 3 by 2 matrix $[BB]$ whose columns are the ray unit vector \hat{s}_1 and the translation vector, and premultiplying it by the rotation matrix $[A]$. $[A]$ operates on each column of $[BB]$ independently, causing the ray unit vector and the translation vector to be rotated into the reference system,

$$[A][BB] = [B] = [b_{ij}].$$




FIG. 3. VECTOR OPERATION

The resulting matrix [B] has the transformed ray unit vector as its first column and the transformed translation vector as its second. All points in the path of the ray are now described in the reference system by the parametric equations

$$x = b_{11}r - b_{12}$$

$$y = b_{21}r - b_{22}$$

$$z = b_{31}r - b_{32}$$

where r is the distance travelled from the feed origin along the ray. Simultaneous solution of the above parametric equations with the equation of the reflector surface will yield the point of intersection (x_0, y_0, z_0) and the distance from the feed origin R . The unit normal to the surface is evaluated at this point and used to compute a vector in the direction of the reflected ray,

$$\vec{s}_r = \hat{s}_i - 2(\hat{n} \cdot \hat{s}_i)\hat{n}.$$

Because the reflector is assumed to be in the far field of the feed antenna, the electric field incident on the reflector surface, denoted \vec{E}_i , is attenuated by a factor $1/R$. The reflected field, assuming a perfect conductor, is given by

$$\vec{E}_r = 2(\hat{n} \cdot \vec{E}_i)\hat{n} - \vec{E}_i.$$

To find the intersection of the reflected ray with the aperture plane, another set of parametric equations is formulated,

$$x = x_0 + d \cos (\alpha_x)$$

$$y = y_0 + d \cos (\alpha_y)$$

$$z = z_0 + d \cos (\alpha_z)$$

where d is the distance travelled along the ray. The direction cosines are easily computed by

$$\cos \alpha_x = \frac{(\hat{x} \cdot \vec{s}_r)}{|\vec{s}_r|}$$

$$\cos \alpha_y = \frac{(\hat{y} \cdot \vec{s}_r)}{|\vec{s}_r|}$$

$$\cos \alpha_z = \frac{(\hat{z} \cdot \vec{s}_r)}{|\vec{s}_r|}.$$

The parametric equations are solved simultaneously with the equation of the aperture plane ($x = x_c$) to give the point of intersection (x_a, y_a, z_a) and the distance d . The phase of the field upon reaching the aperture plane is computed using

$$\phi = \frac{2\pi(R + d)}{\lambda} + \phi_0$$

where ϕ_0 is the phase of the feed antenna radiation pattern at the angles defining that ray. There are five quantities computed at the point at which the ray intersects the aperture plane: the y and z coordinates, the y and z components of the electric field, and the phase of the field. A more detailed discussion of the above operations is provided by Kauffman [2].

The field strength radiated by a reflector antenna at a particular point in space is computed by evaluating two integrals over the aperture plane. It is necessary to integrate only those points which result from reflections from the actual surface and not from its mathematical extension. To do this, the reflector boundary must be defined on the aperture plane allowing the extraneous points to be identified. Methods for finding and describing the boundary are discussed later. A series of edge points is interpolated on the boundary using information from points which lie outside of the aperture. The reason for over-illuminating the reflector as mentioned earlier is to insure that there will be points external to the aperture with which to interpolate edge points. The points external to the aperture are then discarded. The next processing step is to quantize the aperture plane points in their y-coordinate. A series of equispaced constant-y lines, called grid bars, is created across the bounded aperture. If the field strength and phase vary slowly across the aperture compared to the grid bar spacing, little error is incurred if the point is simply assigned a new y-coordinate corresponding to the nearest grid bar.

The integrals to be evaluated are:

$$E_{\theta} = \iint_{\text{Aperture}} ER_z \cos \phi \exp\{j[ky \sin \theta \sin \phi + kz \cos \theta - \phi]\} dydz$$

$$E_{\phi} = \iint_{\text{Aperture}} (ER_y \sin \theta + ER_z \cos \theta \sin \phi) \exp\{j[ky \sin \theta \sin \phi + kz \cos \theta - \phi]\} dydz.$$

The development of these integrals may be found in Appendix A. They are evaluated in two steps. First, the z-dependent part of each integral is computed as a line integral along each individual grid bar. The results of the grid bar integrations, weighted by the grid spacing, are then summed to give the total integrals. This procedure is repeated for each pair of angles in the desired pattern. When the pattern is complete, the field value of largest magnitude in each polarization is assigned the value of zero decibels. The remaining field strength values are tabulated and plotted in dB relative to these maximum values. The above operations form the core of both algorithms.

2.2 Review of the Original Program

The latest version of REFLECTR prior to this work was organized as shown in Figure 4. The subroutines in the double-lined boxes will be briefly discussed to describe how the various tasks were distributed in the program and by what means they were accomplished. The main procedure (MAIN) was little more than a calling program to the five principal subroutines shown below it and will receive no further attention.

NPUT was the first routine called by the main program. Its primary function was to read the input data for the reflector under computation. In addition to the basic geometrical data, the old version required the programmer to supply parameters for an aperture plane boundary ellipse; the grid bar location and spacing; and the minimum, maximum, and incremental values of θ' and ϕ' for the illumination pattern. All of these had to be calculated prior to running the program. NPUT passed the illumination pattern specifications to the subroutine called FILL.




FIG. 4. STRUCTURE OF ORIGINAL VERSION

The function of FILL was to load the main working array of the program, hereafter referred to as the P array, with illumination data. FILL had no established form. It was simply a name assigned to any subroutine which would accept minimum, maximum, and incremental values of theta and phi and load the P array with ray data. If some type of information was needed for this purpose, such as a table of field strengths for the feed antenna, it was read in at this time. FILL would load the P array and return to NPUT, which would then compute some trigonometric constants and return control to the main procedure.

The next subroutine called was APERTUR. APERTUR was responsible for tracing the rays to the aperture plane, determining whether or not they resided within the aperture boundary ellipse, and interpolating a set of edge points. The routine began by computing the rotation matrix, then proceeded to trace each ray to the aperture plane. When the location of a point on the aperture plane was found, it was tested for residence by evaluating the aperture plane ellipse equation using its y- and z-coordinates. Aperture blockage was tested similarly. If a point was inside the ellipse, it was stored at the beginning of the P array. If a point was on the edge of the ellipse, it was stored at the end of the array. If a point was found to be outside, it was discarded. When two successive points were on opposite sides of the ellipse, an edge point was interpolated between them and stored with the naturally occurring edge points.

QUANTIZ prepared the aperture plane for integration by quantizing the locations of the aperture plane points in the y-coordinate. The edge points found by APERTUR were used in a spline interpolation

routine to compute a new set of edge points at the grid bar locations. The interior points were quantized separately and concatenated in the array with the new edge points. Finally, the array was sorted; first with respect to y , then with respect to z .

APRPLT made a plot of the locations of the computed points on the aperture plane both before and after quantizing. Different symbols were used for every three dB variation in electric field strength across the aperture. A modified version of APRPLT is used in the revised program.

A feature of the old program was that in the radiation pattern request, one could specify a pattern referenced to the beam maximum. The computer estimated the beam maximum by finding the ray corresponding to $\theta = 90^\circ$; $\phi = 180^\circ$ in the feed system and stored the angles of its reflection from the reflector surface in the reference system. This feature was not retained in the revised program.

2.3 Numerical Techniques for the Revised Program

In order to accommodate multi-panelled surfaces, several new numerical techniques were added to the algorithm. These additions are now discussed in detail.

Each panel of the reflector is described by a surface code, surface parameters, and a list of edge points. The surface code and parameters allow the computer to select the correct surface equations with which to compute the ray reflections. The edge points, hereafter referred to as perimeter points, are the vertices of a convex polygon which approximates the boundary of the panel in question. The perimeter points are expressed in the reflector cartesian coordinate system and

must be input to the computer in order as one follows the boundary of the reflector panel either clockwise or counterclockwise. These need not lie in a single plane as they will be projected onto the aperture plane in order to estimate the aperture boundary.

The large number of panels possible in a reflector antenna motivated the development of an algorithm to delineate the angular extent and incrementation of the feed pattern to be used for the illumination of a given panel. By performing the reverse of the ray-tracing procedure, the perimeter points can be expressed as pairs of angles in the feed spherical coordinate system. The details of this operation may be found in Appendix B. With this information, the angles subtended by the panel may be found and the illumination array created. The angles defined by each perimeter point are stored in the illumination pattern with the generated angles and projected to the aperture plane. These projected perimeter points define the aperture boundary for the particular panel.

The illumination pattern is composed under three constraints. The first constraint is that a certain number of rays are to be generated. This number, NTPPL, is supplied by the programmer for each panel. It is the approximate number of rays which he desires to use in illuminating the particular panel. The algorithm will generate a pattern with equal theta and phi increments which contains a number of rays as close to NTPPL as possible. Second, the algorithm will generate an additional set of rays one angular increment beyond the angles actually subtended by the reflector in order to slightly over-illuminate the panel. These extra rays are reflected from the mathematical extension

of the surface and used to interpolate edge point data later in the program. The third constraint involves quantizing considerations. If, in the feed system, ϕ is held constant and θ is varied, a constant- ϕ contour will be traced on the aperture plane. The program attempts to make the grid bars fall on these constant- ϕ contours. When this is done, the distance the points must be moved during quantizing is minimized. Another consideration concerning the grid bars is that the outermost bars come close to the edge of the reflector. If this is not done, the panel will be represented in quantized form as being narrower than is actually the case. If both of these conditions are to be met, some forethought must be exercised when creating the illumination array. The illumination pattern is constructed such that the outermost ϕ angles exceed the angular extents of the reflector panel (as determined by the perimeter points) by $4/5$ of an angular increment. The angles just within the angles subtended by the reflector are then $1/5$ of an angular increment inside the boundary angles. The resulting point distribution on the aperture plane will then exhibit qualities favorable to quantizing. The creation of the illumination pattern is thus a more complex procedure than it was in the old program, but it is almost completely automatic and less haphazard. It should be noted here that this system is hardly infallible and tends toward greater deviation as the rays become less parallel with the x-axis of the reference system; that is, for panels which lie near the edges of large reflectors. In these regions, the constant- ϕ contours bend into arcs, and a grid bar may cross several contour lines

The field strength is usually low in these regions, however, and this deviation has not been found to cause problems.

A major difference exists between the old and revised programs regarding the method by which the aperture plane points are prepared for integration, both in the handling of the edge points and in the determination of the aperture plane boundary. No attempt is made to distinguish between interior and exterior points in the APRTUR routine; instead, all of the rays are traced to the aperture plane and the array of points is delivered to the quantizing routine. The quantizing routine computes the position and spacing of the grid bars in accordance with the criteria stated earlier and assigns each point, except for those which are the projections of the perimeter points, a new y-coordinate corresponding to that of the nearest grid bar.

The aperture boundary is convex and closed; thus, each grid bar will intersect it at two points. The intersection points may be considered the endpoints of the grid bar, since any aperture plane point not lying on the resulting line segment does not reside in the aperture. Once the z-coordinate of each endpoint is known, residence of a data point in the aperture may be determined by comparing the z-coordinate of the data point with those of the endpoints for that particular grid bar.

To find the endpoints, the computer works its way around the polygonal boundary, formulating the line equations given by adjacent perimeter points. When the line equation for a particular pair of points has been found, any grid bars lying between the generating points are intersected with the line and are assigned the resulting z-coordinate

as one of their endpoints. After the entire boundary has been processed, each grid bar will have two endpoints and the extraneous points may be identified. This operation is pictured in Figure 5.

One of the major changes in the program is the procedure of integrating the aperture field panel by panel instead of all at once. This change is numerically justified by the fact that the phase of the fields for various panels is measured in absolute angle from the same phase reference and the integrations are all performed over the same plane. It is justified from a theoretical standpoint in that the linearity of the integrals and Maxwell's equations allow the superposition principle to be applied.

The program has the ability to compute single-panel antennas using an elliptical rather than a polygonal boundary. This has the advantage that a smooth edge will be created and only four perimeter points are required in the input data. The points supplied to the program are those constituting the maximum and minimum y- and z-coordinates; that is, the highest, lowest, leftmost, and rightmost points on the reflector as seen by the feed antenna. These points are projected to the aperture plane in the same way as those used to define a polygonal edge, and an ellipse is formulated using the distance between the high and low z-coordinates as the minor axis and the distance between the high and low y-coordinates as the major axis (See Figure 6). The grid bar endpoints are computed by solving the ellipse equation for z using the y-values of the grid bars. The solution is multi-valued, and the two solutions for each grid bar are its endpoints. This option will cause the edge to be misrepresented in configurations where the illuminating




FIG. 5. FINDING THE BOUNDARY




FIG. 6. SINGLE-PANEL TECHNIQUE

rays take on extreme values of the angular coordinates, but it does serve as a valuable simplification in the use of the program in many instances.

3. THE STRUCTURE OF REFLECTR

3.1 Overview

A block diagram of the revised version of REFLECTR is shown in Figure 7. The primary subroutines, pictured in the double-lined boxes, will be examined in detail in this section. The main procedure is last since a knowledge of the other primary routines is prerequisite to its discussion. The remaining subroutines function mainly in a support capacity and will be discussed in Section 5.

With the exception of the plotting package (APRPLT and PLTSET), the entire program is written using double-precision constants and functions. IBM double precision employs eight bytes of storage for each real variable and sixteen bytes for each complex variable. This corresponds to fifteen significant figures in real variables and in both the real and imaginary parts of the complex variables. The program has been tried with four-byte variables with a significant degradation in the results. In its present form, REFLECTR requires 258K of memory.

As a means of introducing some of the variables in the program, the eight common storage blocks will be listed and explained:

BLOCKG/YCBL, ZCBL, HFMABL, HFMIBL

(Aperture plane blockage information.)

YCBL, ZCBL -

y and z center coordinates of the aperture plane blockage ellipse.




FIG. 7. STRUCTURE OF REVISED VERSION

HFMABL, HFMIBL -

Half-major and half-minor axes of the aperture plane blockage ellipse (along y and z, respectively).

CONTRL/NOPT(3), NLIST, IOPT, ILIST(100)

(Program control variables.)

NOPT(3) -

Three numbers specifying options regarding printer, plotter, and aperture plane data output, respectively (See Section 4).

NLIST -

The number of panels for which the algorithm will print complete illumination and quantizing data.

IOPT -

A variable which is zero when the program is to run normally and one when the single-panel option is in effect.

ILIST(100) -

The specific panels for which the algorithm is to provide complete illumination and quantizing data (See Section 4).

DIMENS/YDIM, ZDIM, YCT, ZCT

(Dimensional data for the bounded aperture.)

YDIM, ZDIM -

The maximum y- and z-dimensions for the aperture to be plotted by APRPLT or APRMAP.

YCT, ZCT -

The y and z center coordinates of the aperture to be plotted.

EXTENT/YMIN, YMAX, ZMIN, ZMAX

(Dimensional data for the bounded aperture.)

YMIN, YMAX -

The lower and upper limits of the bounded aperture in the y-coordinate.

ZMAX, ZMIN -

The lower and upper limits of the bounded aperture in the z-coordinate.

(This is actually the same information as is contained in the DIMENS block but in a form which is more convenient for operations other than plotting.)

FEED/EP(91), ET(91), NP, NT.

(Feed antenna parameters.)

EP(91), ET(91) -

Arrays containing the electric field strengths of the feed antenna in one degree increments off-axis in the $\theta = 90^\circ$ and $\phi = 180^\circ$ planes, respectively.

NP, NT -

The number of increments of phi and theta used in the illumination pattern, respectively.

(The contents of this block will change depending on how the feed antenna is described. The above block was used in the first test case for which the feed pattern was interpolated from E- and H-plane tables.)

MATH/PI, PI2, PID2, DTOR, RTOD

(Mathematical constants.)

PI, PI2, PID2 -

Pi, two times pi, and pi divided by two.

DTOR, RTOD -

Constants for degree-to-radian conversion and radian-to-degree conversion.

PARAMS/AORORF, BELLP, PSI, PLNPNT(3), PLNORM(3), FEED(3), ALPHA, BETA, GAMMA, XLAM, SURFCE, NPNL, NPOINT

(Antenna system parameters.)

AORORF -

The focal length of a paraboloidal reflector, the focal length of a parabolic cylindrical reflector, the radius of a spherical reflector, or the semi-major axis of an ellipsoidal reflector (along x), depending on which surface is intended to represent the reflector.

BELLP -

The semi-minor axes (along y and z) of an ellipsoidal reflector surface. Note that this does not define a completely arbitrary ellipsoid since the axes along y and z must be equal.

PSI -

The angle of rotation of a parabolic cylinder whose focal line is in the yz plane as measured from the positive y-axis when looking in the negative-x direction in the reflector coordinate system (See Appendix C).

PLNPNT(3) -

The coordinates of a point on a planar reflector surface (x, y, z).

PLNORM(3) -

The components of a unit normal vector to a planar reflector surface (x, y, z).

FEED(3) -

The reference coordinate system origin as expressed in the feed coordinate system (x' , y' , z').

ALPHA, BETA, GAMMA -

The angles of rotation between the two coordinate systems as described in Section 2.1.

XLAM -

The wavelength of the radiation emitted by the feed antenna.

SURFCE -

An integer variable containing the value of the surface code.

- 1 - surface is a plane.
- 2 - surface is an ellipsoid.
- 3 - surface is a sphere.

- 4 - surface is a paraboloid.
- 5 - surface is a parabolic cylinder.

NPNL -

The number of panels comprising the reflector. If the value supplied to the computer is one or greater, the program expects a list of perimeter points and other surface parameters for each panel and the aperture boundary is approximated by a polygon. Entering the value of zero causes the program to use an ellipse to represent the boundary--the single-panel option.

NPOINT -

The number of points or rays which are being stored for processing in the P array at any given time.

PATRN/ ETOT(2,400), AMINOR (3,5), AMAJOR(5), MINOR(5), MAJOR(5),
NANGLE(5)

(Information concerning the overall radiation pattern.)

ETOT(2,400) -

A complex array which contains the summation of the aperture plane integration results from the individual reflector panels. The first subscript is one or two, denoting the θ - or ϕ -directed electric field, respectively. The pattern cuts are stacked end to end in the array. Presently, 400 angles may be stored.

AMINOR(3,5) -

A pattern request array. The first subscript is one, two, or three, denoting the lower, upper, or incremental values of the minor angle of the pattern. The second subscript denotes the particular request.

AMAJOR(5) -

A pattern request array which contains the angle defining the principle plane of the pattern cut. The subscript denotes the particular request.

MINOR(5) -

A pattern request array containing the angular coordinate (theta or phi) to which AMINOR applies. The subscript denotes the particular request.

MAJOR(5) -

A pattern request array containing the angular coordinate (theta or phi) of the principle plane of the pattern cut. The subscript denotes the particular request.

NANGLE(5) -

Contains the total number of angles in each requested pattern cut as determined by AMINOR. The subscript denotes the particular request.

The remaining variables will be introduced as the subroutines are examined. The reader is referred to Appendix D for a listing of the code while reading this section.

3.2 NPUT

NPUT is primarily an input/output routine. As it begins, IOPT, the single-panel option variable, is set to zero, indicating that the program is to run in the multi-panelled reflector option. The first four cards are read into the TITLE array as character data. NPUT then reads values for FEED, ALPHA, BETA, GAMMA, XLAM, SURFCE, NPNL, AORORF, BELLP, PSI, PLNPNT, PLNORM, XC, YCBL, ZCBL, HFMABL, AND HFMIBL. These numbers are all read regardless of whether or not they are applicable to the reflector under study. If a value is not needed, it is simply not used. Following this, any data required for the feed antenna pattern is read by appropriate statements. This section of NPUT is often changed to accommodate differences in the information required by a particular FILL routine. Any data read here is passed to FILL through the FEED common block. If NPNL was entered as zero, the four extreme points on the reflector are read into the P array. This is followed by the output option data.

Statements 77 to 98 are the pattern request input loop. AMINOR, AMAJOR, MINOR, and MAJOR are read for consecutive requests during which the total number of pattern cuts and angles are monitored. If the number of cuts is greater than five, if the total number of angles involved is greater than 400, or if any one pattern contains more than 75 angles, an error message is printed and the program terminates. These maximum numbers are storage constraints which may be changed, if desired, and if sufficient memory is available in the computer. The number of pattern cuts is limited by the dimensioning of AMINOR, AMAJOR, MAJOR, MINOR, and NANGLE. The total number of angles in all patterns is limited by the dimensioning of ETOT, FIELDY, and FIELDZ. The number of angles in any given pattern is restricted by the dimensions of the arrays YFLD, ZFLD, and PWER in the main procedure.

The DO-loop to statement 108 clears as many locations in the ETOT array as are required to store all of the angles in the patterns. Following this step, the information received by the computer is printed and the mathematical constants in the MATH common block are calculated.

3.3 APRTUR and APRIN

In the first call to APRTUR, the rotation matrix is computed from the rotation angles ALPHA, BETA, and GAMMA. Because it is a rotation matrix, [A] belongs to the class of Orthogonal Matrices. An Orthogonal matrix is non-singular and its inverse is equal to its transpose. AINV is thus obtained simply. The NPTPPL variable is set to 2250 to signify that in the case of the single-panel option, 2250 rays are to be generated to illuminate the panel. NPERIM is set to four in order to accommodate the four extreme points which are entered when the single-panel

option is used. If the program is to run normally; that is, using a polygonal aperture boundary, the APRIN routine will be called and NPERIM and NPTPPL will be updated to the appropriate values. In subsequent calls to APRTUR, the above steps are skipped.

If the single-panel option is not in effect, the APRIN subroutine is called to read data for the reflector panel. APRIN reads NPERIM, SURFCE, and NPTPPL on the first card of the panel data and screens these values for easily detected errors. If any are found, an error message is printed and the program stops execution. The perimeter points are then read into the P array with the x-, y-, and z-coordinates occupying the first, second, and third locations, respectively. These are followed by any other geometrical information needed for that surface. For example, were the panel an elliptical surface, values would be expected for AORORF and BELLP. If the output control variables dictate that data is to be printed for this panel, APRIN will do so. If not, it returns to APRTUR. After a call to APRIN, the values of SURFCE and whatever other parameters are required for the panel have been updated. For example, if the overall reflector was not an ellipsoid, an ellipsoidal panel would cause AORORF, BELLP, and SURFCE to be changed.

The statements in APRTUR between 50 and 65 are concerned with finding the angles subtended by the reflector or the reflector panel. The perimeter points are expressed as angles in the feed system and monitored to record the maximum and minimum θ' and ϕ' angles represented by the set of points. This procedure is applied to both the perimeter points and the four extreme points in the single-panel

option. Appendix B details the geometrical formulation for this operation.

The statements between 65 and 95 create the illumination array from the information found above. DELP and DELT are the angular dimensions of the panel in phi and theta, respectively. It is required that

$$NP * NT = NPTPPL.$$

An estimate of an appropriate NP is found by

$$NP * [NP * (DELT/DELP)] = NPTPPL$$

$$NP = [(DELP/DELT) * NPTPPL]^{0.5} + 1.$$

One is added to round NP to the next larger integer. The statement following this insures that the illumination pattern will have a set of angles generated at the phi angular center of the reflector by forcing NP to be odd.

If the reflector subtends DELP radians, it is desirable to have

$$ANGINC * (NP - 1) = DELP + (0/8 * ANGINC) * 2.$$

(See Section 2.3 concerning the illumination pattern.) Simplifying the above, the angular increment is found to be

$$ANGINC = DELP / (NP - 2.6).$$

NT is computed such that a set of rays exist at the θ' angular center of the reflector and the rays corresponding to the upper and lower limits of θ' miss the reflector. The resulting maxima, minima, and the

total number of angles generated are computed and, if desired, printed. The DO-loop to statement 95 loads the complete set of illumination angles into the P array just after the angle pairs corresponding to the perimeter points. The FILL routine is then called to supply the angle pairs in the P array with field strength and phase information.

3.4 FILL

Many FILL subroutines have been written for REFLECTR. One of the most useful is described in this section. It may be used for any antenna for which the E- and H-plane patterns are available as long as these patterns are symmetrical with respect to the negative x' -axis and may be adequately represented when sampled at one-degree intervals. The subroutine must be provided with two tables of relative field strengths in one-degree increments--one in the $\theta' = 90^\circ$ plane and one in the $\phi' = 180^\circ$ plane.

Consider the feed coordinate system and a typical ray as shown in Figure 8. The ray and the x' -axis define a plane. Let δ be the angle formed between the ray and the negative x' -axis in this plane. δ is given by

$$\delta = \arccos(\sin \theta' \cos \phi').$$

Because it is the angle between the ray and the axis of radiation symmetry, δ determines the values for the electric field to be taken from both the $\theta' = 90^\circ$ and $\phi' = 180^\circ$ patterns. Interpolation from the field strength tables is linear. Let ϵ be the angle between the $x'y'$ plane and the plane containing the ray and the x' -axis. Measured from the fourth quadrant of the $x'y'$ plane, ϵ is given by




FIG. 8. DEFINITION OF ANGLES
FOR FILL




FIG. 9. INTERPOLATION ELLIPSE

$$\epsilon = \arctan \left(\frac{\cos \theta'}{\sin \theta' \sin \phi'} \right).$$

This angle determines the proportion of each pattern used in computing the final electric field strength for the ray. The interpolation scheme is based on an ellipse as shown in Figure 9. The half-major and half-minor axes are the $\theta' = 90^\circ$ plane and $\phi' = 180^\circ$ plane field strengths, respectively. The ellipse equation is written in polar form to express the radius in terms of the angle ϵ .

$$\left(\frac{u}{E_{\theta'=90}} \right)^2 + \left(\frac{v}{E_{\phi'=180}} \right)^2 = 1$$

$$u = r \cos \epsilon$$

$$v = r \sin \epsilon$$

$$r = E_{\text{tot}} = \frac{E_{\theta'=90} E_{\phi'=180}}{E_{\theta'=90}^2 \sin^2 \epsilon + E_{\phi'=180}^2 \cos^2 \epsilon}.$$

The code for this subroutine may be found in Appendix C. PROJX is the direction cosine of the ray with the negative x' -axis; that is, the cosine of the angle δ . PROJY, the cosine of the angle ϵ , is set to zero. ϵ is undefined when $\delta = 0$; thus, it is not computed in this case. ANGLX is the measure of δ in degrees. LO and IHI are the indices of the array locations for the integral angles just below and just above δ , respectively. These are used to linearly interpolate the electric field in each principal plane. The elliptical interpolation is then carried out and the result is loaded into the proper location in the

P array. The subroutine is presently written so that the antenna is ϕ' -polarized and the initial phase is zero.

3.5 QUANTZ

It is assumed that the rays representing the extreme values of ϕ' miss the reflector; hence, there are NP-2 constant- ϕ' contours on the reflector. NBARS, the number of grid bars, is set to this value. An appropriate number of locations in the array of grid bar endpoints, Z, are set to 10^{20} . This number is used as a flag later in the program to determine whether the particular location has received an endpoint. After initializing the Z array, a loop finds the maximum and minimum y- and z-coordinates represented in all of the perimeter point projections and writes these points into the PR5 array. This array must be 5 by n where n is one greater than the number of perimeter points expected for any particular panel. The array is presently 5 by 41. The information found in this loop is used to compute plotting parameters (YCT, ZCT, YDIM, and ZDIM) and the grid bar locations. Note that the grid bars are placed in such a way that the outermost grid bars are 1/5 of a grid spacing inside the aperture. Lines 31 through 41 constitute the quantizing loop. A point is first examined to determine whether the y-coordinate lies within the established y-range of the aperture. If it does, it is assigned the y-coordinate of the nearest grid bar. If not, it is discarded. NPOINT is adjusted to account for the points which are deleted in this operation. The remaining points are sorted; first with respect to y, then with respect to z. The sorting process may be thought of as arranging the grid bars end to end in the array.

The next processing step is to compute the grid bar endpoints. The method using perimeter points is described first. As stated before, the basic strategy is to formulate line equations with adjacent perimeter points and intersect these with any grid bars which might lie between them. The variables involved are defined below:

KDEX -

The index of the perimeter point currently under consideration.

Y1, Z1 -

The y- and z-coordinates of the first point used to formulate the line equation.

Y2, Z2 -

The y- and z-coordinates of the second point used to formulate the line equation.

SLOPE -

The slope of the line.

B -

The z-intercept of the line.

YLO, YHI -

The lesser and greater values of the y-coordinate of the two perimeter points under consideration.

Z(2,71) -

The array of grid bar endpoints. Z(1,J) and Z(2,J) are the lower and upper endpoints of the Jth grid bar, respectively.

INDEX -

The index of the location in the Z array in which the computed endpoint is stored.

YQ -

The y-coordinate of the grid bar which is to be intersected with the line.

ZEE -

The z-coordinate of the computed endpoint.

ILOAD -

A loading index controlling which of two possible locations in the Z array will receive the computed endpoint once the second subscript is fixed.

A flowchart of the process used to load the Z array is shown in Figure 10. To begin, the first point in the PR5 array is copied into the location following the last perimeter point. KDEX is set to 2 to start the loop at the second point in the array. Y2 and Z2 are assigned the y- and z-coordinates of the first point. Y1 and Z1 are taken from the second point in the array and the difference between Y1 and Y2 is checked to insure that the line will not have infinite slope. Since the boundary is assumed to be convex, a vertical line must have one of the two outermost y-coordinates of the reflector. The grid bars were placed inside of these extremes; thus, a vertical line will intersect no grid bars. If Y1 and Y2 differ by too small an amount, the algorithm rejects the line and goes to the next point pair. Otherwise, the slope and z intercept are computed and YLO and YHI are determined. The first grid bar beyond YLO is the first candidate for intersection with the line. The y-coordinate and its index in the Z array are computed. If the grid bar is beyond YHI, the line is abandoned and the next line is formulated. If it is within the range of the line, the intersection is found and stored in the Z array. The index and y-coordinate are incremented by 1 and GRID, respectively, until YHI has




FIG. 10. FLOWCHART FOR LOADING Z ARRAY

been exceeded. The next line is then formulated and the process continues until the boundary has been closed.

After the Z array is loaded, a short loop following the loading procedure insures that $Z(1,J)$ is less than $Z(2,J)$ and that all locations of the array have been loaded with intersection coordinates.

If the single-panel option is in effect, the endpoints are found by solving the boundary ellipse equation at the grid bar locations. HFMAEX and HFMIEX are the half-major and half-minor axes of this ellipse, respectively.

The next section of QUANTZ imposes the boundary on the aperture. The approach taken is to step through the data points in each grid bar in ascending order, discarding those which are outside the aperture and retaining those which are inside or on the edge. When a grid bar endpoint is crossed, a new data point is interpolated with that z-coordinate. Any point found to reside in the aperture plane blockage ellipse is assigned zero field strength and phase. Upon completion of a grid bar, the number of retained and interpolated points is checked and the grid bar is deleted if this number is less than three. This is a requirement of the integration routine. A flowchart for this section of QUANTZ appears in Figure 11. The variables are defined below in order of their appearance.

N -

One greater than the total number of points retained in the aperture (including blocked points) at any given time.

L -

The total of points retained on the present grid bar (including blocked points) at any given time during the processing of that grid bar.




FIG. 11a. PARTIAL FLOWCHART FOR QUANTZ




FIG. 11b. PARTIAL FLOWCHART FOR QUANTZ

PBLK -

An array representing a blocked point. The field and phase values are zero and the first two locations contain the y- and z-coordinates of the point under consideration.

YQ -

The y-coordinate of the present grid bar.

IDEX -

The second subscript of the location of the Z array which contains the endpoints of the grid bar at YQ.

TEST -

A variable which is negative, zero, or positive if the data point is outside, on, or between the grid bar endpoints, respectively.

TESTBL -

A variable which is negative, zero, or positive if the data point is outside, on, or inside the blockage ellipse, respectively.

TESTO -

The value of TEST for the previous data point.

POLD -

The previous data point.

NCHG -

A variable controlling where a new point is loaded into the P array. NCHG = 0 means that the new point is to be loaded normally, while NCHG = 1 means that the point is to be loaded one location before the location indicated by N.

The only complication in the process occurs when the algorithm encounters an interior point after an exterior point. A point is interpolated on the boundary after the interior point has already been stored in the array. The interior point should follow the interpolated

point in the array because of its higher z-coordinate; thus, the points would be out of order if the interpolated point were loaded normally. When this situation arises, the interior point is moved up one space in the array and the interpolated point is loaded into the gap by subtracting NCHG from the loading index N. If the interpolation is a result of moving from an interior point to an exterior point, NCHG is zero and the interpolated point is loaded in normal order.

The end of QUANTZ sets NPOINT to the proper value and returns the perimeter points to the P array, storing them after the aperture points. Quantizing data is then printed and the P array is written to a disk file (excluding the perimeter points at the end) if the output control code indicates.

3.6 INTGRT

INTGRT is essentially the section of the old RADPAT subroutine which computed the radiation pattern integrals. The sections which performed other tasks have been deleted or moved to other parts of the program. INTGRT accepts the quantized P array and the pattern request from the main procedure and returns the integrated results for each angle of the pattern in the FIELDY and FIELDZ arrays in complex form. The integrals evaluated by INTGRT are:

$$E_0 = \iint_{\text{Aperture}} ER_z \cos \theta \exp \{j[ky \sin \theta \sin \phi + kz \cos \theta - \phi]\} dydz$$

$$E_\phi = \iint_{\text{Aperture}} (ER_y \sin \theta + ER_z \cos \theta \sin \phi) \exp \{j[ky \sin \theta \sin \phi + kz \cos \theta - \phi]\} dydz$$

where ER_y , ER_z , and ϕ are the y- and z-components and phase of the electric field at the point (y,z) in the aperture. The derivation of these integrals appears in Appendix D. Each of these integrals is divided into a set of integrations along each grid bar and a transverse integration of the results from the grid bars. The grid bar integrals are:

$$ZI = \int ER_z \cos \phi \exp\{j[kz \cos \theta - \phi]\} dz$$

$$y = \text{const.}$$

$$YI = \int (ER_y \sin \theta + ER_z \cos \theta \sin \phi) \exp\{j[kz \cos \theta - \phi]\} dz.$$

$$y = \text{const.}$$

The total integrals are the transverse integrals.

$$E_\theta = \text{FLDZ} = \int_{\text{All bars}} ZI \exp\{jky \sin \theta \sin \phi\} dy$$

$$E_\phi = \text{FLDY} = \int_{\text{All bars}} YI \exp\{jky \sin \theta \sin \phi\} dy$$

Integration is by the trapezoidal rule with the accuracy being enhanced by linearly interpolating a series of equidistant intermediate points between the existing data points. The number of subdivisions, called NPARTS, is presently seven.

A partial flowchart for INTGRT is shown in Figure 12. The variable SEN signifies the beginning and end of the P array. The first time it is encountered indicates that the first grid bar has just been integrated. The second time indicates that the last grid bar has been integrated. The subroutine begins by determining the first θ and ϕ




FIG. 12. PARTIAL FLOWCHART FOR INTGRT

angles in the pattern and computes their sines and cosines as required in the integrals. Although the integrals are evaluated simultaneously, only the E_θ integral will be discussed for the sake of clarity. The first two grid bars are integrated and these results form the first trapezoid of the transverse integral. This trapezoid is evaluated and stored in FLDZ. The next grid bar closes the second trapezoid, which is evaluated and summed into FLDZ. Each successive grid bar integral closes another trapezoid for the transverse integral such that the final grid bar closes the last trapezoid and FLDZ contains the result of the aperture integration for the theta polarization of the field. FLDZ is stored in FIELDZ(1) and the computation continues with the next set of angles. When the integrals have been evaluated for all angles in the pattern, the subroutine returns to the main procedure.

3.7 Main Procedure

The main procedure orchestrates the principal subroutines described earlier in the section to make a radiation pattern calculation. The variables introduced are defined below:

ETOT(2,400) -

A summing array for the complex values returned by INTGRT. FIELDY and FIELDZ are summed into ETOT(1,.) and ETOT(2,.), respectively.

YFLD(75), ZFLD(75) -

Arrays containing the magnitudes of the unnormalized ϕ - and θ -polarized electric field strengths, respectively, in a final antenna pattern.

PWER(75) -

An array containing the unnormalized power for angles in a final antenna pattern.

PR(2,500) -

An array containing the perimeter points of all panels of the reflector for use by the APRMAP subroutine. The y- and z-coordinates are denoted by the first subscript being one or two, respectively. Panels are punctuated in the array by a very large number in the y-coordinate location.

MLVL -

The stack pointer for the PR array. It denotes the next location pair [PR(1,.), PR(2,.)] to receive a perimeter point.

YLO, YHI -

The lowest and highest y-coordinate possessed by any panel yet processed.

ZLO, ZHI -

The lowest and highest z-coordinate possessed by any panel yet processed.

ISUM -

The index of the last pair of locations in the ETOT array to receive or supply pattern data.

NANG -

The number of angles in the present pattern.

FMAXY, FMAXZ -

The maximum ϕ - and θ -polarized electric field magnitudes, respectively, in a particular pattern.

PWR -

The total power corresponding to FMAXY and FMAXZ.

D -

The current value of the incremented angle in a particular pattern.

FMYDB, FMZDB, PWRMDB -

The decibel values of FMAXY, FMAXZ, and PWR, respectively.

DBZZ, DBZY -

The relative power in dB of the θ -polarized electric field with respect to FMZDB and FMYDB, respectively.

DBYZ, DBYY -

The relative power in dB of the ϕ -polarized electric field with respect to FMZDB and FMYDB, respectively.

The procedure begins by defining the decibel function and calling NPUT to read the reflector antenna parameters and computational requests. A loop is then begun which is performed once for each panel. APRTUR is called to create the illumination array and trace the rays to the aperture plane; then QUANTZ is called to prepare the aperture for integration. APRPLT is called if the output control code dictates. The dimensions of the aperture are checked with the current maximum and minimum values (YLO, YHI, ZLO, and ZHI), after which the perimeter points are stored in the PR array in locations indicated by the stack pointer MLVL. MLVL is updated and punctuation for that panel is stored after its perimeter points. The punctuation is used by APRMAP to distinguish between separate panels.

Patterns are stacked in the ETOT array as shown in Figure 13. INTGRT is called once for each pattern request. Each time a pattern is returned by INTGRT, FIELDY and FIELDZ are summed into the portion of the stack containing that pattern. ISUM is the pointer indicating the




FIG. 13. THE ETOT ARRAY

last pair of locations in ETOT to receive values. It is updated after every pattern and reset to zero after every panel.

After these steps have been performed, APRTUR is called to begin computation of the next panel. The process is repeated until all panels are finished, after which an APRMAP plot is generated, if specified by the output option code.

The rest of the main procedure is concerned with printing tables of electric field strengths for each pattern request. The first pattern is taken from the ETOT array and the magnitudes of the ϕ - and θ -polarized fields are placed in the YFLD and ZFLD arrays, respectively. The maximum and minimum of each of these arrays is found and assigned to FMAXY and FMAXZ, respectively. If these values are greater than 10^{-10} , they are converted to dB and the pattern from which they are taken is computed, tabulated, and plotted. If one or both of them are less than 10^{-10} , the entire pattern is set to -60 dB. This is an indication to the programmer that the magnitude of that polarization of the field is insignificantly small or that some problem exists in the calculation. Once the pattern maximum has been deemed large enough to output the pattern, the lowest value converted to dB for an individual angle is 10^{-15} . Any value smaller than this is assigned the value of -100 dB. This provides 100 dB of dynamic range for the weakest pattern qualifying for computation. The above precautions are exercised to prevent problems with the logarithm function in the computer.

The relative field values (DBZZ, DBZY, DRYZ, and DBYY) are computed and the table is printed one line at a time. PLOT4 is

called to make a printer plot of the table entries. The above steps are repeated until all requested patterns have been printed.

4. OUTPUT CONTROL AND PROGRAM OPTIONS

4.1 Introduction

In order to better monitor the calculation, a large quantity of output is available from the program. Selection of specific output is accomplished by means of a three-digit output option code which is supplied to the program along with the antenna parameters in the input file. This section describes the printing, plotting, and permanent storage abilities of the program and how the code may be used to exercise them.

The output option specification requires between one and eight cards, depending on which values are supplied for the output option code. These cards appear just before the pattern request cards in the input file. The option code, known to the computer as NOPT(3), is punched in the first three columns of the first card. Another field on the first card is for the variable NLIST. The remaining seven cards, if required, are for the dimensioned variable ILIST(100). These variables will be explained later in the section.

4.2 Printing Options

An example of the printed output from REFLECTR may be found in Appendix E. The portion of the output prior to the illumination data is not under control of the option code. The panel illumination and quantizing data (also in Appendix E) are under the control of the first digit of the code. If it is desired to print panel data for all panels, NOPT(1) is specified as two. It may be desirable to print this information only for several specific panels. In this case, NOPT(1) is

specified as one and the total number of panels for which data is requested is entered for the NLIST parameter. NLIST is right-justified in column 10 of the first card. If NOPT(1) is one, the program will look for the numbers of NLIST specific panels on the following cards according to a 16I5 format. Panels are numbered by the program in the order in which they are received. If it were required to print panel data for panels 6, 12, and 19, for example, NLIST would be given the value 3 and the first three I5 fields on the next card would contain the numbers 6, 12, and 19. These need not be supplied in any specific order and no more option cards would be required. If no panel data is to be printed, NOPT(1) is specified as zero. Printed output following the panel quantizing data; that is, the computed radiation pattern of the antenna, is not under control of the code.

4.3 Plotting Options

Two types of plotted output are available from REFLECTR: a plot of data points in the aperture plane (APRPLT) and a plot of the panel aperture boundaries on the aperture plane (APRMAP). APRPLT plots the aperture data points for a single panel (an example appears in Appendix E). APRMAP, which also appears in Appendix E, plots the boundaries of all of the apertures in one plot. Plotting is controlled by the second digit of the output option code, NOPT(2). If all of the panel apertures are to be plotted, NOPT(2) is specified as two. If only specific panel apertures are to be plotted, NOPT(2) is specified as one. In this case, the procedure followed is identical to that for the printing option. If both the printing and plotting options are specified as one, the panels to be printed and plotted must be the same. That is, only one

set of cards for ILIST follow the option code card; thus, there is no provision for printing and plotting different sets of panels. APRMAP is called automatically if any panels are plotted. If no plotting is to occur, NOPT(2) is specified as zero. Note that NLIST and ILIST only need to be provided if NOPT(1) or NOPT(2) equals one.

4.4 Disk Storage Options

REFLECTR has the ability to write the post-QUANTZ P array to a disk file for later examination or to be retrieved at the end of the program. This option is controlled by the third digit of the code, NOPT(3). If NOPT(3) is specified as two, the P array will be stored for all panels, then retrieved and printed at the end of the program. If NOPT(3) is one, the P array will be stored for all panels. Finally, specifying NOPT(3) as zero will cause the program not to store any aperture data. The data may be examined at a later time by submitting a job which calls the PTLIST subroutine described in Section 5.4.

5. THE SUPPORT CODE

5.1 Introduction

The support subroutines are subroutines which do not participate directly in the radiation pattern calculation. Instead, they aid the calculation in some way--either by preparing output or by performing simple data processing tasks. These subroutines do not appear in Appendix C with the principal subroutines. Instead, a listing of each is provided along with its description in this section.

The plotting package does not appear in this section. Plotting subroutines tend to be extremely installation-dependent and it was felt that a plotting package using local software would not be useful in general application. Agrawal's version of APRPLT [3] makes a good example on which to base a new version. There is enough information in Section 3.7 and the test case plots in Appendix E with which to synthesize a new version of APRMAP.

5.2 PLOT4

PLOT4 is the printer plot subroutine which produces the output shown in Figure 14. It plots the table of relative field strengths comprising the radiation pattern over a 60 dB dynamic range with one angular increment to a line and one dB to a print column. If a value to be plotted is more than 60 dB below the maximum value, a "<" character is printed at -60 dB. The angular axis is labelled every five angular increments and the lower plot border is always extended to the next even multiple of five increments. A listing of the subroutine appears in Table 1.

TABLE I. PLOT4

```

SUBROUTINE PLOT4 (NAME, FMAX, F, NT, MINOR, AMINOR)
  IMPLICIT REAL*8 (A-H, O-Z)
  REAL*8 NAME(8), MINOR
  DIMENSION LINE(71)
  DIMENSION F(NT), AMINOR(3)
  DATA IBLANK, LESS, IDOT, IDASH, I/1H, 1H<, 1H., 1H-, 1HI/
  PRINT 10, NAME, MINOR
10  FORMAT(///25X, 8A8, ///7X, A5, ' (DEG)  -60', 7X, '-50', 7X, '-40', 7X,
      .    '-30', 7X, '-20', 7X, '-10', 7X, '0', 9X, '+10', /20X, '*', 9X, '*', 9X,
      .    '*', 9X, '*', 9X, '*', 9X, '*', 9X, '*')
      DO 20 J=1, 70
20    LINE(J)=IDASH
      DO 22 K=1, 71, 5
22    LINE(K)=I
      DO 170 J=1, NT
      IF (J.EQ.1) GO TO 41
      DO 29 N=1, 70
29    LINE(N)=IBLANK
      TEST=DFLOAT(J-1)/5.0
      IF ((TEST-DINT(TEST)).EQ.0.0) LINE(2)=IDASH
      IF (LINE(2).EQ.IDASH) LINE(70)=IDASH
41    PLACE=F(J)-FMAX+60.0
      IF (PLACE) 90, 80, 70
70    LINE(1)=I
      K=PLACE+1.5
      LINE(K)=IDOT
      GO TO 99
80    LINE(1)=IDOT
      GO TO 98
90    LINE(1)=LESS
98    LINE(2)=IBLANK
99    PRINT 105, LINE
105   FORMAT(20X, 71A1)
      ANGLE=AMINOR(1)+(J-1)*AMINOR(3)
      IF (LINE(70).EQ.IDASH) PRINT 149, ANGLE
149   FORMAT(' ', 8X, F8.3)
170   CONTINUE
      DO 515 L=2, 70
515   LINE(L)=IBLANK
      LINE(1)=I
      II=NT+1
      JJ=NT+6
      DO 520 L=II, JJ
      TEST=DFLOAT(L-1)/5.0
      IF ((TEST-DINT(TEST)).EQ.0.0) GO TO 524
520   PRINT 105, LINE
524   DO 525 M=1, 70
525   LINE(M)=IDASH
      DO 545 N=1, 71, 5
545   LINE(N)=I
      PRINT 105, LINE
      ANGLE=ANGLE+5.*AMINOR(3)
      PRINT 149, ANGLE
      RETURN
      END

```

The lines of the plot are composed one at a time in the character array LINE(71). The array begins and ends with the character "I". On every fifth multiple of the angular increment, LINE(2) and LINE(70) are loaded with the "-" character and the value of the angle is printed beside the line. The dot is placed by using the value of the relative field strength to compute the index of LINE which will locate it properly with respect to the dB axis. The upper and lower plot borders are generated by loading all 71 locations with dashes, then writing an "I" over every fifth dash.

The calling arguments are NAME(.), FMAX, F(.), NT, MINOR, and AMINOR(.). NAME(.) is a 1-by-8 array of eight-byte variables containing the title of the plot. The title must be 64 characters long or padded with blanks to make 64 characters. FMAX is the maximum unnormalized field strength magnitude for the entire pattern in dB. F(.) is an array containing the unnormalized magnitudes of the pattern field strengths in dB. NT is the number of angles in the pattern. Finally, MINOR is the name of the angle to be varied in the pattern, and AMINOR(i) is for the low, high, and incremental values of this angle for i equal to one, two, and three, respectively.

5.3 IO

IO is the output control function subroutine. A referral to the output control variables is made by supplying IO with an integer code for the particular output operation and the number of the panel currently under computation. IO returns a 1 if the operation is permitted and a 0 if it is not.

A listing of IO is presented in Table 2. INTENT is the output operation code variable. The codes are:

1. Print panel illumination and quantizing data.
2. Plot the P array after quantizing (APRPLT).
3. Create a map of panel projections with the plotter (APRMAP).
4. Write the P array to a disk file after quantizing.
5. Read the P array from the disk file and print it at the end of the program.

ITER, or iteration, is the number of the present panel.

5.4 Utility Routines

Utility routines are those subroutines which perform standard data processing tasks. Included in this section are SETM, MOVEM, INTPL, MULT32, PTSORT, and PTLIST. All of these routines are relatively simple; thus, only a brief description of each will be provided.

SETM is listed in Table 3. It loads N locations of a singly-dimensioned array (A) with the constant X. Because of the way arrays are indexed in the computer, SETM may also be used to load X into rows of doubly-dimensioned arrays--such as the P array. For example, the Nth row of the P array could be loaded with X using the statement

CALL SETM (X,P(1,N),5).

SETM is used primarily in this capacity.

MOVEM appears in Table 4. Its function is to copy N values from one singly-dimensioned array (AOLD) into another array of the same type (ANEW). Like SETM, MOVEM may also be used to operate on rows of doubly-dimensioned arrays. The main use of MOVEM in this program is to

TABLE 2. IO

```

FUNCTION IO(INTENT,ITER)
IMPLICIT REAL*8 (A-H,O-Z)
INTEGER SURFCE
COMMON/CONTRL/NOPT(3),NLIST,IOP,ILIST(100)
GO TO (20,30,40,50,60),INTENT
20 IF (NOPT(1).EQ.0) GO TO 90
   IF (NOPT(1).EQ.2) GO TO 91
22 DO 25 I=1,NLIST
   IF (ILIST(I).EQ.ITER) GO TO 91
25 CONTINUE
   GO TO 90
30 IF (NOPT(2).GT.0) GO TO 91
   GO TO 90
40 IF (NOPT(2).EQ.0) GO TO 90
   IF (NOPT(2).EQ.2) GO TO 91
   GO TO 22
50 IF (NOPT(3).GE.1) GO TO 91
   GO TO 90
60 IF (NOPT(3).EQ.2) GO TO 91
90 IO=0
   RETURN
91 IO=1
   RETURN
END

```

TABLE 3. SETM

```

SUBROUTINE SETM(X,ANEW,N)
IMPLICIT REAL*8 (A-H,O-Z)
DIMENSION ANEW(N)
IF(N.LE.0) RETURN
DO 100 I=1,N
  ANEW(I)=X
100 CONTINUE
RETURN
END

```

TABLE 4. MOVEM

```

SUBROUTINE MOVEM(AOLD,ANEW,N)
IMPLICIT REAL*8 (A-H,O-Z)
DIMENSION AOLD(N),ANEW(N)
IF(N.LE.0) RETURN
DO 100 I=1,N
  ANEW(I)=AOLD(I)
100 CONTINUE
RETURN
END

```


copy 1-by-5 vectors such as PBLK(5) into rows of the P array, as shown below:

```
CALL MOVEM (PBLK, P(1,N),5).
```

INTPL is a linear interpolation subroutine used for the edge point interpolations in the aperture plane. It is listed in Table 5. PLO(·) and PHI(·) are arrays containing the data for the two known points with the lower and higher z-coordinates, respectively. Z(·) is an array containing the z-coordinates of the endpoints for the grid bar on which the interpolation is to be performed. The z-coordinate of the endpoint between the known points is assigned to the interpolated point PINT(·). The phase and both components of the electric field are interpolated based on the relationship between the z-coordinate of the endpoint and those of the known points.

MULT32 premultiplies a 3-by-2 matrix (OPB) with a 3-by-3 matrix (OPA) and stores the result in a 3-by-2 array (ROP). It is listed in Table 6.

PTSORT sorts a 5-by-n array A(5,n) in ascending order, first with respect to the numbers stored in the first column A(1,n), then with respect to the second column, A(2,n). The first and second columns correspond to the y- and z-coordinates of the data points in the P array, respectively. A listing of PTSORT is presented in Table 7. NROW is the length of the array in the second dimension. SWAP(·) is an intermediate array used to store information during a row exchange. The operation of the subroutine is simple. The first row is compared to every other row in the array. If any row is found which should appear before the first row, the information in the rows is

TABLE 5. INTPL

```

SUBROUTINE INTPL(PLO,PHI,PINT,Z)
IMPLICIT REAL*8 (A-H,O-Z)
DIMENSION PLO(5),PHI(5),PINT(5),Z(2)
ZC=Z(1)
IF (PLO(2).GT.Z(1)) ZC=Z(2)
FAC=(ZC-PLO(2))/(PHI(2)-PLO(2))
DO 10 I=1,5
10 PINT(I)=PLO(I)+FAC*(PHI(I)-PLO(I))
RETURN
END

```

TABLE 6. MULT32

```

SUBROUTINE MULT32(ROP,OPA,OPB)
IMPLICIT REAL*8 (A-H,O-Z)
DIMENSION ROP(3,2),OPA(3,3),CPB(3,2)
ROP(1,2)=OPA(1,1)*OPB(1,2)+OPA(1,2)*OPB(2,2)+OPA(1,3)*OPB(3,2)
ROP(2,2)=OPA(2,1)*OPB(1,2)+OPA(2,2)*OPB(2,2)+OPA(2,3)*OPB(3,2)
ROP(3,2)=OPA(3,1)*OPB(1,2)+OPA(3,2)*OPB(2,2)+OPA(3,3)*OPB(3,2)
ROP(1,1)=OPA(1,1)*OPB(1,1)+OPA(1,2)*OPB(2,1)+OPA(1,3)*OPB(3,1)
ROP(2,1)=OPA(2,1)*OPB(1,1)+OPA(2,2)*OPB(2,1)+OPA(2,3)*OPB(3,1)
ROP(3,1)=OPA(3,1)*OPB(1,1)+OPA(3,2)*OPB(2,1)+OPA(3,3)*OPB(3,1)
RETURN
END

```

TABLE 7. PTSORT

```

SUBROUTINE PTSORT(A,NCOL,NROW)
IMPLICIT REAL*8 (A-H,O-Z)
DIMENSION A(NCOL,NROW),SWAP(5)
DO 900 I=2,NROW
DO 900 J=1,NROW
100 IF ( A(1,J)-A(1,I-1) ) 100,200,900
DO 150 K=1,NCOL
SWAP(K)=A(K,I-1)
A(K,I-1)=A(K,J)
150 A(K,J)=SWAP(K)
GO TO 900
200 IF ( A(2,J)-A(2,I-1) ) 220,900,900
DO 250 K=1,NCOL
SWAP(K)=A(K,I-1)
A(K,I-1)=A(K,J)
250 A(K,J)=SWAP(K)
900 CONTINUE
RETURN
END

```

interchanged. After scanning the entire array, the first row will be that which has the lowest numbers in the first and second columns. The second row is then compared to the third and greater rows, and so forth, until the last row is reached. At this point, the array is sorted.

PTLIST reads the aperture data points which have been stored on disk earlier in the program and prints them in tables, one for each panel. NLIST is the number of points in the aperture and IPNL is the number of the panel corresponding to the aperture. A negative number read in the NLIST field indicates the end of the file. A listing of PTLIST appears in Table 8.

TABLE 8. PTLIST

```
SUBROUTINE PTLIST
REAL*8 Q(5)
2  READ(7,18) NLIST,IPNL
   IF (NLIST.LE.0) GO TO 8
   PRINT 20, NLIST,IPNL
   DO 4 I=1,NLIST
   READ(7,21) Q
   PRINT 22, Q
4  CONTINUE
   GO TO 2
8  PRINT 19
   STOP
18  FORMAT(2I8)
19  FORMAT(///10X,'***** END OF RECORD ON DATA SET 7 *****')
20  FORMAT('1',//10X,'LISTING OF APERTURE PLANE POINTS AS SUPPLIED TO
.RADPAT'//10X,I6,' POINTS INTEGRATED FOR PANEL NUMBER',I4,
.///14X,'Y-COORDINATE',8X,'Z-COORDINATE',10X,'EY (V/M)',12X,
. 'EZ (V/M)',10X,'PHASE (RADIANS)'//)
21  FORMAT(5D16.10)
22  FORMAT(10X,F15.8,6X,F15.8,6X,D16.10,4X,D16.10,4X,F16.8)
   RETURN
END
```

6. EXAMPLE AND FIRST TEST CASE

6.1 Introduction

The use of the program will now be demonstrated. In addition, a card-by-card description of the general input file will be provided before considering the specific antenna configurations. The example is taken from work reported by Rusch [5] and was used in an earlier report on REFLECTR prior to the work reported herein. The reflector will be described in general, then analyzed by the program in three roughly equivalent configurations. In Case I, the single-panel option will be used to represent the reflector as a single piece of material with an elliptical edge. In Case II, the reflector will be represented as a single panel with the edge defined by 20 perimeter points. This will closely approximate the elliptical edge. Finally, the reflector will be described as three panels such that these panels together form the surface of Case III. The object of the procedure is to compute nearly identical patterns in all three cases and to demonstrate agreement with the calculations in [5]. The first case verifies that the point processing changes made in QUANTZ will not adversely affect the performance of the program. The second case shows that a reflector edge may be adequately represented by a polygon. The third representation shows that it is numerically justified to superpose the patterns of the component panels to obtain the total pattern and that the algorithm is working correctly. In each case, the complete input file will be developed and listed.

6.2 Description of the Problem

The antenna, shown in Figure 15, is an offset-fed parabolic dish with a focal length of 31.5 inches. Measured in the focus-centered reference coordinates, the physical reflector lies between 21.8 and 84.1 degrees in the theta coordinate. The aperture projects onto the yz plane as a one-meter circle. The phase center of the feed antenna is located at

$$x = -1.854 \text{ in.}$$

$$y = 0.0$$

$$z = -3.966 \text{ in.}$$

in the reference system with the horn tilted upward 40 degrees.

The feed system origin is placed at the phase center of the feed antenna. The system is inclined 40 degrees in order to make $\theta = 90^\circ$, $\phi = 180^\circ$ correspond to the boresight of the antenna. This coordinate system rotation is given by $\text{ALPHA} = 0^\circ$, $\text{BETA} = 0^\circ$, and $\text{GAMMA} = -40^\circ$. The translation vector must be expressed in feed system coordinates. This is found by

$$x' = 1.854 \sin 40^\circ - 3.966 \sin 40^\circ = -1.129 \text{ in.}$$

$$y' = 0.0$$

$$z' = 3.966 \cos 40^\circ + 1.854 \sin 40^\circ = 4.230 \text{ in.}$$

The aperture plane should be placed just forward of the reflector surface. Some clearance should be allowed to insure that the over-illumination rays encounter the aperture plane before striking the reflector surface. The maximum x-coordinate of the surface in this example may be found by using the polar form of the parabola equation.




FIG. 15. OFFSET-FED PARABOLA

$$r = \frac{2f}{1 + \cos \theta_{\max}} = \frac{2(31.5)}{1 + \cos 68.2^\circ} = 45.94 \text{ in.}$$

$$x = -r \cos \theta_{\max} = -45.94 \cos 68.2^\circ = -17.06 \text{ in.}$$

The aperture plane will be placed at $XC = -16.0$ in. to provide the necessary clearance.

The feed antenna for this reflector is a scalar horn with a 15 dB amplitude taper at 34.1 degrees. Rusch [5] computed field strengths for this antenna in one-degree increments off boresight in both the E- and H-planes. These values are used by the FILL routine described in Section 3.4 to assign field strengths to the illumination array. The radiation is ϕ' -polarized with a wavelength of 2.367 inches [4.99 GHz].

6.3 General Input File

To help clarify the organization of the input file for REFLECTR, the general input file is explained below. The three examples in the following sections will provide files for actual computations.

<u>Card(s)</u>	<u>Information</u>
1-4	Title cards
5	FEED(1-3), ALPHA, BETA, GAMMA, XLAM
6	SURFCE, NPNL, AORORF, BELLP, PSI
7	PLNPNT(1-3), PLNORM(1-3)
8	XC, YCBL, ZCBL, HFMABL, HFMIBL
9-N	Any data required by the FILL subroutine.
(N+1)-(N+4)	Four extreme points (X, Y, Z) on the edge of the reflector. One point goes on each card (single panel option only).

<u>Card(s)</u>	<u>Information</u>
N+5	NOPT, NLIST (If NOPT specifies that only certain panels are to be printed or plotted, cards containing the list of these panels follow this card.)
N+6	MAJOR, AMAJOR, MINOR, AMINOR(1-3) (Pattern request cards. There will be between one and five of these cards in this location--the order of the requests is not important.)
N+7	DONE typed in the first four columns of the card.

These cards are followed by the panel data unless the single panel option is exercised. The organization of the panel data appears below.

<u>Card(s)</u>	<u>Information</u>
1	NPERIM, SURFCE, NPTPPL
2-(NPERIM+1)	(X, Y, Z) Perimeter points. (One perimeter point is put on each card.)
NPERIM+2	AORORF or AORORF, BELLP or AORORF, PSI or PLNPNT(1-3), PLNORM(1-3) depending on which parameters are needed to describe the surface specified by SURFCE.

The files for the individual panels are concatenated in the main input file after the DONE card. The order in which the panels appear is unimportant; however, they will be numbered by the program in this order.

6.4 First Configuration

Case I uses the single-panel option. In addition to the general information computed in the previous section, four points defining the aperture boundary ellipse must be found. Since these points are used to find the maximum and minimum θ' and ϕ' values for the illumination array, these four points must represent the extreme points on the dish

in each angular coordinate. The θ' extrema are the uppermost and lowermost points on the dish and may be found as follows:

Upper point -

$$r = \frac{2f}{1 + \cos \theta_{\max}} = \frac{2(31.5)}{1 + \cos 68.2^\circ} = 45.94 \text{ in.}$$

$$x = -r \cos \theta_{\max} = -17.060 \text{ in.}$$

$$y = 0.0$$

$$z = r \sin \theta_{\max} = 42.654 \text{ in.}$$

Lower point -

$$r = \frac{2f}{1 + \cos \theta_{\min}} = \frac{2(31.5)}{1 + \cos 5.9^\circ} = 31.58 \text{ in.}$$

$$x = -r \cos \theta_{\min} = -31.416 \text{ in.}$$

$$y = 0.0$$

$$z = r \sin \theta_{\min} = 3.246 \text{ in.}$$

The two points representing the y -extrema of the dish are almost exactly the ϕ' extrema as well. The z -coordinates of these points are identical.

$$z = \frac{z_{\min} + z_{\max}}{2} = \frac{42.654 + 3.246}{2} = 22.95 \text{ in.}$$

The dish is one meter wide and symmetrical with respect to the xz plane

$$y = \pm \frac{39.37}{2} = \pm 19.685 \text{ in.}$$

Finally, the paraboloid equation provides the x-coordinate.

$$x = \frac{y + z}{4f} - f = -24.244 \text{ in.}$$

Table 9 shows the input file for Case I. The first four cards contain title information which is reproduced at the beginning of the printout. The coordinate system information (FEED, ALPHA, BETA, and GAMMA) and the wavelength (XLAM) appear on Card 5. Cards 6 and 7 contain information about the surface of the reflector. Card 6 is for SURFCE, NPNL, AORORF, BELLP, and PSI. Card 7 is for PLNPNT and PLNORM. For this reflector, SURFCE, NPNL, and AORORF are given values of 4, 0, and 31.5, respectively. None of the other parameters are required for this surface, so all are given the value zero. Card 8 is for aperture plane information--XC, YCBL, ZCBL, HFMABL, and HFMIBL. In this case, there is no aperture blockage, so HFMABL and HFMIBL are both set to zero. Cards 9 through 46 are the tables of electric field strengths for the particular feed antenna in one-degree increments. The values begin at 0 degrees and progress to 90 degrees as one reads text--line by line from left to right. The $\phi = 180^\circ$ plane follows the $\theta = 90^\circ$ plane. The card order that follows is peculiar to the single-panel option. Cards 47 through 50 are for the extreme points on the dish. Unlike the perimeter points, they may be entered in any order. Card 51 is for the output option code. Here the computer is instructed to exercise the print and plot options for all panels and to write the aperture plane point array onto a disk file at the end of the QUANTZ subroutine. Since it is not requested that output options be exercised for any particular panels, NLIST has been left blank and there are no panel number cards

TABLE 9. CASE I INPUT

	OFFSET-FED PARABOLIC DISH		RUSCH/AEROJET		CASE ONE	
	ILLUMINATION INTERPOLATED FROM TABLES; NO BLOCKAGE; SINGLE-PANEL OPTION		USED IN THIS RUN.			
1	MAY 22, 1980	NCSU	PGMR: BOTULA	FCLTY: HILLSBORO		
2	-1.129	0.0	0.0	-40.0	2.367	
3	4	0	0.0	0.0		
4	0.0	0.0	0.0	0.0		
5	-16.0	0.0	0.0	0.0		
6	1.000000	0.998514	0.994251	0.987122	0.977230	ELECT
7	0.964645	0.949470	0.931827	0.911855	0.889713	
8	0.865567	0.839603	0.812006	0.782983	0.752735	
9	0.721474	0.689409	0.656752	0.623711	0.590488	
10	0.557281	0.524280	0.491659	0.459590	0.428226	
11	0.397712	0.368184	0.339747	0.312513	0.286573	
12	0.262009	0.238890	0.217275	0.197210	0.178732	
13	0.161864	0.146621	0.133000	0.120987	0.110546	
14	0.101622	0.094129	0.087955	0.082958	0.078977	
15	0.075836	0.073357	0.071374	0.069737	0.068321	
16	0.067025	0.065772	0.064510	0.063205	0.061836	
17	0.060394	0.058875	0.057280	0.055609	0.053868	
18	0.052066	0.050215	0.048333	0.046438	0.044547	
19	0.042671	0.040818	0.038990	0.037187	0.035415	
20	0.033683	0.032004	0.030391	0.028854	0.027391	
21	0.025998	0.024666	0.023388	0.022164	0.021002	
22	0.019913	0.018906	0.017981	0.017128	0.016331	
23	0.015576	0.014856	0.014177	0.013550	0.012989	
24	0.012496					
25						
26						
27						

for ILIST following Card 51. Cards 52 and 53 are the radiation pattern requests. Patterns are requested in the $\phi = 0^\circ$ plane for θ from 68.0° to 98.0° by 0.5° , and in the $\theta = 83^\circ$ plane for ϕ from -15.0° to 15.0° by 0.5° . The next card has DONE typed in the first four columns, which signifies that no more pattern requests follow. All of the above cards are read by the NPUT subroutine. This completes the input file for Case I. The output appears in Appendix E.

6.5 Second Configuration

In Case II, the program will run normally with 20 points on the dish edge selected as perimeter points. It was previously noted that the dish edge projects to a one-meter circle on the yz plane. The perimeter points are calculated by choosing twenty equispaced points on this circle and solving the paraboloid equation for the appropriate x-coordinate. The input file for this test case is shown in Table 10. The only changes in the file before Card 47 are the title cards and the NPPL parameter. NPPL is changed from 0 to 1 to indicate that the panel is to be treated normally and perimeter points are to be expected. The four extreme points used in Case I are deleted so that the option code card becomes Card 47 and the pattern requests become Cards 48 and 49. Card 50 is the DONE card. The panel data begins on Card 51 with NPERIM, SURFCE, and NPTPPL. NPTPPL is entered as 2250 to match the default value used in the single-panel option. The next NPERIM cards each contain the coordinates of a perimeter point (x, y, z) in its order of appearance as one traces around the dish edge. The final card in the panel data file is reserved for whatever parameters are required for the panel surface. In this case, the focal length of the paraboloid is

TABLE 10. CASE II INPUT

1	OFFSET-FED PARABOLIC DISH				RUSCH/AEROJET		CASE THREE	
2	ILLUMINATION INTERPOLATED FROM TABLES; NO BLOCKAGE; THREE PANELS -							
3	PANEL ONE- 20 PNTS		PANEL TWO- 21 PNTS		PANEL THREE- 21 PNTS			
4	MAY 22, 1980		NCSU	PCMR: BOTULA	FCLTY: HILLSBORO			
5	-1.129	0.0	4.229	0.0	0.0	-40.0	2.367	
6	4		3 31.5	0.0	0.0			
7	0.0	0.0	0.0	0.0	0.0	0.0		
8	-16.0	0.0	0.0	0.0	0.0			
9	1.000000		0.998514	0.994251	0.987122	0.977230		ELECT
10	0.964645		0.949470	0.931827	0.911855	0.889713		
11	0.865567		0.839603	0.812006	0.782983	0.752735		
12	0.721474		0.689409	0.656752	0.623711	0.590488		
13	0.557281		0.524280	0.491659	0.459590	0.428226		
14	0.397712		0.368184	0.339747	0.312513	0.286573		
15	0.262009		0.238890	0.217275	0.197210	0.178732		
16	0.161864		0.146621	0.133000	0.120987	0.110546		
17	0.101622		0.094129	0.087955	0.082958	0.078977		
18	0.075836		0.073357	0.071374	0.069737	0.068321		
19	0.067025		0.065772	0.064510	0.063205	0.061836		
20	0.060394		0.058875	0.057280	0.055609	0.053868		
21	0.052066		0.050215	0.048333	0.046438	0.044547		
22	0.042671		0.040818	0.038990	0.037187	0.035415		
23	0.033683		0.032004	0.030391	0.028854	0.027391		
24	0.025998		0.024666	0.023388	0.022164	0.021002		
25	0.019913		0.018906	0.017981	0.017128	0.016331		
26	0.015576		0.014856	0.014177	0.013550	0.012989		
27	0.012496							
28	1.000000		0.998486	0.994139	0.986870	0.976794		MAGNE
29	0.963975		0.948527	0.930586	0.910294	0.887824		
30	0.863348		0.837063	0.809177	0.779891	0.749428		
31	0.718007		0.685849	0.653170	0.620182	0.587093		
32	0.554100		0.521397	0.489158	0.457544	0.426712		
33	0.396795		0.367920	0.340184	0.313682	0.288490		
34	0.264668		0.242263	0.221307	0.201820	0.183806		
35	0.167258		0.152158	0.138473	0.126161	0.115165		
36	0.105417		0.096837	0.089334	0.082808	0.077149		
37	0.072248		0.067993	0.064278	0.061002	0.058077		
38	0.055427		0.052987	0.050705	0.048543	0.046470		
39	0.044465		0.042513	0.040607	0.038742	0.036916		
40	0.035129		0.033383	0.031682	0.030028	0.028426		
41	0.026878		0.025389	0.023961	0.022594	0.021291		
42	0.020050		0.018874	0.017760	0.016709	0.015719		
43	0.014790		0.013918	0.013102	0.012338	0.011623		
44	0.010954		0.010329	0.009746	0.009203	0.008696		
45	0.008223		0.007780	0.007366	0.006976	0.006609		
46	0.006265							
47	221							
48	PHI	0.0	THETA	68.0	98.0	0.5		
49	THETA	83.0	PHI	-15.0	15.0	0.5		
50	DONE							

TABLE 10. (continued).

47	221					
48	PHI	0.0	THETA	68.0	98.0	0.5
49	THETA	83.0	PHI	-15.0	15.0	0.5
50	DONE					
51	20	4 2250				
52	-24.244	19.685	22.950			
53	-22.028	18.722	29.033			
54	-20.029	15.925	34.521			
55	-18.443	11.571	38.875			
56	-17.424	6.083	41.672			
57	-17.073	0.0	42.635			
58	-17.424	-6.083	41.672			
59	-18.443	-11.571	38.875			
60	-20.029	-15.925	34.521			
61	-22.028	-18.722	29.033			
62	-24.244	-19.685	22.950			
63	-26.460	-18.722	16.867			
64	-28.459	-15.925	11.379			
65	-30.046	-11.571	7.025			
66	-31.064	-6.083	4.228			
67	-31.415	0.0	3.265			
68	-31.064	6.083	4.228			
69	-30.046	11.571	7.025			
70	-28.459	15.925	11.379			
71	-26.460	18.722	16.867			
72	31.5					

needed (AORORF). Were the panel part of an ellipsoid, both AORORF and BELLP would be expected on this card. A parameter received in a panel data file replaces any value supplied previously. The output received from this configuration is shown in Appendix E.

6.6 Third Configuration

Case III requires the synthesis of three separate panels from the single parabolic dish. The division of the surface and the location of the perimeter points are shown in Figure 16. The perimeter points on the edge of the dish are the same as those used in Case II. The points on the face of the dish were found by relating the y- and z-coordinates with line equations and using the paraboloid equation to find the corresponding x-coordinates. The density of illumination is kept close to that of the first two cases by requesting that each panel be illuminated by 800 rays.

The input file is shown in Table 11. It is identical to the file for Case II through Card 50 except for the title cards, the NPPL specifications, and the NPTPL parameter. For illustrative purposes, the panels have been input in the order shown in Figure 16, although the panels may be input in any desired sequence. Organization of the panel input files follows from Case II. The output appears in Appendix E.

6.7 Results

The results of these calculations are shown in Figures 17(a,b). The solid line represents Rusch's calculations. The circles, triangles, and squares represent the results of Cases I, II, and III, respectively. Whenever the Case II or III points fall on those computed from Case I,




FIG. 16. PANELS AND PERIMETER
POINTS FOR CASE III

TABLE II. CASE III INPUT

1	OFFSET-FED PARABOLIC DISH RUSCH/AEROJET						CASE TWO
2	ILLUMINATION INTERPOLATED FROM TABLES; NO BLOCKAGE						
3	REFLECTOR IS ONE PANEL DEFINED BY 20 PERIMETER POINTS						
4	MAY 22, 1980	NCSU	PGMR: BOTULA	FCLTY: HILLSBORO			
5	-1.129	0.0	4.229	0.0	0.0	-40.0	2.367
6	4		1 31.5	0.0	0.0		
7	0.0	0.0	0.0	0.0	0.0	0.0	
8	-16.0	0.0	0.0	0.0	0.0		
9	1.000000	0.998514	0.994251	0.987122	0.977230		ELECT
10	0.964645	0.949470	0.931827	0.911855	0.889713		
11	0.865567	0.819603	0.812006	0.782983	0.752735		
12	0.721474	0.689409	0.656752	0.623711	0.590488		
13	0.557281	0.524260	0.491659	0.459590	0.428226		
14	0.397712	0.368184	0.339747	0.312513	0.286573		
15	0.262009	0.238890	0.217275	0.197210	0.178732		
16	0.161864	0.146621	0.133000	0.120987	0.110546		
17	0.101622	0.094129	0.087955	0.082958	0.078977		
18	0.075836	0.073357	0.071374	0.069737	0.068321		
19	0.067025	0.065772	0.064510	0.063205	0.061836		
20	0.060394	0.058875	0.057280	0.055609	0.053868		
21	0.052066	0.050215	0.048333	0.046438	0.044547		
22	0.042671	0.040818	0.038990	0.037187	0.035415		
23	0.033683	0.032004	0.030391	0.028854	0.027391		
24	0.025998	0.024666	0.023388	0.022164	0.021002		
25	0.019913	0.018906	0.017981	0.017128	0.016331		
26	0.015576	0.014856	0.014177	0.013550	0.012989		
27	0.012496						
28	1.000000	0.998486	0.994139	0.986870	0.976794		MAGNE
29	0.963975	0.948527	0.930586	0.910294	0.887824		
30	0.863348	0.837063	0.809177	0.779891	0.749428		
31	0.718007	0.685849	0.653170	0.620182	0.587093		
32	0.554100	0.521397	0.489158	0.457544	0.426712		
33	0.396795	0.367920	0.340184	0.313682	0.288490		
34	0.264668	0.242263	0.221307	0.201820	0.183806		
35	0.167258	0.152158	0.138473	0.126161	0.115165		
36	0.105417	0.096837	0.089334	0.082808	0.077149		
37	0.072248	0.067993	0.064278	0.061002	0.058077		
38	0.055427	0.052987	0.050705	0.048543	0.046470		
39	0.044465	0.042513	0.040607	0.038742	0.036916		
40	0.035129	0.033383	0.031682	0.030028	0.028426		
41	0.026878	0.025389	0.023961	0.022594	0.021291		
42	0.020050	0.018874	0.017760	0.016709	0.015719		
43	0.014790	0.013918	0.013102	0.012338	0.011623		
44	0.010954	0.010329	0.009746	0.009203	0.008696		
45	0.008223	0.007780	0.007366	0.006976	0.006609		
46	0.006265						

TABLE II. (continued).

51	20	4	800	
52	-27.320		0.0	22.950
53	-26.428		-1.653	25.225
54	-25.411		-3.306	27.500
55	-24.269		-4.959	29.775
56	-23.001		-6.612	32.050
57	-21.607		-8.265	34.325
58	-20.088		-9.918	36.600
59	-18.443		-11.571	38.875
60	-20.029		-15.925	34.521
61	-22.028		-18.722	29.033
62	-24.244		-19.685	22.950
63	-26.460		-18.722	16.867
64	-28.459		-15.925	11.379
65	-30.046		-11.571	7.025
66	-30.033		-9.918	9.300
67	-29.895		-8.265	11.575
68	-29.631		-6.612	13.850
69	-29.241		-4.959	16.125
70	-28.726		-3.306	18.400
71	-28.086		-1.653	20.675
72	31.5			
73	21	4	800	
74	-27.320		0.0	22.950
75	-27.257		2.812	22.950
76	-27.064		5.624	22.950
77	-26.755		8.436	22.950
78	-26.316		11.249	22.950
79	-25.751		14.061	22.950
80	-25.060		16.873	22.950
81	-24.244		19.685	22.950
82	-22.028		18.722	29.033
83	-20.029		15.925	34.521
84	-18.443		11.571	38.875
85	-17.424		6.083	41.672
86	-17.073		0.0	42.635
87	-17.424		-6.083	41.672
88	-18.443		-11.571	38.875
89	-20.088		-9.918	36.600
90	-21.607		-8.265	34.325
91	-23.001		-6.612	32.050
92	-24.269		-4.959	29.775
93	-25.411		-3.306	27.500
94	-26.428		-1.653	25.225
95	31.5			

TABLE II. (continued).

96	21	4	800	
97	-27.320		0.0	22.650
98	-28.086		-1.653	20.675
99	-28.726		-3.306	18.400
100	-29.241		-4.959	16.125
101	-29.631		-6.612	13.850
102	-29.895		-8.265	11.575
103	-30.033		-9.918	9.300
104	-30.046		-11.571	7.025
105	-31.064		-6.083	4.228
106	-31.415		0.0	3.265
107	-31.064		6.083	4.228
108	-30.046		11.571	7.025
109	-28.459		15.925	11.379
110	-26.460		18.722	16.867
111	-24.244		19.685	22.950
112	-25.060		16.873	22.950
113	-25.751		14.061	22.950
114	-26.316		11.249	22.950
115	-26.755		8.436	22.950
116	-27.064		5.624	22.950
117	-27.257		2.812	22.950
118	31.5			




FIG. 17a. PARABOLA H-PLANE PATTERN




FIG. 17b. PARABOLA E-PLANE PATTERN

only the circles are plotted. In all cases, the H-plane results agree almost perfectly with Rusch's calculations. The major deviation in the E-plane pattern occurs where Rusch predicts a beam shoulder and REFLECTR predicts a shallow null. This is probably due to the fact that such points on the beam are extremely dependent on the placement of the feed phase center. Rusch accounted for the difference in phase center between the E- and H-plane feed patterns, while we did not. Still, the E-plane patterns agree well with Rusch's computed pattern.

7. SEGMENTED SPHERICAL REFLECTOR TEST CASE



7.1 Description of the Antenna

In order to test the algorithm with measured data, a segmented spherical reflector antenna was constructed and tested by NASA at the Langley Research Center. The reflector surface consisted of 54 triangular-shaped planar facets, the vertices of which were located on a sphere with a 24-inch radius. The center of the surface was elevated 21 degrees above the negative x-axis. The boundary of the reflector was hexagonal in shape and measured 11.6 inches from point to point. The surface was fabricated from fiberglass molded onto a machined metal negative and sprayed with conducting paint. The feed antenna was a dual mode horn with a 16 dB amplitude taper at 23 degrees. Illuminating radiation was y-polarized at a frequency of 35 GHz. The center of the horn aperture was located at -12.52 inches on the negative x-axis and the feed antenna was elevated 40 degrees above horizontal. A diagram of the antenna appears in Figure 18.

7.2 Computation and Results

For computational purposes, the phase center of the feed horn was assumed to be $0.5(\lambda)$ or 0.169 inches behind the aperture. The aperture plane was placed at $x = -18.7$ inches. The triangular panels were represented by three perimeter points corresponding to their three vertex points as computed for the mold surface. Each panel was illuminated with 150 rays. Patterns were computed in the $\theta = 91^\circ$ plane with ϕ varied from 0 to 16 degrees and in the $\phi = 0^\circ$ plane with θ varied

54 PANELS



FEED -

DUAL MODE HORN
16 DB AMPLITUDE
TAPER AT 23°
Y POLARIZED
35 GHz

FIG. 18. FACETED SPHERICAL REFLECTOR

from 81 to 101 degrees. The incremental angle was 0.5 degrees in both cuts. The algorithm performed the computation in 6.3 minutes.

The results of the computation are compared with the measured patterns in Figures 19(a,b). The H-plane pattern compares extremely well with the measured results. The E-plane pattern exhibits a slightly wider beamwidth and a higher amplitude of the fourth sidelobe. The fourth sidelobe is a grating lobe caused by the periodicity of the reflector surface in the y-coordinate. It is present regardless of the polarization of the illuminating radiation. It should be noted that the program exactly predicts the location of the lobe as well as the fact that it is more steeply sloped on its inward edge. The level of the lobe, however, is about 6 dB lower than predicted.

One possible explanation for these discrepancies is that the vertex points used in the program were computed for the mold and not measured from the actual surface. The reflector may have sprung out somewhat in the xy plane after being removed from the mold, which would cause the reflector surface analyzed by the program to be different from that used in the pattern measurements. The exact location of the vertex points on the fiberglass reflector will be measured in the future and the computation will be repeated in hopes of obtaining better agreement in the E-plane.




FIG. 19a. SPHERE H-PLANE PATTERN




FIG. 19b. SPHERE E-PLANE PATTERN

8. CONCLUSIONS

An algorithm has been developed to compute radiation patterns for large segmented reflector antennas by extending an existing algorithm for smooth-edged, single-panel reflectors. Included in this algorithm are new techniques for aperture boundary definition, feed antenna description, output formatting, and reflector illumination. Equations for parabolic cylinders have been included so that the program can be used to analyze deployable umbrella reflector antennas.

The algorithm has been tested by comparing calculations with calculations made by Rusch [5], and with measured data, with the results presented in Sections 6 and 7.

Because of the discrepancies between the calculated and measured E-plane patterns of the faceted spherical reflector, it is recommended that the reflector surface be measured and the program rerun to see if the pattern might be better predicted. If the spherical test case does not achieve better results, a return to the theory underlying the program would be required to determine what electromagnetic effects are contributing to the error and how they might be included in the program.

LIST OF REFERENCES

1. Kauffman, J. F., W. F. Croswell, and L. J. Jowers. 1976. Analysis of the radiation patterns of reflector antennas. IEEE Transactions on Antennas and Propagation, Vol AP-24, No. 1.
2. Kauffman, J. F. 1976. Calculation of the radiation patterns of reflector antennas. North Carolina State University, Department of Electrical Engineering (Report).
3. Agrawal, Pradeep K. 1978. A computer program to calculate radiation properties of reflector antennas. NASA Technical Memorandum 78721, Langley Res. Ctr, Hampton, VA.
4. Agrawal, Pradeep K. 1979. A preliminary study of a very large space radiometric antenna. NASA Technical Memorandum 80047, Langley Res. Ctr., Hampton, VA.
5. Rusch, W. V. T. 1973. A study on a scanning multifrequency reflector antenna. Aerojet Electrosystems Company, Final IR&D Report, No. 8714-46-1.
6. Harrington, Roger F. 1961. Time-Harmonic Electromagnetic Fields. McGraw-Hill, Inc., The Maple Press Co., York, PA, pp. 95-116.

C-2

APPENDIX A

DEVELOPMENT OF THE APERTURE PLANE INTEGRALS

In a source-free region, the electric field at a point is given by

$$\vec{E} = -\nabla v - j\omega\vec{A} - \frac{1}{\epsilon}\nabla \times \vec{F} \quad (1)$$

where sinusoidal time variation is assumed.

Supplying the Lorentz gauge condition, this can be rewritten as

$$\vec{E} = \frac{\nabla \nabla \cdot \vec{A}}{j\omega\epsilon\mu} - j\omega\vec{A} - \frac{1}{\epsilon}\nabla \times \vec{F}. \quad (2)$$

By the equivalence principle [6], the tangential aperture electric field becomes a magnetic current source of strength $\vec{M} = -2(\mathbf{n} \times \vec{E})$. The radiated electric field strength is thus

$$\vec{E} = -\frac{1}{\epsilon}\nabla \times \vec{F} \quad (3)$$

where

$$\vec{F} = \frac{1}{4\pi} \int_{V'} \frac{\epsilon \vec{M} e^{-jkr}}{r} dV'. \quad (4)$$

The integration over the source volume is independent of the observation coordinates acted on by the ∇ operator. (3) and (4) are combined and the curl is taken of the integrand.

$$\vec{E} = -\frac{1}{4\pi} \int_{V'} \nabla \times \left(\frac{\vec{M} e^{-jkr}}{r} \right) dV'. \quad (5)$$

To expand the integrand, we make use of the vector identity

$$\nabla \times (\phi \vec{M}) = (\nabla \phi) \times \vec{M} + \phi (\nabla \times \vec{M}) \quad (6)$$

and note that \vec{M} is a function only of source coordinates, thus

$$\phi(\nabla \times \vec{M}) = 0$$

$$\begin{aligned} \nabla \phi &= \nabla \left(\frac{e^{-jkr}}{r} \right) \\ &= - \left\{ \hat{x} \frac{(x-x')}{r} + \hat{y} \frac{(y-y')}{r} + \hat{z} \frac{(z-z')}{r} \right\} \frac{e^{-jkr}}{r} \left(jk + \frac{1}{r} \right). \end{aligned} \quad (7)$$

If \vec{M} is represented as

$$\vec{M} = \hat{x}M_x + \hat{y}M_y + \hat{z}M_z, \quad (8)$$

the cross product is

$$\nabla \times \frac{\vec{M} e^{-jkr}}{r} = \left\{ \begin{aligned} &\left[-M_z \frac{(y-y')}{r} + M_y \frac{(z-z')}{r} \right] \hat{x} \\ &+ \left[-M_x \frac{(z-z')}{r} + M_z \frac{(x-x')}{r} \right] \hat{y} \\ &+ \left[-M_y \frac{(x-x')}{r} + M_x \frac{(y-y')}{r} \right] \hat{z} \end{aligned} \right\} \frac{e^{-jkr}}{r} \left[jk + \frac{1}{r} \right]. \quad (9)$$

We now make the far field approximations:

$$(A) \quad \left[jk + \frac{1}{r} \right] \cong [jk]$$

$$(B) \quad r \cong r_0 - \left[x' \sin\theta \cos\phi + y' \sin\theta \sin\phi + z' \cos\theta \right]$$

(See Figure A1)

$$\begin{aligned} (C) \quad x-x' &\cong x \\ y-y' &\cong y \\ z-z' &\cong z \end{aligned}$$

$$\begin{aligned} (D) \quad \frac{x}{r} &\cong \sin\theta \cos\phi \\ \frac{y}{r} &\cong \sin\theta \sin\phi \\ \frac{z}{r} &\cong \cos\theta \end{aligned}$$

Using these approximations in the integrand (9), we obtain




FIG. A1. FAR FIELD APPROXIMATION (B)

$$\nabla \times \frac{\vec{M} e^{-jkr}}{r} = \left\{ \begin{array}{l} \left[-M_z \sin\theta \sin\phi + M_y \cos\theta \right] \hat{x} \\ \left[-M_x \cos\theta + M_z \sin\theta \cos\phi \right] \hat{y} \\ \left[-M_y \sin\theta \cos\phi + M_x \sin\theta \sin\phi \right] \hat{z} \end{array} \right\} \quad (10)$$

$$\cdot \frac{jke^{-jkr_0}}{r_0} \exp\{ jk[x' \sin\theta \cos\phi + y' \sin\theta \sin\phi + z' \cos\theta] \}.$$

The electric field integral becomes

$$\vec{E} = \frac{-jke^{-jkr_0}}{4\pi r_0} \int_{V'} G \, dv' \quad (11)$$

where

$$G = \left\{ \begin{array}{l} \left[-M_z \sin\theta \sin\phi + M_y \cos\theta \right] \hat{x} \\ \left[-M_x \cos\theta + M_z \sin\theta \cos\phi \right] \hat{y} \\ \left[-M_y \sin\theta \cos\phi + M_x \sin\theta \sin\phi \right] \hat{z} \end{array} \right\} \quad (12)$$

$$\cdot \exp\{ jk[x' \sin\theta \cos\phi + y' \sin\theta \sin\phi + z' \cos\theta] \}.$$

The source is an aperture in the $y'z'$ plane. \vec{M} is given by

$$\begin{aligned} \vec{M} &= -2(\hat{n} \times \vec{E}) \\ &= 2[-\hat{x} \times (E_x \hat{x} + E_y \hat{y} + E_z \hat{z})] \\ &= -2\hat{z}E_y + 2\hat{y}E_z. \end{aligned}$$

Thus

$$\begin{aligned} M_x &= 0 \\ M_y &= 2E_z \\ M_z &= -2E_y \end{aligned} \quad (13)$$

and the electric field in the far field is given by

$$E_x = \frac{-j2ke^{-jkr_0}}{4\pi r_0} \int_{s'} [E_y \sin\theta \sin\phi + E_z \cos\theta] e^{jk[y' \sin\theta \sin\phi + z' \cos\theta]} dy' dz' \quad (14)$$

$$E_y = \frac{-j2ke^{-jkr_0}}{4\pi r_0} \int_{s'} [-E_y \sin\theta \cos\phi] e^{jk[y' \sin\theta \sin\phi + z' \cos\theta]} dy' dz' \quad (15)$$

$$E_z = \frac{-j2ke^{-jkr_0}}{4\pi r_0} \int_{s'} [-E_z \sin\theta \cos\phi] e^{jk[y' \sin\theta \sin\phi + z' \cos\theta]} dy' dz' \quad (16)$$

The vectors $\hat{\phi}$ and $\hat{\theta}$ in spherical coordinates are given by

$$\hat{\phi} = -\hat{x} \sin\phi + \hat{y} \cos\phi \quad (17)$$

$$\hat{\theta} = \hat{x} \cos\phi \cos\theta + \hat{y} \sin\phi \cos\theta - \hat{z} \sin\theta \quad (18)$$

$$E_\theta = \frac{-2ke^{-jkr_0}}{4\pi r_0} \int_{s'} U \exp\{jk[y' \sin\theta \sin\phi + z' \cos\theta]\} dy' dz' \quad (19)$$

where

$$\begin{aligned} U &= \cos\phi \cos\theta [E_y \sin\theta \sin\phi + E_z \cos\theta] + \sin\phi \cos\theta [-E_y \sin\theta \cos\phi] \\ &\quad + \sin\theta [E_z \sin\theta \cos\phi] \\ &= E_y (\sin\theta \sin\phi \cos\phi \cos\theta - \sin\theta \sin\phi \cos\phi \cos\theta) \\ &\quad + E_z (\cos^2\theta \cos\phi + \sin^2\theta \cos\phi) \end{aligned}$$

$$U = E_z \cos\phi \quad (20)$$

$$E_\phi = \frac{-j2ke^{-jkr_0}}{4\pi r_0} \int_{s'} V \exp\{jk[y' \sin\theta \sin\phi + z' \cos\theta]\} dy' dz' \quad (21)$$

where

$$\begin{aligned} V &= -\sin\phi [E_y \sin\theta \sin\phi + E_z \cos\theta] + \cos\phi [-E_y \sin\theta \cos\phi] \\ &= E_y (-\sin^2\phi \sin\theta - \cos^2\phi \sin\theta) - E_z \sin\phi \cos\theta \\ V &= -E_y \sin\theta - E_z \sin\phi \cos\theta \quad (22) \end{aligned}$$

We are interested in the relative magnitudes and phases of these field components. Furthermore, the relative phase of each component needs only to be preserved with respect to itself. Hence, the constant premultiplier may be dropped. The initial phase of the fields on the aperture is accounted for as ϕ in the phase term. We have

$$E_{\theta} = \iint_{\text{Aperture}} E_z \cos \phi \exp\{j[ky' \sin \theta \sin \phi + kz' \cos \theta - \phi]\} dy' dz' \quad (23)$$

$$E_{\phi} = \iint_{\text{Aperture}} [E_y \sin \theta + E_z \cos \theta \sin \phi] \exp\{j[ky' \sin \theta \sin \phi + kz' \cos \theta - \phi]\} dy' dz' \quad (24)$$

These integrals are evaluated numerically in the program.

APPENDIX B

DEVELOPMENT OF RAY BACKTRACING EQUATIONS

The object of tracing a ray back to the feed antenna is to express a point on the reflector surface by its angles θ' and ϕ' in the feed spherical coordinate system.

Let us define a new coordinate system which is parallel to the feed system but centered on the reference origin. These coordinates are denoted x'' , y'' , and z'' . The point on the reflector is expressed as a vector and rotated into the double-prime system by the inverse of the original rotation matrix.

$$\begin{bmatrix} A^{-1} \end{bmatrix} \begin{bmatrix} x \\ y \\ z \end{bmatrix} = \begin{bmatrix} x'' \\ y'' \\ z'' \end{bmatrix} = \vec{V}''$$

The translation to the feed system is accomplished by adding the translation vector $\vec{O'O}$. The x , y , and z components of this vector are called FEED(1), FEED(2), and FEED(3), respectively.

The distance R of the point from the feed origin is found by taking the magnitude of the vector $\vec{O'O} + \vec{V}'' = \vec{V}'$.

$$R = [(x')^2 + (y')^2 + (z')^2]^{1/2}$$

The angle θ' is found by

$$z' = R \cos \theta'$$

$$\theta' = \cos^{-1}\left(\frac{z'}{R}\right)$$

The angle ϕ' is found by

$$y' = R \sin \theta' \sin \phi'$$

$$\phi' = \sin^{-1} \left(\frac{y'}{R \sin \theta'} \right) .$$

R and $\sin \theta'$ will always be positive. If y' is positive, the desired ϕ' is less than π radians. The arcsine function will return an angle between 0 and $\pi/2$. If y' is zero, the desired ϕ' is π , but the arcsine returns 0. Finally, if y' is negative, the desired ϕ' is greater than π , and the arcsine returns a negative angle. It is concluded that if the returned angle is subtracted from π , the desired angle is obtained.

$$\phi' = \pi - \sin^{-1} \left(\frac{y'}{R \sin \theta'} \right)$$

APPENDIX C
ADDITION OF PARABOLIC CYLINDERS

Standard form of the parabolic cylinder equation shall be with the directrix in the xz plane, opening in the positive x direction. The focal point of the directrix lies on the coordinate origin. This surface is shown in Figure C1.




FIG. C1. STANDARD POSITION

The equation for the surface in this position is

$$z^2 = 4f(f + x) \quad (1)$$

where f is the focal length of the directrix. We now allow the surface to be rotated about the x -axis. Rotation is considered as positive when counter-clockwise if the observer looks in the negative- x direction. The angle of rotation is denoted by ψ . The coordinate system rotation is pictured in Figure C2.




FIG. C2. COORDINATE ROTATION

An arbitrary point P may be rotated from the unprimed to the primed coordinates by the relations

$$z' = z \cos \psi - y \sin \psi \quad (2)$$

$$y' = z \sin \psi + y \cos \psi \quad (3)$$

The parametric equations for a ray are

$$\begin{aligned} x &= RB_{11} - B_{12} \\ y &= RB_{21} - B_{22} \\ z &= RB_{31} - B_{32} \end{aligned} \quad (4)$$

First account for the rotation of the surface by substitution of z' in (2) for z in (1).

$$\begin{aligned} (z')^2 &= 4f(f + x) \\ (z \cos \psi - y \sin \psi)^2 &= 4f(f + x) \end{aligned}$$

$$z^2 \cos^2 \psi - 2yz \sin \psi \cos \psi + y^2 \sin^2 \psi = 4f(f + x). \quad (5)$$

Then substitute the parametric expressions for x , y , and z .

$$\begin{aligned} & (RB_{31} - R_{32})^2 \cos^2 \psi - 2(RB_{21} - B_{22})(RB_{31} - B_{32}) \cos \psi \sin \psi \\ & + (RB_{21} - B_{22})^2 \sin^2 \psi = 4f(f + RB_{11} - B_{12}) \\ & (R^2 B_{31}^2 - 2RB_{31}B_{32} + B_{32}^2) \cos^2 \psi - 2(R^2 B_{21}B_{31} - RB_{31}B_{22} - RB_{21}B_{32} + B_{22}B_{32}) \\ & \cos \psi \sin \psi + (R^2 B_{21}^2 - 2RB_{21}B_{32} + B_{22}^2) \sin^2 \psi - 4f^2 - 4fRB_{11} \\ & + 4fB_{12} = 0. \end{aligned} \quad (6)$$

The last equation (6) is of the form

$$AR^2 + BR + C = 0 \quad (7)$$

where

$$A = B_{31}^2 \cos^2 \psi - 2B_{21}B_{31} \cos \psi \sin \psi + B_{21}^2 \sin^2 \psi \quad (8)$$

$$\begin{aligned} B = & -2B_{31}B_{32} \cos^2 \psi + 2(B_{31}B_{22} + B_{21}B_{32}) \cos \psi \sin \psi \\ & - 2B_{21}B_{22} \sin^2 \psi - 4fB_{11} \end{aligned} \quad (9)$$

$$C = B_{32}^2 \cos^2 \psi - 2B_{22}B_{32} \cos \psi \sin \psi + B_{22}^2 \sin^2 \psi - 4f^2 + 4fB_{12} \quad (10)$$

Expressions (8), (9), and (10) are evaluated by the program and (7) is solved to find the intersection point of the ray with the surface.

Using (5), the inside normal of the surface may be found at any point by taking the negative of the gradient.

$$-\nabla \phi(x, y, z) = \vec{n}(x, y, z) \quad (11)$$

where

$$\phi(x,y,z) = z^2 \cos^2 \psi - 2yz \sin \psi \cos \psi + y^2 \sin^2 \psi - 4f(f+x) = 0$$

$$-\nabla \phi_x = 4f \quad (12)$$

$$-\nabla \phi_y = 2z \sin \psi \cos \psi - 2y \sin^2 \psi \quad (13)$$

$$-\nabla \phi_z = 2y \sin \psi \cos \psi - 2z \cos^2 \psi. \quad (14)$$

A unit vector is obtained by normalizing this vector. The common factor of 2 is removed from each component prior to normalization such that

$$\begin{aligned} \hat{n} = & \hat{x} \, 2f/\text{NMAG} + \hat{y}(z \sin \psi \cos \psi - y \sin^2 \psi)/\text{NMAG} \\ & + \hat{z}(y \sin \psi \cos \psi - z \cos^2 \psi)/\text{NMAG} \end{aligned}$$

where

$$\text{NMAG} = [4f^2 + (z \sin \psi \cos \psi - y \sin^2 \psi)^2 + (y \sin \psi \cos \psi - z \cos^2 \psi)^2]^{1/2}$$

APPENDIX D
LISTING OF THE CODE FOR REFLECTR

PROGRAM REFLECTR

```

      IMPLICIT REAL*8 (A-H,O-Z)
      REAL*8 MAJOR(5),MINOR(5)
      INTEGER SURFCE
      COMPLEX*16 ETOT(2,400),FIELDY(400),FIELDZ(400)
      COMMON/APRPRM/NPTPPL,NPERIM
      COMMON/CONTRL/NOPT(3),NLIST,IOPT,ILIST(100)
      COMMON/DIMENS/YDIM,ZDIM,YCT,ZCT
      COMMON/EXTENT/YMIN,YMAX,ZMIN,ZMAX
      COMMON/MATH/PI,PI2,PID2,DTOR,RTOD
      COMMON/PATRN/ETOT,AMINOR(3,5),AMAJOR(5),MINOR,MAJOR,NANGLE(5)
      COMMON/PARAMS/AORORF,BELLP,PSI,PLNPNT(3),PLNORM(3),FEED(3),
      .      ALPHA,BETA,GAMMA,XLAM,XC,SURFCE,NPNL,NPOINT
      DIMENSION P(5,2750),YFLD(75),ZFLD(75),PWER(75),PR(2,500)
      DATA DONE/5HDONE /,MLVL,NPARTS/0,7/
      DATA YLO,YHI,ZLO,ZHI/1.0D+10,-1.0D+10,1.0D+10,-1.0D+10/
      FDB(X)=20.0*DLOG10(X)
      PDB(X)=10.0*DLOG10(X)
      MAXPTS=2750
      CALL NPUT(P,NPAT)
      DG 400 I=1,NPNL
      CALL APRTUR(P,I)
      PRINT 777
      CALL QUANTZ(P,NPERIM,I)
      PRINT 778
      IF (IO(3,I).EQ.0) GO TO 80
      ISW=I
      IF (IOPT.EQ.1) ISW=-1
      CALL APRPLT(P,NPOINT,ISW)
      PRINT 780
80    CONTINUE
      IF (YMIN.LT.YLO) YLO=YMIN
      IF (YMAX.GT.YHI) YHI=YMAX
      IF (ZMIN.LT.ZLO) ZLO=ZMIN
      IF (ZMAX.GT.ZHI) ZHI=ZMAX
      DO 95 L=1,NPERIM
      PR(1,L+MLVL)=P(1,L+NPOINT)
95    PR(2,L+MLVL)=P(2,L+NPOINT)
      MLVL=MLVL+NPERIM+1
      PR(1,MLVL)=1.0D+40
      ISUM=0
      DO 200 K=1,NPAT
      CALL INTGRT(P,MAJOR(K),AMAJOR(K),AMINOR(1,K),FIELDY,FIELDZ)
      PRINT 779
      NANG=NANGLE(K)
      DO 150 L=1,NANG
      ETOT(1,L+ISUM)=ETOT(1,L+ISUM)+FIELDY(L)
150    ETOT(2,L+ISUM)=ETOT(2,L+ISUM)+FIELDZ(L)
200    ISUM=ISUM+NANG
400    CONTINUE
      PRINT 781
      IF (IOPT.EQ.1) GO TO 420
      IF (IO(2,1).EQ.0) GO TO 420
      YDIM=YHI-YLO
      ZDIM=ZHI-ZLO
      YCT=(YHI+YLO)/2.0
      ZCT=(ZHI+ZLO)/2.0
      CALL APRMAP(PR,NPNL,-1)
      PRINT 782
420    ISUM=0
      DO 770 I=1,NPAT
      NANG=NANGLE(I)

```

ORIGINAL PAGE 1
OF 100 PAGES

```

FMAXY=-1.0D+40
FMAXZ=-1.0D+40
DO 450 J=1,NANG
YFLD(J)=CDABS(ETOT(1,J+ISUM))
ZFLD(J)=CDABS(ETOT(2,J+ISUM))
FMAXY=DMAX1(FMAXY,YFLD(J))
450 FMAXZ=DMAX1(FMAXZ,ZFLD(J))
ISUM=ISUM+NANG
D=AMINOR(1,I)
FMYDB=-60.0D0
FMZDB=-60.0D0
PWRMDB=-60.0D0
PWR=FMAXZ*FMAXZ+FMAXY*FMAXY
IF (FMAXY.GT.1.0D-10) FMYDB=FDB(FMAXY)
IF (FMAXZ.GT.1.0D-10) FMZDB=FDB(FMAXZ)
IF (PWR.GT.1.0D-10) PWRMDB=PDB(PWR)
PRINT 600,MAJOR(I),AMAJOR(I),MINOR(I),(AMINOR(J,I),J=1,3)
600 FORMAT(1H1,///24X,
.      'TABLE OF ELECTRIC FIELD STRENGTHS (DB)',/'+',23X,
.      ' ',
.      '///19X,PRINCIPAL PLANE OF CUT IS ',A5,' = ',F8.3,' DEG'
.      '///19X,ANGLE ',A5,' FROM ',F8.3,' TO ',F8.3,' BY ',F6.3,' DEG')
PRINT 666, MINOR(I)
666 FORMAT(//13X,A5,4X,'DB(Z/Z)',4X,'DB(Y/Z)',4X,'DB(Z/Y)',5X,
.      'DB(Y/Y)',5X,'PWRDB',/)
DO 700 K=1,NANG
PWR(K)=PWRMDB-100.0D0
DBY =FMYDB -100.0D0
DBZ =FMZDB -100.0D0
PWR=ZFLD(K)*ZFLD(K)+YFLD(K)*YFLD(K)
IF (YFLD(K).GT.1.0D-15) DBY=FDB(YFLD(K))
IF (ZFLD(K).GT.1.0D-15) DBZ=FDB(ZFLD(K))
IF (PWR.GT.1.0D-30) PWR(K)=PDB(PWR)
IF (FMYDB.EQ.-60.0D0) DBY=-60.0D0
IF (FMZDB.EQ.-60.0D0) DBZ=-60.0D0
DBZZ=DBZ-FMZDB
DBYY=DBY-FMYDB
DBZY=DBZ-FMYDB
DBYZ=DBY-FMZDB
PWRDB=PWR(K)-PWRMDB
PRINT 690, D,DBZZ,DBYZ,DBZY,DBYY,PWRDB
690 FORMAT(10X,F9.3,5F11.5)
D=D+AMINOR(3,I)
YFLD(K)=DBY
ZFLD(K)=DBZ
CONTINUE
PRINT 750, FMAXZ,FMZDB,FMAXY,FMYDB
750 FORMAT(//15X,'MAXIMUM FIELD VALUES-'//15X,
.      '      20LOG(MAX(FIELD-Z))=20LOG('',1PE15.7,'')=',0PF12.7//15X,
.      '      20LOG(MAX(FIELD-Y))=20LOG('',1PE15.7,'')=',0PF12.7)
PRINT 755, NPARTS
755 FORMAT(//14X,
.      ' INTERPOLATION NUMBER USED FOR INTEGRATION IS.....',I5)
PRINT 765,MAJOR(I),AMAJOR(I)
765 FORMAT(1H1,///20X,'PRINCIPAL PLANE = ',A5,F7.3,' DEGREES')
CALL PLOT4(64H,NORMALIZED Z-COMPONENT OF SECONDARY PATTERN (DB)
.      ,FMZDB,ZFLD,NANG,MINOR(I),AMINOR(1,I))
PRINT 765,MAJOR(I),AMAJOR(I)
CALL PLOT4(64H,NORMALIZED Y-COMPONENT OF SECONDARY PATTERN (DB)
.      ,FMYDB,YFLD,NANG,MINOR(I),AMINOR(1,I))
PRINT 765,MAJOR(I),AMAJOR(I)
CALL PLOT4(64H,NORMALIZED POWER PATTERN (DB)
.      ,PWRMDB,PWR,NANG,MINOR(I),AMINOR(1,I))

```

```

770 CONTINUE
    IF (IO(4,1).EQ.1) WRITE(7,775)
    IF (IO(5,1).EQ.0) STOP
    REWIND 7
    CALL PTLIST
775 FORMAT(' -1234')
776 FORMAT(/' ----- FINISHED INPUT -----')
777 FORMAT(/' ----- FINISHED APRTUR -----')
778 FORMAT(/' ----- FINISHED QUANTZ -----')
779 FORMAT(/' ----- FINISHED INTGRT -----')
780 FORMAT(' ***** EXECUTED APRPLT *****')
781 FORMAT(/' ----- PATTERN COMPUTATIONS COMPLETE -----')
782 FORMAT(/' ***** EXECUTED APRMAP *****')
    STOP
    END

```

```

SUBROUTINE NPUT(P,NPAT)
IMPLICIT REAL*8 (A-H,O-Z)
REAL*8 MAJOR(5),MINOR(5)
COMPLEX*16 ETOT(2,400)
INTEGER SURFCE
COMMON/BLOCKG/YCBL,ZCBL,HFMABL,HFMIBL
COMMON/CONTRL/NOPT(3),NLIST,IOPT,ILIST(100)
COMMON/FEED/EP(91),ET(91),NP,NT
COMMON/MATH/PI,PI2,PID2,DTOR,RTOD
COMMON/PARAMS/AORORF,BELLP,PSI,PLNPNT(3),PLNORM(3),FEED(3),
    ALPHA,BETA,GAMMA,XLAM,XC,SURFCE,NPNL,NPOINT
COMMON/PATRN/ETOT,AMINOR(3,5),AMAJOR(5),MINOR,MAJOR,ANGLE(5)
DIMENSION P(5,2750),TITLE(40)
DATA DONE/5HDONE /
IOPT=0
READ 200, TITLE
READ(1,10) FEED,ALPHA,BETA,GAMMA,XLAM
10 FORMAT(7F10.4)
READ(1,20) SURFCE,NPNL,AORORF,BELLP,PSI,PLNPNT,PLNORM
20 FORMAT(I1,14X,I5,3F10.4/6F10.4)
READ(1,30) XC,YCBL,ZCBL,HFMABL,HFMIBL
30 FORMAT(5F10.4)
READ(1,40) EP
READ(4,40) ET
40 FORMAT(5F15.6)
IF (NPNL.LE.0) READ(1,50) ((P(I,J),I=1,3),J=1,4)
50 FORMAT(3F10.4)
READ(1,60) NOPT,NLIST
60 FORMAT(3I1,2X,I5)
IF (NOPT(1).EQ.1.OR.NOPT(2).EQ.1) READ(1,70) (ILIST(I),I=1,NLIST)
70 FORMAT(16I5)
ISUM=0
NPAT=1
77 READ(1,80) MAJOR(NPAT),AMAJOR(NPAT),MINOR(NPAT),(AMINOR(I,NPAT),
    I=1,3)
80 FORMAT(A5,5X,F10.4,A5,5X,3F10.4)
IF (MAJOR(NPAT).EQ.DONE) GO TO 98
ANGLE(NPAT)=(AMINOR(2,NPAT)-AMINOR(1,NPAT))/AMINOR(3,NPAT)+1.5
IF (ANGLE(NPAT).GT.75) GO TO 88
ISUM=ISUM+ANGLE(NPAT)
NPAT=NPAT+1
IF (NPAT.LT.6) GO TO 77
PRINT 573
STOP

```

```

83  PRINT 574
    STOP
98  IF (ISUM.LE.400) GO TO 105
    PRINT 575,ISUM
    STOP
105  NPAT=NPAT-1
    DO 108 L=1,ISUM
    ETOT(1,L)=(0.0D0,0.0D0)
108  ETOT(2,L)=(0.0D0,0.0D0)
    GO TO (120,130,140,150,160),SURFCE
120  PRINT 578, TITLE,XLAM,FEED,ALPHA,BETA,GAMMA,PLNPNT,PLNORM
    GO TO 170
130  PRINT 579, TITLE,XLAM,FEED,ALPHA,BETA,GAMMA,AORORF,BELLP
    GO TO 170
140  PRINT 580, TITLE,XLAM,FEED,ALPHA,BETA,GAMMA,AORORF
    GO TO 170
150  PRINT 581, TITLE,XLAM,FEED,ALPHA,BETA,GAMMA,AORORF
    GO TO 170
160  PRINT 582, TITLE,XLAM,FEED,ALPHA,BETA,GAMMA,AORORF,PSI
170  IF (NPNL.GE.1) GO TO 180
    IOPT=1
    NPNL=1
    PRINT 583, ((P(I,J),I=1,3),J=1,4)
180  PRINT 584, XC,YCBL,ZCBL,HFMABL,HFMIBL,NPNL
    PRINT 586
    PRINT 587
    PRINT 590,EP
    PRINT 586
    PRINT 588
    PRINT 590,ET
    PRINT 576,NPAT
    DO 190 M=1,NPAT
190  PRINT 577, MAJOR(M),AMAJOR(M),MINOR(M),(AMINOR(KK,M),KK=1,3)
200  FORMAT(10A8)
573  FORMAT(' ***** ERROR - MORE THAN 5 PATTERN ',
.      'CALCULATIONS REQUESTED *****')
574  FORMAT(' ***** ERROR - MORE THAN 75 ANGLES IN',
.      'ONE PATTERN REQUEST *****')
575  FORMAT(' ***** ERROR - REQUESTED',I5,' ANGLES TO BE ',
.      'CALCULATED EXCEEDS AVAIL. STORAGE *****')
576  FORMAT(//
.      'NUMBER OF PATTERN GROUPS REQUESTED.....',I5/)
577  FORMAT(5X,A5,' =',F10.4,10X,A5,' FROM',F10.4,' TO',F10.4,' BY',
.      F10.4)
578  FORMAT(1H1,////,13X,'PLANAR REFLECTOR FAR FIELD RADIATION' //
.      'PATTERN CALCULATION'////' ',10A8/' ',10A8
.      /' ',10A8/' ',10A8//
.      'INPUT PARAMETERS- ',//
.      'WAVELENGTH OF ELECTRIC FIELD.....',F9.4/
.      'LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....',3F8.3
.      /' FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....',3F8.3
.      /' A POINT ON THE REFLECTOR SURFACE (X,Y,Z).....',3F8.3
.      /' COMPONENTS OF UNIT NORMAL TO SUFACE (X,Y,Z).....',3F8.3
.      /)
579  FORMAT(1H1,////,11X,'ELLIPTICAL REFLECTOR FAR FIELD RADIATION' //
.      'PATTERN CALCULATION'////' ',10A8/' ',10A8
.      /' ',10A8/' ',10A8//
.      'INPUT PARAMETERS- ',//
.      'WAVELENGTH OF ELECTRIC FIELD.....',F9.4/
.      'LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....',3F8.3
.      /' FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....',3F8.3
.      /' MAJOR AXIS OF THE ELLIPTICAL REFLECTOR.....',F78.3
.      /' MINOR AXIS OF THE ELLIPTICAL REFLECTOR.....',F8.3)

```



```

580 FORMAT(1H1,////,11X,'SPHERICAL REFLECTOR FAR FIELD RADIATION' //
      .    .   /' ',10A8/' ',10A8//
      .    .   INPUT PARAMETERS-
      .    .     WAVELENGTH OF ELECTRIC FIELD.....F9.4/
      .    .     LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....F8.3
      .    . /'   FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....F8.3
      .    . /'   RADIUS OF REFLECTOR SPHERE.....F8.3)
581 FORMAT(1H1,////,11X,'PARABOLIC REFLECTOR FAR FIELD RADIATION' //
      .    .   /' ',10A8/' ',10A8//
      .    .   INPUT PARAMETERS-
      .    .     WAVELENGTH OF ELECTRIC FIELD.....F9.4/
      .    .     LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....F8.3
      .    . /'   FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....F8.3
      .    . /'   FOCAL LENGTH OF THE REFLECTOR.....F8.3)
582 FORMAT(1H1,////,11X,'PARABOLIC CYLINDRICAL REFLECTOR FAR FIELD' //
      .    .   /' ',10A8/' ',10A8/' ',10A8//
      .    .   INPUT PARAMETERS-
      .    .     WAVELENGTH OF ELECTRIC FIELD.....F9.4/
      .    .     LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....F8.3
      .    . /'   FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....F8.3
      .    . /'   FOCAL LENGTH OF PARABOLIC CYLINDER.....F8.3/
      .    . /'   ANGLE OF ROTATION ABOUT X-AXIS (PSI).....F8.3)
583 FORMAT(
      .    . ***** PROGRAM IN SINGLE PANEL MODE *****
      .    . /' MINIMUM-Y POINT ON THE REFLECTOR (X,Y,Z).....F8.3
      .    . /' MAXIMUM-Y POINT ON THE REFLECTOR (X,Y,Z).....F8.3
      .    . /' MINIMUM-Z POINT ON THE REFLECTOR (X,Y,Z).....F8.3
      .    . /' MAXIMUM-Z POINT ON THE REFLECTOR (X,Y,Z).....F8.3
      .    . )
584 FORMAT(
      .    . APERTURE PLANE LOCATION (XC).....F7.2/
      .    . FEED SHADOW CENTER COORDINATES IN APERTURE PL.....F7.2
      .    . /' HALF MAJOR AXIS OF FEED SHADOW.....F7.2/
      .    . /' HALF MINOR AXIS OF FEED SHADOW.....F7.2/
      .    . NUMBER OF PANELS IN REFLECTOR.....I6/)
586 FORMAT('/' PATTERN OF FEED IN ONE DEG INCREMENTS OFF-AXIS-'/)
587 FORMAT(' THETA=0 PLANE -'/)
588 FORMAT(' PHI=180 PLANE -'/)
590 FORMAT(2X,5F14.6)
      PI=DARCOS(-1.0D0)
      PI2=PI+PI
      PID2=0.5*PI
      DTOR=PI/180.
      RTOD=180./PI
      RETURN
      END
```

```

SUBROUTINE APRTUR(P,ICALL)
IMPLICIT REAL*8 (A-H,O-Z)
REAL*8 NHAT(3),NMAG
INTEGER SURFCE
COMMON/APRPRM/NPTPPL,NPERIM
COMMON/CONTRL/NOPT(3),NLIST,IOPT,ILIST(100)
COMMON/FEED/EP(91),ET(91),NP,NT
COMMON/MATH/PI,PI2,PID2,DTOR,RTOD
COMMON/PARAMS/AORORF,BELP,PSI,PLNPNT(3),PLNORM(3),FEED(3),
      ALPHA,BETA,GAMMA,XLAM,XC,SURFCE,NPNL,NPOINT

```

```

      DIMENSION A(3,3),AINV(3,3),B(3,2),BB(3,2),C(3),EI(3),ER(3),
      P(5,2750),SR(3),X(3)
      IF (ICALL.GT.1) GO TO 50
      ALPHAR=ALPHA*DTOR
      BETAR=BETA*DTOR
      GAMMAR=GAMMA*DTOR
      A(1,1)=DCOS(ALPHAR)*DCOS(GAMMAR)-DSIN(ALPHAR)*DSIN(BETAR)*
      . DSIN(GAMMAR)
      A(1,2)=DSIN(ALPHAR)*DCOS(GAMMAR)+DCOS(ALPHAR)*DSIN(BETAR)*
      . DSIN(GAMMAR)
      A(1,3)=-DCOS(BETAR)*DSIN(GAMMAR)
      A(2,1)=-DSIN(ALPHAR)*DCOS(BETAR)
      A(2,2)=DCOS(ALPHAR)*DCOS(BETAR)
      A(2,3)=DSIN(BETAR)
      A(3,1)=DCOS(ALPHAR)*DSIN(GAMMAR)+DSIN(ALPHAR)*DSIN(BETAR)*
      . DCOS(GAMMAR)
      A(3,2)=DSIN(ALPHAR)*DSIN(GAMMAR)-DCOS(ALPHAR)*DSIN(BETAR)*
      . DCOS(GAMMAR)
      A(3,3)=DCOS(BETAR)*DCOS(GAMMAR)
      DO 40 I=1,3
      DO 40 J=1,3
40    AINV(I,J)=A(J,I)
      NPERIM=4
      NPTPPL=2250
50    IF (IOPT.EQ.0) CALL APRIN(P,ICALL)
      TMAX=0.0D0
      TMIN=PI
      PMIN=PI+PID2
      PMAX=PID2
      DO 65 I=1,NPERIM
      DO 60 J=1,3
60    X(J)=AINV(J,1)*P(1,I)+AINV(J,2)*P(2,I)+AINV(J,3)*P(3,I)
      R=DSQRT((X(1)+FEED(1))**2+(X(2)+FEED(2))**2+(X(3)+FEED(3))**2)
      P(1,I)=DARCOS((X(3)+FEED(3))/R)
      SINTHT=DSIN(P(1,I))
      IF (SINTHT.LT.1.D-10) SINTHT=1.D-10
      P(2,I)=PI-DARSIN((X(2)+FEED(2))/(R*SINTHT))
      IF (P(1,I).GT.TMAX) TMAX=P(1,I)
      IF (P(1,I).LT.TMIN) TMIN=P(1,I)
      IF (P(2,I).GT.PMAX) PMAX=P(2,I)
      IF (P(2,I).LT.PMIN) PMIN=P(2,I)
65    CONTINUE
      DELP=PMAX-PMIN
      DELT=TMAX-TMIN
      NP=DSQRT(DELP*DFLOAT(NPTPPL)/DELT)+1.0
      NP=((NP-1)/2)*2+1
      ANGINC=DELP/(DFLOAT(NP)-2.6)
      NTD2=DELT/(2.0*ANGINC)+1.0
      NT=2*NTD2+1
      PMIN=PMIN-0.8*ANGINC
      PMAX=PMAX+0.8*ANGINC
      TCT=(TMAX+TMIN)/2.0
      TMIN=TCT-DFLOAT(NTD2)*ANGINC
      TMAX=TCT+DFLOAT(NTD2)*ANGINC
      DO 95 J=1,NT
      DO 95 K=1,NP
95    P(1,NPERIM+(J-1)*NP+K)=TMIN+(J-1)*ANGINC
      P(2,NPERIM+(J-1)*NP+K)=PMIN+(K-1)*ANGINC
      NTNP=NT*NP
      NPOINT=NPERIM+NTNP
      TMIN=TMIN*RTOD
      TMAX=TMAX*RTOD
      PMIN=PMIN*RTOD

```

```

      PMAX=PMAX*RTOD
      ANGINC=ANGINC*RTOD
      IF (IO(1,ICALL).EQ.1) PRINT 107, TMIN,TMAX,PMIN,PMAX,
        ANGINC,NTNP,NPOINT
107  FORMAT(// ' ILLUMINATION DATA-'//
      . ' THETA ILLUMINATION FROM.....',F9.3,' TO
      . ' F9.3/
      . ' PHI ILLUMINATION FROM.....',F9.3,' TO
      . ' F9.3/
      . ' INCREMENTAL ANGLE (DEG).....',F7.4/
      . ' THEREFORE TOTAL NUMBER OF GENERATED RAYS.....',I7 /
      . ' TOTAL NUMBER OF APERTURE PLANE POINTS.....',I7 )
      IF (SURFCE.LT.5) GO TO 114
      SNPSI=DSIN (PSI*DTOR)
      CSPSI=DCOS (PSI*DTOR)
114  CALL FILL(P,NPOINT)
      DO 600 I=1,NPOINT
      SINP=DSIN (P(2,I))
      COSP=DCOS (P(2,I))
      SINT=DSIN (P(1,I))
      COST=DCOS (P(1,I))
      BB(1,1)=SINT*COSP
      BB(2,1)=SINT*SINP
      BB(3,1)=COST
      BB(1,2)=+FEED(1)
      BB(2,2)=+FEED(2)
      BB(3,2)=+FEED(3)
      CALL MULT32(B,A,BB)
      GO TO (120,130,140,150,160),SURFCE
120  AR=0.0
      BR=B(1,1)*PLNORM(1)+B(2,1)*PLNORM(2)+B(3,1)*PLNORM(3)
      CR=- (B(1,2)+PLNPNT(1))*PLNORM(1)
      . - (B(2,2)+PLNPNT(2))*PLNORM(2)
      . - (B(3,2)+PLNPNT(3))*PLNORM(3)
      GO TO 180
130  AR=B(1,1)**2/AORORF**2+(B(2,1)**2+B(3,1)**2)/BELLP**2
      BR=-2.0*(B(1,1)*B(1,2)/AORORF**2+(B(2,1)*B(2,2)+B(3,1)*B(3,2))/
      . BELLP**2)
      CR=B(1,2)**2/AORORF**2+(B(2,2)**2+B(3,2)**2)/BELLP**2-1.0
      GO TO 180
140  AR=B(1,1)*B(1,1)+B(2,1)*B(2,1)+B(3,1)*B(3,1)
      BR=-2.*(B(1,1)*B(1,2)+B(2,1)*B(2,2)+B(3,1)*B(3,2))
      CR=B(1,2)*B(1,2)+B(2,2)*B(2,2)+B(3,2)*B(3,2)-AORORF*AORORF
      GO TO 180
150  AR=B(2,1)*B(2,1)+B(3,1)*B(3,1)
      BR=-2.0*(B(2,1)*B(2,2)+B(3,1)*B(3,2)+2.0*AORORF*B(1,1))
      CR=B(2,2)*B(2,2)+B(3,2)*B(3,2)+4.0*AORORF*B(1,2)-4.0*AORORF**2
      GO TO 180
160  AR=B(3,1)*B(3,1)*CSPSI*CSPSI-2.0*B(2,1)*B(3,1)*CSPSI*SNPSI
      . +B(2,1)*B(2,1)*SNPSI*SNPSI
      BR=-2.0*(B(3,1)*B(3,2)*CSPSI*CSPSI
      . - (B(3,1)*B(2,2)+B(2,1)*B(3,2))*CSPSI*SNPSI
      . +B(2,1)*B(2,2)*SNPSI*SNPSI+2.0*AORORF*B(1,1))
      CR=B(3,2)*B(3,2)*CSPSI*CSPSI-2.0*B(2,2)*B(3,2)*CSPSI*SNPSI
      . +B(2,2)*B(2,2)*SNPSI*SNPSI+4.0*AORORF*(B(1,2)-AORORF)
180  IF (AR.LT.1.0D-10) R=-CR/BR
      IF (AR.LT.1.0D-10) GO TO 189
      R=(-BR+DSQRT(BR*BR-4.*AR*CR))/(AR+AR)
189  CONTINUE
      XO=B(1,1)*R-B(1,2)
      YO=B(2,1)*R-B(2,2)
      ZO=B(3,1)*R-B(3,2)
219  GO TO (220,230,240,250,260),SURFCE

```

```

220  NHAT(1)=PLNORM(1)
      NHAT(2)=PLNORM(2)
      NHAT(3)=PLNORM(3)
      GO TO 288
230  NHAT(1)=-X0*BELLP**2/DSQRT(X0**2*BELLP**4+(Y0**2+Z0**2)*AORORF**4)
      NHAT(2)=-Y0*AORORF**2/DSQRT(X0**2*BELLP**4+(Y0**2+Z0**2)*
      . AORORF**4)
      NHAT(3)=-Z0*AORORF**2/DSQRT(X0**2*BELLP**4+(Y0**2+Z0**2)*
      . AORORF**4)
      GO TO 288
240  NHAT(1)=-X0/AORORF
      NHAT(2)=-Y0/AORORF
      NHAT(3)=-Z0/AORORF
      GO TO 288
250  NHAT(1)=2.0*AORORF/DSQRT(4.0*AORORF**2+Y0**2+Z0**2)
      NHAT(2)=      -Y0/DSQRT(4.0*AORORF**2+Y0**2+Z0**2)
      NHAT(3)=      -Z0/DSQRT(4.0*AORORF**2+Y0**2+Z0**2)
      GO TO 288
260  NMAG=DSQRT(4.0*AORORF*AORORF+(Z0*CSPSI*SNPSI-Y0*SNPSI*SNPSI)**2
      . +(Y0*SNPSI*CSPSI-Z0*CSPSI*CSPSI)**2)
      NHAT(1)=2.0*AORORF/NMAG
      NHAT(2)=SNPSI*(Z0*CSPSI-Y0*SNPSI)/NMAG
      NHAT(3)=CSPSI*(Y0*SNPSI-Z0*CSPSI)/NMAG
288  SCALAR=2.0*(B(1,1)*NHAT(1)+B(2,1)*NHAT(2)+B(3,1)*NHAT(3))
      DO 295  L=1,3
295  SR(L)=B(L,1)-SCALAR*NHAT(L)
      ETI=P(3,1)/R
      EPI=P(4,1)/R
      C(1)=COST*COSP*ETI-SINP*EPI
      C(2)=COST*SINP*ETI+COSP*EPI
      C(3)=-SINT*ETI
      DO 400  N=1,3
      EI(N)=0.0
      DO 400  M=1,3
400  EI(N)=EI(N)+A(N,M)*C(M)
      SCALAR=2.0*(EI(1)*NHAT(1)+EI(2)*NHAT(2)+EI(3)*NHAT(3))
      DO 500  K=1,3
500  ER(K)=SCALAR*NHAT(K)-EI(K)
      Y=Y0+(XC-X0)*SR(2)/SR(1)
      Z=Z0+(XC-X0)*SR(3)/SR(1)
      D=DSQRT((XC-X0)*(XC-X0)+(Y-Y0)*(Y-Y0)+(Z-Z0)*(Z-Z0))
      PHASE=PI2*(R+D)/XLAM+P(5,1)
      P(1,1)=Y
      P(2,1)=Z
      P(3,1)=ER(2)
      P(4,1)=ER(3)
      P(5,1)=PHASE
600  CONTINUE
      RETURN
      END

```

```

SUBROUTINE APRIN(P,ICALL)
  IMPLICIT REAL*8 (A-H,O-Z)
  INTEGER SURFCE
  COMMON/APRPRM/NPTPPL,NPERIM
  COMMON/CONTRL/NOPT(3),NLIST,IOPT,ILIST(100)
  COMMON/PARAMS/AORORF,BELLP,PSI,PLNPNT(3),PLNORM(3),FEED(3),
  . ALPHA,BETA,GAMMA,XLAM,XC,SURFCE,NPNL,NPOINT
  DIMENSION P(5,2750)
  READ(1,10) NPERIM,SURFCE,NPTPPL

```

```

10  FORMAT(3I5)
    IF (NPERIM.LE.2)          GO TO 250
    IF (NPERIM.GT.40)         GO TO 260
    IF (SURFCE.GT.5)          GO TO 250
    IF (NPTPPL.GT.2500)       GO TO 270
    IF ((NPERIM*SURFCE).LE.0) GO TO 250
    READ(1,20) ((P(I,J),I=1,3),J=1,NPERIM)
20  FORMAT(3F10.4)
28  GO TO (30,40,50,50,60),SURFCE
30  READ(1,35) PLNPNT,PLNORM
35  FORMAT(6F10.4)
    GO TO 100
40  READ(1,45) AORORF,BELLP
45  FORMAT(2F10.4)
    GO TO 100
50  READ(1,55) AORORF
55  FORMAT(F10.4)
    GO TO 100
60  READ(1,65) AORORF,PSI
65  FORMAT(2F10.4)
100 CONTINUE
199 IF (IO(1,ICALL).EQ.0) RETURN
    PRINT 200, ICALL
200 FORMAT('1',35X,'REFLECTOR PANEL NUMBER',I4)
    GO TO (320,330,340,350,360),SURFCE
250 PRINT 252,ICALL
252 FORMAT(///' ***** INPUT ERROR ON CARD ONE FOR PANEL NUMBER',
        .   I4,' EXECUTION TERMINATING *****')
    STOP
260 PRINT 262,ICALL
262 FORMAT(///' ***** STORAGE DOES NOT EXIST FOR NUMBER OF',
        .   ' PERIMETER POINTS SPECIFIED - PANEL',I4,' *****')
    STOP
270 PRINT 272,ICALL
272 FORMAT(///' ***** MAXIMUM ILLUMINATION REQUEST IS 2500',
        .   ' RAYS - PANEL',I4,' *****'////)
    NPTPPL=2500
    GO TO 28
320 PRINT 401,PLNPNT,PLNORM,NPERIM
    RETURN
330 PRINT 402,AORORF,BELLP,NPERIM
    RETURN
340 PRINT 403,AORORF,NPERIM
    RETURN
350 PRINT 404,AORORF,NPERIM
    RETURN
360 PRINT 405,AORORF,PSI,NPERIM
    RETURN
401 FORMAT(///10X,'PANEL IS A PLANAR SURFACE',///
        .   ' A POINT ON THE REFLECTOR SURFACE (X,Y,Z).....',3F7.2
        .   ' COMPONENTS OF UNIT NORMAL TO SURFACE (X,Y,Z).....',3F7.2
        .   ' NUMBER OF USER-SUPPLIED EDGE POINTS.....',I7)
402 FORMAT(///10X,'PANEL IS AN ELLIPTICAL SECTION',///
        .   ' MAJOR AXIS OF ELLIPTICAL REFLECTOR.....',F7.2/
        .   ' MINOR AXIS OF ELLIPTICAL REFLECTOR.....',F7.2/
        .   ' NUMBER OF USER-SUPPLIED EDGE POINTS.....',I7)
403 FORMAT(///10X,'PANEL IS A SPHERICAL SECTION'///
        .   ' RADIUS OF REFLECTOR SPHERE.....',F7.2/
        .   ' NUMBER OF USER-SUPPLIED EDGE POINTS.....',I7)
404 FORMAT(///10X,'PANEL IS A PARABOLIC SECTION',///
        .   ' FOCAL LENGTH OF THE PARABOLA.....',F7.2/
        .   ' NUMBER OF USER-SUPPLIED EDGE POINTS.....',I7)
405 FORMAT(///10X,'PANEL IS SECTION OF A PARABOLIC CYLINDER'///

```

```

.      : FOCAL LENGTH OF THE PARABOLA.....',F8.3/
.      : FOCAL LINE ROTATION FROM Y-AXIS (PSI).....',F8.3/
.      : NUMBER OF USER-SUPPLIED EDGE POINTS.....',I7)
END

```

```

SUBROUTINE FILL(P,NPT)
IMPLICIT REAL*8 (A-H,O-Z)
COMMON/FEED/EP(91),ET(91),NP,NT
COMMON/MATH/PI,PI2,PID2,DTOR,RTOD
DIMENSION P(5,NPT)
DO 100 I=1,NPT
  PROJX=DSIN(P(1,I))*DCOS(P(2,I))
  PROJY=0.0D0
  IF (DABS(P(2,I)-PI).GT.1.0D-5)
    .PROJY=DCOS(DATAN(DCOS(P(1,I))/DSIN(P(1,I))/DSIN(P(2,I))))
  ANGLX=DARCOS(DABS(PROJX))*RTOD
  LO=ANGLX+1.0D0
  IHI=LO+1
  PPFLD=(ANGLX-DFLOAT(LO-1))*(EP(IHI)-EP(LO))+EP(LO)
  TPFLD=(ANGLX-DFLOAT(LO-1))*(ET(IHI)-ET(LO))+ET(LO)
  COSE2=PROJX*PROJY
  SINE2=1.0D0-COSE2
  P(3,I)=0.0D0
  P(4,I)=PPFLD*TPFLD/(DSQRT(TPFLD*TPFLD*COSE2+
    .PPFLD*PPFLD*SINE2))
  P(5,I)=0.0D0
100 CONTINUE
RETURN
END

```

```

SUBROUTINE QUANTZ(P,NPERIM,ICALL)
IMPLICIT REAL*8 (A-H,O-Z)
INTEGER SURFCE
COMMON/BLOCKG/YCBL,ZCBL,HFMABL,HFMIBL
COMMON/CONTRL/NOPT(3),NLIST,IOPT,ILIST(100)
COMMON/DIMENS/YDIM,ZDIM,YCT,ZCT
COMMON/EXTENT/YMIN,YMAX,ZMIN,ZMAX
COMMON/FEED/EP(91),ET(91),NP,NT
COMMON/PARAMS/AORCAF,BELLP,PSI,PLNPNT(3),PLNORM(3),FEED(3),
  .ALPHA,BETA,GAMMA,XLAM,XC,SURFCE,NPNL,NPOINT
DIMENSION P(5,2750),PINT(5),POLD(5),PBLK(5),PR5(5,41),Z(2,101)
NBARS=NP-2
YMIN=1.0D+10
YMAX=-1.0D+10
ZMIN=1.0D+10
ZMAX=-1.0D+10
NOS=2*NBARS
CALL SETM(1.0D+20,Z,NOS)
DO 20 I=1,NPERIM
  IF (P(1,I).GT.YMAX) YMAX=P(1,I)
  IF (P(1,I).LT.YMIN) YMIN=P(1,I)
  IF (P(2,I).GT.ZMAX) ZMAX=P(2,I)
  IF (P(2,I).LT.ZMIN) ZMIN=P(2,I)
20 CALL MOVEM(P(1,I),PR5(1,I),5)
YDIM=YMAX-YMIN
YCT=(YMAX+YMIN)/2.
ZDIM=ZMAX-ZMIN

```

ORIGINAL PAGE IS
POOR QUALITY

```

ZCT=(ZMAX+ZMIN)/2.
GRID=(YMAX-YMIN)/(DFLOAT(NBARS)-0.6)
GRIDLO=YMIN+GRID/5.000
GRIDHI=YMAX-GRID/5.000
31  IBGN=NPBARS+1
    NDEX=NPBARS
    DO 100 I=IBGN,NPOINT
      IF (P(1,I).GT.YMAX) GO TO 98
      IF (P(1,I).LT.YMIN) GO TO 98
      NGRID=(P(1,I)-GRIDLO)/GRID+0.5
      P(1,I)=GRIDLO+DFLOAT(NGRID)*GRID
      CALL MOVEM(P(1,I),P(1,I-NDEX),5)
      GO TO 100
98  NDEX=NDEX+1
100  CONTINUE
      NPOINT=NPOINT-NDEX
      CALL PTSORT(P,5,NPOINT)
      IF (IOPT.EQ.1) GO TO 422
      CALL MOVEM(P(1,1),P(1,NPBARS+1),5)
      KDEX=2
      Y2=PR5(1,1)
      Z2=PR5(2,1)
200  Y1=PR5(1,KDEX)
      Z1=PR5(2,KDEX)
      IF (DABS(Y1-Y2).LT.1.0D-5) GO TO 400
      SLOPE=(Z1-Z2)/(Y1-Y2)
      Z=Z2-SLOPE*Y2
      IF (Y1-Y2) 220,230,230
220  YHI=Y2
      YLO=Y1
      GO TO 240
230  YHI=Y1
      YLO=Y2
240  INDEX=(YLO-GRIDLO)/GRID+1.0
250  INDEX=INDEX+1
      YQ=GRIDLO+DFLOAT(INDEX-1)*GRID
      IF (YQ.GT.YHI) GO TO 400
      ILOAD=1
      ZEE=SLOPE*YQ+B
      IF (Z(1,INDEX).LT.1.0D+10) ILOAD=2
      Z(ILOAD,INDEX)=ZEE
      GO TO 250
400  Y2=Y1
      Z2=Z1
      KDEX=KDEX+1
      IF (KDEX.LE.NPBARS+1) GO TO 200
      DO 420 I=1,NBARS
        IF ((Z(1,I)+Z(2,I)).GT.1.0D+10) GO TO 1005
        IF (Z(2,I)-Z(1,I)) 410,420,420
110  Z2=Z(2,I)
      Z(2,I)=Z(1,I)
      Z(1,I)=Z2
420  CONTINUE
      GO TO 444
422  HPMAEX=YDIM/2.000
      HPMEIX=ZDIM/2.000
      DO 430 I=1,NBARS
        Y=GRIDLO+DFLOAT(I-1)*GRID
        ZZ=HPMEIX*DSORT(1.0D0-((Y-YCT)/HPMAEX)**2)
        Z(1,I)=-ZZ+ZCT
        Z(2,I)= ZZ+ZCT
430  CONTINUE
444  L=0

```

```

N=1
CALL SETM(0.0,PBLK,5)
YQ=P(1,1)
IDEX=DINT((YQ-GRIDLO)/GRID+1.001)
DO 900 I=1,NPOINT
IF (P(1,I).EQ.YQ) GO TO 480
IF (L.GT.2) GO TO 470
N=N-L
470 L=0
YQ=P(1,I)
IDEX=DINT((YQ-GRIDLO)/GRID+1.001)
480 PBLK(1)=P(1,I)
PBLK(2)=P(2,I)
TEST=-1.0
IF (P(2,I).EQ.Z(1,IDEX).OR.P(2,I).EQ.Z(2,IDEX)) TEST= 0.0
IF (P(2,I).GT.Z(1,IDEX).AND.P(2,I).LT.Z(2,IDEX)) TEST=1.0
TESTBL=HFMABL*HFMABL*HFMIBL*HFMIBL
      -HFMABL*HFMABL*(P(2,I)-ZCBL)*(P(2,I)-ZCBL)
      -HFMIBL*HFMIBL*(P(1,I)-YCBL)*(P(1,I)-YCBL)
IF (TEST) 701,501,501
501 IF (TESTBL.LE.0.0) GO TO 510
CALL MOVEM(PBLK,P(1,N),5)
GO TO 515
510 CALL MOVEM(P(1,I),P(1,N),5)
515 N=N+1
L=L+1
IF (TEST.EQ.0.0) GO TO 800
IF (L.EQ.0) GO TO 800
IF (TEST*TESTO) 704,800,800
704 CALL INTPL(POLD,P(1,I),PINT,Z(1,IDEX))
NCHG=0
IF (TEST.LT.0.0) GO TO 711
CALL MOVEM(P(1,N-1),P(1,N),5)
NCHG=1
711 CALL MOVEM(PINT,PBLK,2)
TESTBL=HFMABL*HFMABL*HFMIBL*HFMIBL
      -HFMABL*HFMABL*(PINT(2)-ZCBL)*(PINT(2)-ZCBL)
      -HFMIBL*HFMIBL*(PINT(1)-YCBL)*(PINT(1)-YCBL)
IF (TESTBL.LE.0.0) GO TO 720
CALL MOVEM(PBLK,P(1,N-NCHG),5)
GO TO 725
720 CALL MOVEM(PINT,P(1,N-NCHG),5)
725 N=N+1
L=L+1
800 CALL MOVEM(P(1,I),POLD,5)
TESTO=TEST
900 CONTINUE
NPOINT=N-1
NLOC=5*NPERIM
CALL MOVEM(PRS,P(1,N),NLOC)
IF (IO(4,1).EQ.1) WRITE(7,950) NPOINT,ICALL
IF (IO(4,1).EQ.1) WRITE(7,950) ((P(I,J),I=1,5),J=1,NPOINT)
IF (IO(1,ICALL).EQ.0) RETURN
PRINT 950, YMIN,YMAX,ZMIN,ZMAX,GRIDLO,GRIDHI,GRID,NBARS,NPOINT
950 FORMAT(///' QUANTIZING DATA-///'
      ' POINT PATTERN EXTENTS ON APERTURE PLANE.....YMIN=',F7.2/
      ' .....YMAX=',F7.2/
      ' .....ZMIN=',F7.2/
      ' .....ZMAX=',F7.2/
      ' GRID RANGES FROM.....',F8.3,' TO
      ' F8.3/
      ' SPACING BETWEEN GRID BARS IS.....',F8.4/
      ' THEREFORE NUMBER OF GRID BARS.....',I6/

```



```

      ' NUMBER OF POINTS SUPPLIED TO RADPAT.....',I7 )
951  FORMAT(2I8)
952  FORMAT(5D16.10)
      RETURN
1005  PRINT 1006
1006  FORMAT(///
      ' ***** 2 ARRAY FOR POINT RESIDENCE NOT FILLED CORRECTLY
      ' *****',//10X,'- STOP EXECUTION -')
      STOP
      END

```

```

SUBROUTINE INTGRT(P,MAJOR,AMAJOR,AMINOR,FLDY,FLDZ)
IMPLICIT REAL*8 (A-H,O-Z)
REAL*8 MAJOR,MINOR
COMPLEX*16 CTEMP,CZ1,CZ2,CY1,CY2,TSZ,TSY,DZ1,DY1,ZIOLD,YIOLD,
      ZI,YI,FLDZ,FLDY,FLDZ(200),FLDY(200)
INTEGER SURFCE
COMMON/MATH/PI,P12,PID2,DTOR,RTOD
COMMON/PARAMS/AORORP,BELLP,PR1,PLNPNT(3),PLNORM(3),FEED(3),
      ALPHA,BETA,GAMMA,XLAM,XC,SURFCE,NPML,NPOINT
DIMENSION AMINOR(3),P(5,2750)
DATA HPHI,HTHTA/5HPHI ,5HHTETA/
SEN=999.0
NPARTS=7
RPART=1./NPARTS
ZLAM=PI2/XLAM
CALL SETM(SEN,P(1,NPOINT+1),5)
DEGR=AMAJOR
DEGR=DEGR*DTOR
DLOR=AMINOR(1)*DTOR
DICR=AMINOR(3)*DTOR
DSTOPR=AMINOR(2)*DTOR+DICR*0.5
NTH=0
D=DLOR
IF (MAJOR.NE.HPHI) GO TO 3400
400  COSP=DCOS(DEGR)
      SINP=DSIN(DEGR)
      COST=DCOS(D)
      SINT=DSIN(D)
      GO TO 3425
3400  COSP=DCOS(D)
      SINP=DSIN(D)
      COST=DCOS(DEGR)
      SINT=DSIN(DEGR)
3425  NTH=NTH+1
      CTSP=COST*SINP
      ZK=ZLAM*COST
      YK=ZLAM*SINP*SINT
      IOLD=1
      INEW=2
      FLDY=(0.0,0.0)
      FLDZ=(0.0,0.0)
      YOLD=SEN
      YI=(0.0,0.0)
      ZI=(0.0,0.0)
1450  CONTINUE
      IF (P(1,IOLD) .NE. P(1,INEW)) GO TO 4000
      Z=P(2,IOLD)
      ERY=P(3,IOLD)
      ERZ=P(4,IOLD)

```

```

PH=P(5,IOLD)
DZ=(P(2,INew)-Z)*RPART
DERJ=(P(3,INew)-ERY)*RPART
DERZ=(P(4,INew)-ERZ)*RPART
DPH=(P(5,INew)-PH)*RPART
CTEMP=CDEXP(DCMPLX(0.0D0,ZK*Z-PH))
CZ1=ERZ*COSP*CTEMP
CY1=(ERY*SINT+ERZ*CTSP)*CTEMP
TSY=(0.0,0.0)
TSZ=(0.0,0.0)
DO 3700 N=1,NPARTS
Z=Z+DZ
ERY=ERY+DERY
ERZ=ERZ+DERZ
PH=PH+DPH
CTEMP=CDEXP(DCMPLX(0.0D0,ZK*Z-PH))
CZ2=ERZ*COSP*CTEMP
CY2=(ERY*SINT+ERZ*CTSP)*CTEMP
TSZ=TSZ+CZ1+CZ2
TSY=TSY+CY1+CY2
CZ1=CZ2
CY1=CY2
3700 CONTINUE
ZI=ZI+TSZ*(.5*DZ)
YI=YI+TSY*(.5*DZ)
3900 IOLD=IOLD+1
INew=INew+1
GO TO 3450
4000 CONTINUE
YNew=P(1,IOLD)
IF(YOLD.EQ.SEN) GO TO 4400
4200 DZI=(ZI-ZIOLD)*RPART
DYI=(YI-YIOLD)*RPART
DY=(YNew-YOLD)*RPART
CTEMP=CDEXP(DCMPLX(0.0D0,YK*YOLD))
CZ1=ZIOLD*CTEMP
CY1=YIOLD*CTEMP
TSY=(0.0,0.0)
TSZ=(0.0,0.0)
DO 4300 N=1,NPARTS
YOLD=YOLD+DY
ZIOLD=ZIOLD+DZI
YIOLD=YIOLD+DYI
CTEMP=CDEXP(DCMPLX(0.0D0,YK*YOLD))
CZ2=ZIOLD*CTEMP
CY2=YIOLD*CTEMP
TSZ=TSZ+CZ1+CZ2
TSY=TSY+CY1+CY2
CZ1=CZ2
CY1=CY2
4300 CONTINUE
FLDZ=FLDZ+TSZ*(.5*DY)
FLDY=FLDY+TSY*(.5*DY)
4400 CONTINUE
YOLD=YNew
ZIOLD=ZI
YIOLD=YI
YI=(0.0,0.0)
ZI=(0.0,0.0)
IF(P(1,INew).NE.SEN) GO TO 3900
FIELDY(NTH)=FLDY
FIELDZ(NTH)=FLDZ
D=D+DICR

```

5000 IF (D.GT.DSTOPR) GO TO 5000
IF (MAJOR.EQ.HPHI) GO TO 400
GO TO 3400
CONTINUE
RETURN
END

APPENDIX E
OUTPUT FOR THE EXAMPLE

PARABOLIC REFLECTOR FAR FIELD RADIATION
PATTERN CALCULATION

OFFSET-FED PARABOLIC DISH RUSCH/AEROJET CASE ONE
ILLUMINATION INTERPOLATED FROM TABLES; NO BLOCKAGE; SINGLE-PANEL OPTION
USED IN THIS RUN.
MAY 22, 1980 NCSU PGMR: BOTULA FCLTY: HILLSBORO

INPUT PARAMETERS-

WAVELENGTH OF ELECTRIC FIELD.....	2.3670		
LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....	-1.129	0.0	4.229
FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....	0.0	0.0	-40.300
FOCAL LENGTH OF THE REFLECTOR.....	31.500		
**** PROGRAM IN SINGLE PANEL MODE ****			
MINIMUM-Y POINT ON THE REFLECTOR (X,Y,Z).....	-17.060	0.0	42.654
MAXIMUM-Y POINT ON THE REFLECTOR (X,Y,Z).....	-31.416	0.0	3.247
MINIMUM-Z POINT ON THE REFLECTOR (X,Y,Z).....	-24.244	19.685	22.950
MAXIMUM-Z POINT ON THE REFLECTOR (X,Y,Z).....	-24.244	-19.685	22.950
APERTURE PLANE LOCATION (XC).....	-16.00	0.0	
FEED SHADOW CENTER COORDINATES IN APERTURE PL.....	0.0		
HALF MAJOR AXIS OF FEED SHADOW.....	0.0		
HALF MINOR AXIS OF FEED SHADOW.....	0.0		
NUMBER OF PANELS IN REFLECTOR.....	1		

PATTERN OF FEED IN ONE DEG INCREMENTS OFF-AXIS-

PHI-PLANE -

1.000000	0.998514	0.994251	0.987122	0.977230
0.064645	0.094970	0.031827	0.011855	0.089713
0.865567	0.839673	0.812006	0.782983	0.752735
0.721474	0.689409	0.656752	0.623711	0.590488
0.557281	0.524280	0.491659	0.459590	0.428226
0.397712	0.368194	0.339747	0.312513	0.286573
0.262009	0.238890	0.217275	0.197210	0.178732
0.161864	0.146621	0.133000	0.120987	0.110546
0.101622	0.094129	0.087955	0.082958	0.078977
0.075836	0.073357	0.071374	0.069737	0.068321
0.067025	0.065772	0.064510	0.063205	0.061836
0.060394	0.058875	0.057280	0.055609	0.053868
0.052066	0.050215	0.048333	0.046438	0.044547
0.042671	0.040818	0.038900	0.037197	0.035415
0.032368	0.032004	0.030391	0.028854	0.027391
0.025908	0.024666	0.023388	0.022164	0.021002
0.019913	0.018906	0.017981	0.017128	0.016331
0.015576	0.014856	0.014177	0.013550	0.012989
0.012496				

PATTERN OF FEED IN ONE DEG INCREMENTS OFF-AXIS-

THETA-PLANE -

1.000000	0.998486	0.994139	0.986870	0.976794
0.067075	0.0948527	0.030586	0.010294	0.087824
0.963348	0.837063	0.809177	0.779891	0.749428
0.718007	0.685849	0.653170	0.620182	0.587093
0.554100	0.521397	0.489158	0.457544	0.426712
0.396795	0.367920	0.340184	0.313682	0.288490
0.264668	0.242263	0.221307	0.201820	0.183806
0.167258	0.152158	0.138473	0.126161	0.115165
0.105417	0.096827	0.089334	0.082808	0.077149
0.072248	0.067993	0.064278	0.061002	0.058077
0.055427	0.052987	0.050705	0.048543	0.046470
0.044465	0.042513	0.040607	0.038742	0.036916
0.035129	0.033383	0.031682	0.030028	0.028426
0.026878	0.025389	0.023961	0.022594	0.021291
0.020050	0.018874	0.017760	0.016709	0.015719
0.014790	0.013918	0.013102	0.012358	0.011683
0.010954	0.010329	0.009746	0.009203	0.008696
0.008223	0.007780	0.007366	0.006976	0.006609
0.006265				

ORIGINAL PAGE IS
OF POOR QUALITY

NUMBER OF PATTERN GROUPS REQUESTED..... ?
 PHI = 0.0
 THETA = 0.0000
 THETA FROM 68.0000 TO 98.0000 BY 0.5000
 PHI FROM -15.0000 TO 15.0000 BY 0.5000

ILLUMINATION DATA-

THETA ILLUMINATION FROM..... 57.704 TO 116.651
 PHI ILLUMINATION FROM..... 149.184 TO 210.814
 INCREMENTAL ANGLE (DEG)..... 1.3397
 THEREFORE TOTAL NUMBER OF GENERATED RAYS..... 2115
 TOTAL NUMBER OF APERTURE PLANE POINTS..... 2119

----- FINISHED APRTUP -----

QUANTIZING DATA-

POINT PATTERN EXTENTS ON APERTURE PLANE..... YMIN= -19.73
 YMAX= 19.73
 ZMIN= 5.36
 ZMAX= 42.72
 GRID RANGES FROM..... -19.550 TO 19.550
 SPACING BETWEEN GRID BARS IS..... 0.8887
 THEREFORE NUMBER OF GRID RAYS..... 45
 NUMBER OF POINTS SUPPLIED TO RADPAT..... 1643

----- FINISHED QUANTZ -----
 ***** EXECUTED APRPLT *****
 ----- FINISHED INTGRT -----
 ----- FINISHED INTGRT -----
 ----- PATTERN COMPUTATIONS COMPLETE -----

TABLE OF ELECTRIC FIELD DIRECTIONS (DBL)

PRINCIPAL PLANE OF CUT IS PHI = 0.0 DEG
 ANGLE THETA FROM 68.000 TO 98.000 BY 0.500 DEG

THETA	DR(Z/Y)	DR(Y/Y)	DR(Z/Y)	DR(Y/Y)	PWRDR
68.000	-22.52338	142.72638	-202.63189	-37.38213	-37.38213
69.000	-21.87239	144.77037	-201.98090	-35.33813	-35.33813
70.000	-21.19867	146.38981	-201.30718	-33.71870	-33.71870
71.000	-20.63708	147.26245	-200.74559	-32.84605	-32.84605
72.000	-20.26398	147.40246	-200.37248	-32.70604	-32.70604
73.000	-20.06361	147.03836	-200.17212	-33.07015	-33.07015
74.000	-19.91452	146.83776	-200.02303	-33.27075	-33.27075
75.000	-19.61583	147.70686	-199.72434	-32.40164	-32.40164
76.000	-19.00978	149.48245	-199.11829	-30.62606	-30.62606
77.000	-18.12605	151.23318	-198.23455	-28.87532	-28.87532
78.000	-17.14798	152.44518	-197.25648	-27.66332	-27.66332
79.000	-16.25097	153.00834	-196.35948	-27.10016	-27.10016
80.000	-15.50853	153.07056	-195.61703	-27.03794	-27.03794
81.000	-14.88282	154.38918	-194.99133	-26.89976	-26.89976
82.000	-14.25111	156.70905	-193.58115	-25.71933	-25.71933
83.000	-13.47265	159.28341	-192.60006	-23.39946	-23.39946
84.000	-12.49156	161.56221	-191.49247	-20.82510	-20.82510
85.000	-11.38396	163.45037	-190.40044	-18.54630	-18.54630
86.000	-10.29193	165.04565	-189.43954	-16.65813	-16.65813
87.000	-9.33103	166.52314	-188.65601	-15.06285	-15.06285
88.000	-8.54750	168.06508	-188.01973	-13.58537	-13.58537
89.000	-7.91123	169.77002	-187.42890	-12.04343	-12.04343
90.000	-7.32079	171.60042	-186.73824	-10.33849	-10.33849
91.000	-6.62973	173.43233	-185.87509	-8.50809	-8.50809
92.000	-5.72658	175.14146	-184.72337	-6.67618	-6.67618
93.000	-4.61487	176.64418	-183.52045	-4.96705	-4.96705
94.000	-3.41194	177.89589	-182.37471	-3.46433	-3.46433
95.000	-2.26621	178.87496	-181.40214	-2.23355	-2.23355
96.000	-1.129364	179.57339	-180.67490	-1.053511	-1.053511
97.000	-0.56639				

83.000	-0.12625	179.99622	-180.23476	-0.12229	-0.12229
83.500	0.0	180.10851	-180.10851	0.0	0.0
84.000	-0.21069	179.93229	-180.31920	-0.17621	-0.17621
84.500	-0.78576	179.44439	-180.89426	-0.66412	-0.66412
85.000	-1.76453	178.62303	-181.87303	-1.48458	-1.48458
85.500	-3.20843	177.43885	-183.31694	-2.66965	-2.66965
86.000	-5.21948	175.84004	-185.32798	-4.26847	-4.26847
86.500	-7.98091	173.75049	-188.08942	-6.35802	-6.35802
87.000	-11.86299	171.04395	-191.97150	-9.06456	-9.06456
87.500	-17.72092	167.49986	-197.82942	-12.60865	-12.60865
88.000	-25.18058	162.72074	-205.28908	-17.38777	-17.38777
88.500	-31.06517	156.44363	-201.17368	-23.66488	-23.66488
89.000	-37.64532	153.99921	-197.75783	-26.10929	-26.10929
89.500	-44.50302	151.60552	-196.61153	-23.50299	-23.50299
90.000	-51.80264	149.69275	-196.91115	-22.41575	-22.41575
90.500	-59.30381	147.08129	-198.41232	-23.02721	-23.02721
91.000	-66.82218	144.94127	-201.13069	-25.26723	-25.26723
91.500	-74.78386	142.32418	-204.89236	-29.78433	-29.78433
92.000	-82.86217	139.39594	-206.97067	-40.71257	-40.71257
92.500	-90.92330	141.64320	-205.03180	-38.46531	-38.46531
93.000	-98.97349	148.67057	-203.08200	-31.43793	-31.43793
93.500	-106.9906	150.90994	-202.27757	-29.19857	-29.19857
94.000	-114.97501	151.09314	-202.48752	-29.01537	-29.01537
94.500	-122.93796	149.67820	-203.47646	-30.43031	-30.43031
95.000	-130.78374	146.40131	-204.89224	-33.70719	-33.70719
95.500	-138.91122	139.77992	-206.01973	-40.32858	-40.32858
96.000	-146.11141	134.07889	-206.21991	-46.02962	-46.02962
96.500	-153.73943	142.02805	-205.84793	-38.08046	-38.08046
97.000	-161.55904	145.18454	-205.66754	-34.92396	-34.92396
97.500	-169.97712	145.99786	-206.08562	-34.11064	-34.11064
98.000	-177.10670	145.17431	-207.21520	-34.93419	-34.93419

MAXIMUM FIELD VALUES-


20LOG(MAX(FIELD-Z))=20LOG(1.5881356D-08)=-155.9822484

20LOG(MAX(FIELD-Y))=20LOG(1.6080993D 01)= 24.1262674

INTERPOLATION NUMBER USED FOR INTEGRATION IS..... 7

PRINCIPAL PLANE = PHI 0.0 DEGREES

NORMALIZED POWER PATTERN (DB)






TABLE OF ELECTRIC FIELD DIRECTIONS (DB)

PRINCIPAL PLANE OF CUT IS $\theta = 83.000$ DEGANGLE PHI FROM -15.000 TO 15.000 BY 0.500 DEG

PHI	$\theta(Z/Z)$	$\theta(Y/Y)$	$\theta(R/Y)$	$\theta(Y/Y)$	PWDR
-15.000	-27.50567	-31.35257	-51.23846	-55.08537	-49.75726
-14.500	-28.22097	-18.66090	-51.05377	-42.39379	-41.95631
-14.000	-31.17684	-14.00324	-54.90964	-37.82603	-37.76020
-13.500	-40.09400	-12.18113	-63.82680	-35.91392	-35.92525
-13.000	-38.70648	-12.08991	-62.43928	-35.82270	-35.83160
-12.500	-29.69122	-13.98680	-53.42402	-37.71960	-37.62272
-12.000	-26.17116	-19.30312	-49.00396	-43.03592	-42.24194
-11.500	-24.96087	-23.00121	-48.69367	-46.73400	-44.86128
-11.000	-25.71720	-14.23445	-49.45010	-37.96725	-37.68740
-10.500	-29.36903	-10.03342	-53.10183	-33.76622	-33.73425
-10.000	-46.07978	-8.22000	-69.77257	-31.96180	-31.97043
-9.500	-29.99636	-8.27360	-53.72916	-32.00640	-31.99563
-9.000	-23.34615	-10.58726	-47.07895	-34.32006	-34.11421
-8.500	-20.36214	-18.26762	-44.05493	-42.00042	-39.93066
-8.000	-19.45560	-18.54074	-43.19840	-42.27354	-39.71497
-7.500	-20.56814	-8.71238	-44.30094	-32.44518	-32.18911
-7.000	-23.44725	-4.86341	-47.18005	-28.60121	-28.55973
-6.500	-19.99390	-3.55630	-43.72670	-27.28910	-27.20992
-6.000	-13.51888	-4.28119	-37.25168	-29.01398	-27.54330
-5.500	-8.89955	-4.79682	-32.63235	-28.88962	-27.12197
-5.000	-5.60108	0.62616	-28.37478	-23.10664	-22.19661
-4.500	-3.21912	6.52813	-26.95191	-17.20467	-16.78950
-4.000	-1.54722	11.03004	-25.28002	-12.70276	-12.48759
-3.500	-0.48663	14.49205	-24.21943	-9.24075	-9.12324
-3.000	-0.00000	17.20256	-23.73280	-6.53024	-6.46666
-2.500	-0.10070	19.33058	-23.83350	-4.40222	-4.37134
-2.000	-0.86311	20.97794	-24.59501	-2.75486	-2.74488
-1.500	-2.46875	22.20850	-26.20154	-1.52480	-1.52798
-1.000	-5.76333	23.06297	-29.09613	-0.66987	-0.68198
-0.500	-11.01168	23.56643	-34.74448	-0.16637	-0.18320

0.0	-156.37967	23.73280	-180.11247	0.0	-0.01835
0.500	-11.01168	23.58643	-34.74448	-0.16637	-0.16320
1.000	-5.36333	23.06297	-29.09613	-0.66087	-0.68198
1.500	-2.46875	22.20850	-26.20154	-1.52430	-1.52788
2.000	-0.86211	20.97734	-24.55591	-2.75486	-2.74488
2.500	-0.10070	19.33058	-23.83360	-4.40222	-4.37134
3.000	0.0	17.20256	-23.73280	-6.53024	-6.46666
3.500	-0.48667	14.40205	-24.21943	-9.24975	-9.12324
4.000	-1.54722	11.03004	-25.28002	-12.70276	-12.48759
4.500	-3.21912	6.52813	-26.95191	-17.20467	-16.78880
5.000	-5.60108	0.62616	-29.33478	-23.10664	-22.19661
5.500	-8.89955	-4.79682	-32.63235	-28.52962	-27.12157
6.000	-13.51888	-4.28119	-37.25169	-29.01398	-27.54330
6.500	-19.99390	-3.55630	-43.72670	-27.28910	-27.20992
7.000	-23.44725	-4.26841	-47.18005	-29.60121	-28.55973
7.500	-20.56814	-8.71238	-44.30094	-32.44518	-32.18911
8.000	-19.45560	-18.54075	-43.18840	-42.27754	-39.71497
8.500	-20.36214	-18.26763	-44.09493	-42.00042	-39.93067
9.000	-23.34615	-10.58727	-47.07895	-34.32006	-34.11421
9.500	-29.99636	-8.27360	-53.72916	-32.00640	-31.99553
10.000	-46.01578	-8.22900	-69.77258	-71.06180	-31.97943
10.500	-29.36903	-10.03342	-53.10183	-33.76622	-33.77428
11.000	-25.71730	-14.27445	-49.45010	-37.96725	-37.68740
11.500	-24.96087	-23.00121	-48.69367	-46.73401	-44.61328
12.000	-26.17116	-19.30312	-49.90396	-43.03592	-42.24194
12.500	-29.69122	-13.08680	-53.42402	-37.71960	-37.62272
13.000	-38.70648	-12.08991	-62.43928	-35.82271	-35.83160
13.500	-40.09400	-12.18113	-63.82680	-35.01392	-35.92525
14.000	-31.17684	-14.09324	-54.90964	-37.82603	-37.76020
14.500	-28.22097	-18.66090	-51.95377	-42.39379	-41.95631
15.000	-27.50567	-21.35257	-51.23646	-55.08537	-49.75726


MAXIMUM FIELD VALUES-


20LOG(MAX(FIELD-Z))=20LOG(1.03171237 00)= 0.2711718

20LOG(MAX(FIELD-Y))=20LOG(1.58961790 01)= 20.8023728

INTERPOLATION NUMREF USED FOR INTEGRATION IS..... 7

PRINCIPAL PLANE = THETA 83.000 DEGREES





PARABOLIC REFLECTOR FAR FIELD RADIATION PATTERN CALCULATION

CASE TWO

OFFSET-FEED PARABOLIC DISH RUSCH/AEROJET
ILLUMINATION INTERPOLATED FROM TABLES; NO CLOCKAGE
REFLECTOR IS ONE PANEL DEFINED BY 20 PERIMETER POINTS
MAY 22, 1980 NCSU
PGMP: ROTULA FCLTY: HILLSRPO

INPUT PARAMETERS-

WAVELENGTH OF ELECTRIC FIELD.....	2.767	
LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z).....	-1.129	0.0
FEED ROTATION ANGLES (ALPHA,BETA,GAMMA).....	0.0	0.0
FOCAL LENGTH OF THE REFLECTOR.....	31.500	-40.000
APERTURE PLANE LOCATION (XC).....	-16.00	
FEED SHADOW CENTER COORDINATES IN APERTURE PL.....	0.0	0.0
HALF MAJOR AXIS OF FEED SHADOW.....	0.0	
HALF MINOR AXIS OF FEED SHADOW.....	0.0	
NUMBER OF PANELS IN REFLECTOR.....	1	

PATTERN OF FEED IN ONE DEG INCREMENTS OFF-AXIS-

PHI-PLANE -

1.00000	0.994251	0.994514	0.977230
0.964645	0.931827	0.949470	0.889713
0.965507	0.812006	0.839603	0.752715
0.721474	0.656752	0.689409	0.590488
0.557281	0.491659	0.524280	0.428226
0.397712	0.339747	0.368184	0.286573
0.262009	0.217275	0.238890	0.178732
0.161864	0.133000	0.146621	0.110546
0.101622	0.087955	0.094129	0.078977
0.075836	0.071374	0.073357	0.068321
0.067025	0.064510	0.065772	0.061836
0.060394	0.057280	0.058875	0.053868
0.052066	0.048373	0.050215	0.044547
0.042671	0.038990	0.040818	0.036915
0.037487	0.030391	0.032004	0.027391
0.025998	0.023388	0.024666	0.021002
0.019913	0.017991	0.018906	0.016731
0.015576	0.014177	0.014856	0.013989
0.012406			

PATTERN OF FEED IN ONE DEG INCREMENTS OFF-AXIS-

THETA-PLANE -

1.000000	0.998486	0.994139	0.986870	0.976794
0.963075	0.948527	0.930586	0.910204	0.887824
0.963248	0.837067	0.800177	0.773891	0.749428
0.719007	0.685849	0.653170	0.620182	0.587093
0.554100	0.521397	0.489158	0.457544	0.426712
0.396705	0.367020	0.340184	0.313682	0.288490
0.264668	0.242263	0.221307	0.201820	0.183806
0.167258	0.152154	0.138472	0.126161	0.115165
0.105417	0.096837	0.089334	0.082808	0.077149
0.072248	0.067003	0.064278	0.061022	0.058077
0.055427	0.052587	0.050705	0.048543	0.046470
0.044465	0.042513	0.040607	0.038742	0.036916
0.035129	0.033383	0.031682	0.030028	0.028426
0.026878	0.025380	0.023961	0.022594	0.021291
0.020059	0.018874	0.017750	0.016709	0.015719
0.014790	0.013918	0.013102	0.012338	0.011623
0.010954	0.010329	0.009746	0.009203	0.008696
0.008223	0.007780	0.007366	0.006976	0.006609
0.006255				

NUMREF OF PATTERN GROUPS REQUESTED..... 2

PHI = 0.0 THETA FROM 68.0000 TO 78.0000 BY 0.5000
 THETA = 83.0000 PHI FROM -15.0000 TO 15.0000 BY 0.5000

ORIGINAL PAGE IS
OF POOR QUALITY

REFLECTOR PANEL NUMBER 1

PANEL IS A PARABOLIC SECTION

FOCAL LENGTH OF THE PARABOLA..... 31.50
 NUMBER OF USER-SUPPLIED EDGE POINTS..... 20

ILLUMINATION DATA-

THETA ILLUMINATION FROM..... 57.288 TO 117.055
 PHI ILLUMINATION FROM..... 148.817 TO 211.183
 INCREMENTAL ANGLE (DEG)..... 1.2093
 THEREFORE TOTAL NUMBER OF GENERATED RAYS..... 2303
 TOTAL NUMBER OF APERTURE PLANE POINTS..... 2323

----- FINISHED APERTURE -----

QUANTIZING DATA-

POINT PATTERN EXTENTS ON APERTURE PLANE..... YMIN= -19.73

..... YMAX= 19.73
 YMIN= 5.39
 YMAX= 42.71

GRID RANGES FROM..... -19.558 TO 19.558
 SPACING BETWEEN GRID RAYS IS..... 0.8503
 THEREFORE NUMBER OF GRID RAYS..... 47
 NUMBER OF POINTS SUPPLIED TO RADPAT..... 1720

----- FINISHED QUANT7 -----

***** EXECUTED APERT *****

----- FINISHED INTGRY -----

----- FINISHED INTGRY -----

----- PATTERN COMPUTATIONS COMPLETE -----

***** EXECUTED APRMAP *****

TABLE OF ELECTRIC FIELD STRENGTHS (DB)

PRINCIPAL PLANE OF CUT IS PHI = 5.0 DEG

ANGLE THETA FROM 68.000 TO 98.000 BY 0.500 DEG

THETA	09(Z/Z)	09(Y/Y)	09(Z/Y)	09(Y/Y)	PWDR
68.000	-24.77376	144.60518	-205.07675	-35.65820	-35.65820
68.500	-23.59713	146.68729	-203.86052	-33.57609	-33.57609
69.000	-22.29165	148.02717	-202.55504	-32.24026	-32.24026
69.500	-21.16644	148.54016	-201.42983	-31.72323	-31.72323
70.000	-20.70345	148.27731	-200.56684	-31.08608	-31.08608
70.500	-19.64617	147.44554	-199.90956	-32.81784	-32.81784
71.000	-19.06555	146.85708	-199.32877	-33.41030	-33.41030
71.500	-18.42599	147.75577	-198.68937	-32.50662	-32.50662
72.000	-17.66756	149.70275	-197.93095	-30.46704	-30.46704
72.500	-16.84367	151.70911	-197.10705	-28.55428	-28.55428
73.000	-16.07004	152.07656	-196.33363	-27.28683	-27.28683
73.500	-15.44402	153.54480	-195.70740	-26.71859	-26.71859
74.000	-14.80481	153.60005	-194.92520	-26.66334	-26.66334
74.500	-14.66161	153.74063	-194.02500	-26.52275	-26.52275
75.000	-14.29252	154.91620	-194.55501	-25.74719	-25.74719
75.500	-13.70295	157.19517	-193.96634	-23.06822	-23.06822
76.000	-12.81084	159.71164	-197.07423	-20.55175	-20.55175
76.500	-11.71420	161.93478	-191.97758	-18.32861	-18.32861
77.000	-10.59503	163.77454	-190.86242	-16.48885	-16.48885
77.500	-9.61020	165.33008	-189.87359	-14.93331	-14.93331
78.000	-8.80251	166.77795	-189.06590	-13.48544	-13.48544
78.500	-8.14211	168.30060	-188.40549	-11.96269	-11.96269
79.000	-7.51809	169.99798	-187.78238	-10.26940	-10.26940
79.500	-6.78322	171.81548	-187.04660	-8.44791	-8.44791
80.000	-5.82813	173.67806	-186.09152	-6.62532	-6.62532
80.500	-4.67116	175.33697	-184.93454	-4.92646	-4.92646
81.000	-3.43822	176.82021	-183.70160	-3.43418	-3.43418
81.500	-2.27694	178.07094	-182.54032	-2.19245	-2.19245
82.000	-1.26815	179.04205	-181.56154	-1.22132	-1.22132
82.500	-0.56910	179.73416	-180.83249	-0.52923	-0.52923

87.000	-0.12816	130.14284	-180.39155	-0.12054	-0.12054
88.500	0.0	180.26339	-180.26339	0.0	0.0
89.000	-0.20628	150.08900	-180.46956	-0.17579	-0.17579
90.500	-0.77338	179.60365	-181.03676	-0.65974	-0.65974
91.000	-1.77365	178.78065	-182.00700	-1.47374	-1.47374
92.500	-3.16518	177.61414	-183.42857	-2.64925	-2.64925
93.000	-5.15026	176.02817	-185.41365	-4.27522	-4.27522
94.500	-7.87557	173.95477	-188.11806	-6.30862	-6.30862
95.000	-11.71047	171.26602	-191.97386	-8.99647	-8.99647
96.500	-17.55988	167.73940	-197.82326	-12.52399	-12.52399
97.000	-26.15720	162.94706	-206.42059	-17.31633	-17.31633
98.500	-21.72500	156.42886	-201.98838	-23.83453	-23.83453
99.000	-17.87042	153.63543	-198.13381	-26.62795	-26.62795
99.500	-16.53186	156.63074	-196.79525	-23.63264	-23.63264
99.900	-16.67426	157.61917	-196.93765	-22.34422	-22.34422
99.950	-17.07093	157.45008	-198.23436	-22.81331	-22.81331
99.990	-20.31077	155.37327	-200.57375	-24.89006	-24.89006
99.995	-23.25510	151.15157	-203.51849	-29.11182	-29.11182
99.999	-24.71700	141.55507	-204.97538	-38.79822	-38.79822
99.999	-23.48213	140.66166	-203.74551	-39.60172	-39.60172
99.999	-22.02157	149.57473	-202.28496	-31.68865	-31.68865
99.999	-21.42997	151.09151	-201.69335	-29.17188	-29.17188
99.999	-21.79425	151.46275	-202.05764	-28.80064	-28.80064
99.999	-23.08161	150.24081	-203.34500	-30.02258	-30.02258
99.999	-25.23600	147.25000	-205.49039	-33.00348	-33.00348
99.999	-27.86493	141.51312	-208.12832	-38.75027	-38.75027
99.999	-29.45056	136.36602	-209.71395	-43.83736	-43.83736
99.999	-28.02200	142.65044	-209.12539	-37.61294	-37.61294
99.999	-27.89807	145.95810	-208.16235	-34.40520	-34.40520
99.999	-27.46568	146.81206	-207.72907	-33.45133	-33.45133
99.999	-27.68158	146.12930	-207.94407	-34.13309	-34.13309

MAXIMUM FIELD VALUES


20LOG(MAX(FIELD-7))=20LOG(1.55293020-08)=-156.1769614

20LOG(MAX(FIELD-7))=20LOG(1.55293020-08)=-156.1769614

INTERPOLATION NUMRFC USED FOR INTEGRATION IS..... 7

PRINCIPAL PLANE = PHI 0.0 DEGREES

NORMALIZED POWER PATTERN (DB)






TABLE OF ELECTRIC FIELD SIDINGHS (DB)

PRINCIPAL PLANE OF CUT IS THETA = 83.000 DEG

ANGLE PHI FROM -15.000 TO 15.000 BY 0.500 DEG

PHI	DR(Z/Y)	DR(V/Y)	DR(Z/V)	DR(V/V)	PWPR
-15.000	-27.40767	-28.37456	-51.13925	-52.10613	-49.60390
-14.500	-28.41385	-17.60299	-52.14543	-41.33457	-41.00676
-14.000	-11.97090	-12.62903	-55.60248	-37.36061	-37.31434
-13.500	-43.28422	-12.04810	-67.01580	-35.77968	-35.79477
-13.000	-36.27458	-12.25498	-60.00615	-35.68658	-35.98773
-12.500	-28.75654	-14.59229	-52.48811	-38.32386	-38.17895
-12.000	-25.67357	-21.31572	-49.26510	-45.04730	-43.69840
-11.500	-24.64869	-22.87200	-48.38027	-46.60357	-44.40974
-11.000	-25.60740	-17.65840	-49.37497	-77.39007	-37.13041
-10.500	-20.56714	-9.72936	-53.29871	-33.46094	-33.43444
-10.000	-18.35809	-8.12421	-72.08567	-31.85578	-31.97372
-9.500	-29.16139	-8.36279	-52.89296	-32.09437	-32.07674
-9.000	-22.00311	-10.95754	-46.67460	-34.68911	-34.43849
-8.500	-20.06287	-10.27578	-43.75445	-43.00736	-40.39115
-8.000	-10.24198	-16.21768	-42.97355	-30.94926	-38.21176
-7.500	-20.41390	-7.95280	-44.14548	-31.68438	-31.46305
-7.000	-23.28479	-4.47244	-47.01507	-28.16401	-28.12616
-6.500	-19.78904	-3.27196	-43.52061	-27.00354	-26.92611
-6.000	-13.38134	-4.08388	-37.11202	-27.81546	-27.35111
-5.500	-8.80473	-4.58784	-32.53631	-28.31942	-26.94303
-5.000	-5.571635	0.82247	-29.26797	-22.00910	-22.02793
-4.500	-3.17560	6.66863	-26.90718	-17.06295	-16.55298
-4.000	-1.52170	11.13030	-25.25287	-12.60127	-12.38996
-3.500	-0.47499	14.56323	-24.20657	-9.16835	-9.05256
-3.000	-0.00000	17.26184	-23.73158	-6.47674	-6.41708
-2.500	-0.11010	19.36308	-23.84167	-4.36849	-4.33809
-2.000	-0.87904	20.99768	-24.61151	-2.73389	-2.72415
-1.500	-2.49120	22.21802	-26.22277	-1.51275	-1.51643
-1.000	-5.38972	23.06676	-29.12130	-0.66481	-0.67697
-0.500	-11.04041	23.56646	-34.77199	-0.16511	-0.18196

RECEIVED
10-10-60
QUALITY

0.0	-156.57543	23.73158	-180.27101	0.0	-0.01835
0.500	-11.04041	23.56646	-34.77199	-0.16511	-0.16196
1.000	-5.78977	23.06576	-29.12130	-0.66481	-0.67697
1.500	-2.49120	22.21882	-26.22277	-1.51275	-1.51645
2.000	-0.97904	20.00768	-24.61151	-2.73389	-2.72415
2.500	-0.11010	19.36308	-23.84167	-4.36849	-4.33809
3.000	0.0	17.25184	-23.73158	-6.47574	-6.41708
3.500	-0.47409	14.55323	-24.20657	-9.16935	-9.05266
4.000	-1.52130	11.13030	-25.25287	-12.60127	-12.38906
4.500	-3.17560	6.66863	-26.90718	-17.06295	-16.65298
5.000	-5.53675	0.82247	-29.26793	-22.50910	-22.02397
5.500	-9.80473	-4.58784	-32.53631	-28.71546	-26.94303
6.000	-13.78124	-4.08288	-37.11202	-27.81546	-27.35111
6.500	-19.78904	-3.27196	-43.52061	-27.00364	-26.92611
7.000	-23.29470	-4.43244	-47.01597	-28.16401	-28.12616
7.500	-20.41300	-7.95280	-44.14548	-31.68438	-31.45205
8.000	-10.24198	-16.21768	-42.97355	-39.94926	-38.21136
8.500	-20.06287	-19.27578	-43.75445	-43.00736	-40.39115
9.000	-22.90311	-10.95754	-46.63460	-34.68911	-34.47849
9.500	-29.16139	-8.36279	-52.89206	-32.09437	-32.07674
10.000	-49.35810	-9.12421	-72.03968	-31.85578	-31.87372
10.500	-29.56714	-9.72936	-53.29871	-33.46094	-33.43444
11.000	-25.60340	-17.65849	-49.23497	-37.39907	-37.13941
11.500	-24.63859	-22.87200	-48.31807	-45.10357	-44.40974
12.000	-25.63353	-21.31572	-49.36510	-45.04730	-43.69840
12.500	-28.75654	-14.50220	-52.49811	-38.22387	-38.17885
13.000	-26.27458	-12.25498	-60.00615	-35.08656	-35.98773
13.500	-47.28422	-12.04810	-67.01580	-35.77968	-35.79477
14.000	-31.87090	-13.62903	-55.60248	-37.36061	-37.31434
14.500	-28.41385	-17.60290	-52.14543	-41.33457	-41.00676
15.000	-27.40767	-28.37456	-51.13025	-52.10613	-48.60389


MAXIMUM FIELD VALUES-


20LOG(MAX(FIELD-Z))=20LOG(1.02734260 00)= 0.2343062

20LOG(MAX(FIELD-Y))=20LOG(1.57867080 01)= 23.8855817

INTERPOLATION NUMBER USED FOR INTEGRATION IS..... 7

PRINCIPAL PLANE = THETA 83.000 DEGREES





PARABOLIC REFLECTOR FAR FIELD RADIATION PATTERN CALCULATION

OFFSET-FED PARABOLIC DISH RUSCH/AEROJET CASE THREE
ILLUMINATION INTERPOLATED FROM TABLES: NO BLOCKAGE: THREE PANELS -
PANEL ONE- 20 PNTS PANEL TWO- 21 PNTS PANEL THREE- 21 PNTS
WAV 22.1500 ANGLE PGMD: ROTULA FCITY: MILLSBROO

INPUT PARAMETERS-

WAVELENGTH OF ELECTRIC FIELD..... 2.3670
LOCATION OF COORDINATE ORIGIN WRT FEED (X,Y,Z)..... -1.129 0.0 0.220
FEED POSITION ANGLES (ALPHA,BETA,GAMMA)..... 0.0 0.0 -40.300
FOCAL LENGTH OF THE REFLECTOR..... 31.500
APERTURE PLANE LOCATION (YC)..... -16.00
FEED SHADOW CENTER COORDINATES IN APERTURE PL..... 0.0 0.0
HALF MAJOR AXIS OF FEED SHADOW..... 0.0
HALF MINOR AXIS OF FEED SHADOW..... 0.0
NUMBER OF PANELS IN REFLECTOR..... 3

PATTERN OF FEED IN ONE DEG INCREMENTS OFF-AXIS-

PHI-PLANE -

1.000000	0.004251	0.007122	0.977270
0.964645	0.931827	0.911855	0.889713
0.946527	0.812006	0.792943	0.752735
0.721474	0.656752	0.623711	0.590488
0.557281	0.491650	0.459500	0.428226
0.397712	0.339747	0.312513	0.286573
0.265105	0.217275	0.197210	0.178732
0.161864	0.133000	0.120947	0.110546
0.101422	0.087955	0.082954	0.078977
0.075836	0.071374	0.069737	0.068321
0.060394	0.064510	0.063205	0.061836
0.057025	0.058475	0.056609	0.053868
0.052066	0.050215	0.046434	0.044547
0.042671	0.040814	0.037187	0.034735
0.033687	0.032004	0.021854	0.027301
0.025908	0.024666	0.022164	0.021002
0.019014	0.018906	0.017129	0.016331
0.015576	0.014856	0.013550	0.012389
0.012406			

REFLECTOR PANEL NUMBER 1

PANEL IS A PARABOLIC SECTION

FOCAL LENGTH OF THE PARABOLA..... 11.50
 NUMBER OF USER-SUPPLIED EDGE POINTS..... 20

ILLUMINATION DATA-

THETA ILLUMINATION FROM..... 61.131 TO 108.416
 PHI ILLUMINATION FROM..... 178.818 TO 211.326
 INCREMENTAL ANGLE (DEG)..... 1.4776
 THEREFORE TOTAL NUMBER OF GENERATED RAYS..... 778
 TOTAL NUMBER OF APERTURE PLANE POINTS.....

----- FINISHED APERTURE -----

QUANTIZING DATA-

POINT PATTERN EXTENTS ON APERTURE PLANE..... YMIN= -19.73
 YMAX= 0.00
 ZMIN= 8.99
 ZMAX= 30.05
 GRID RANGES FROM..... -19.835 TO -0.193
 SPACING BETWEEN GRID PARS IS..... 1.0671
 THEREFORE NUMBER OF GRID PARS..... 21
 NUMBER OF POINTS SUPPLIED TO MAGNET..... 405

----- FINISHED QUANTIZING -----

*** EXECUTED APERLT ****

----- FINISHED INTERT -----

REFLECTOR PANEL NUMBER 2

PANEL IS A PARABOLIC SECTION

FOCAL LENGTH OF THE PARABOLA..... 31.50
 NUMBER OF USER-SUPPLIED EDGE POINTS..... 21

ILLUMINATION DATA-

THETA ILLUMINATION FROM..... 56.916 TO 84.587
 PHI ILLUMINATION FROM..... 149.252 TO 197.047
 INCREMENTAL ANGLE (DEG)..... 1.2578
 THEREFORE TOTAL NUMBER OF GENERATED RAYS..... 897
 TOTAL NUMBER OF APERTURE PLANE POINTS..... 918

----- FINISHED APERTURE -----

QUANTIZING DATA-

POINT PATTERN EXTENTS ON APERTURE PLANE.....

.....YMIN= -11.391
YMAX= 19.73
XMIN= 23.82
XMAX= 42.71

GRID RANGES FROM..... -11.391 TO 19.556

SPACING BETWEEN GRID RAYS IS..... 0.8556

THEREFORE NUMBER OF GRID RAYS..... 37

NUMBER OF POINTS SUPPLIED TO RADPAT..... 560

----- FINISHED QUANTIZING -----

**** EXECUTED APERLT ****

----- FINISHED INTEGRATION -----

REFLECTOR PANEL NUMBER 3

PANEL IS A PARABOLIC SECTION

FOCAL LENGTH OF THE PARABOLA..... 31.50
 NUMBER OF USER-SUPPLIED EDGE POINTS..... 23

ILLUMINATION DATA-

THETA ILLUMINATION FROM..... 90.971 TO 116.367
 PHI ILLUMINATION FROM..... 149.569 TO 203.272
 INCREMENTAL ANGLE (DEG)..... 1.6089
 THEREFORE TOTAL NUMBER OF GENERATED RAYS..... 822
 TOTAL NUMBER OF APERTURE PLANE ECINTS..... 822

----- FINISHED APRTUP -----

QUANTIZING DATA-

POINT PATTERN EXTENTS ON APERTURE PLANE..... XMIN= 11.11 TO 11.11
 XMAX= 19.73
 YMIN= 5.38
 YMAX= 24.24
 GRID RANGES FROM..... 11.11 TO 11.11
 SPACING BETWEEN GRID RAYS IS..... 0.5737
 THEREFORE NUMBER OF GRID RAYS..... 23
 THEREFORE NUMBER OF POINTS SUPPLIED TO RADPAT..... 520

----- FINISHED QUANT7 -----

**** EXECUTED APPRPT ****

----- FINISHED INTGRT -----

----- FINISHED INTGRT -----

----- PATTERN COMPUTATIONS COMPLETE -----

**** EXECUTED APPRMAP ****

TABLE OF ELECTRIC FIELD STRENGTHS (DB)

PRINCIPAL PLANE OF CUT IS PHV = 0.0 DEG

ANGLE THETA FROM 68.000 TO 98.000 BY 0.500 DEG

THETA	00(7/7)	33(Y/7)	38(Z/Y)	58(Y/Y)	PWRDB
68.000	-3.05912	32.79431	-52.05577	-34.23359	-34.23180
68.500	-3.25746	32.22068	-68.28505	-32.80692	-32.80569
69.000	-3.52412	32.17200	-68.55178	-31.85451	-31.85368
69.500	-3.89259	33.40343	-68.92058	-31.62417	-31.62336
70.000	-4.33282	32.77811	-67.42047	-32.24918	-32.24865
70.500	-4.85110	31.26024	-70.07870	-33.76665	-33.76563
71.000	-5.43263	29.55108	-70.91427	-35.47561	-35.47437
71.500	-6.07215	30.23885	-71.92974	-34.78975	-34.78791
72.000	-6.77007	27.15574	-73.05849	-31.87145	-31.87152
72.500	-7.52724	35.78742	-74.34493	-29.24018	-29.24004
73.000	-8.34283	27.54707	-75.82043	-27.49157	-27.49150
73.500	-9.21679	38.53403	-76.39549	-26.49356	-26.49352
74.000	-10.14823	39.02811	-76.70582	-25.99648	-25.99643
74.500	-11.13456	40.54890	-76.25975	-25.47869	-25.47866
75.000	-12.16456	42.74764	-75.21215	-24.27995	-24.27992
75.500	-13.23899	42.71504	-73.67658	-22.31255	-22.31252
76.000	-14.35803	44.71751	-71.95553	-20.10809	-20.10806
76.500	-15.52180	46.93520	-70.28930	-18.09239	-18.09237
77.000	-16.73769	42.54703	-68.77528	-16.78456	-16.78454
77.500	-18.00272	50.10893	-67.45031	-14.91857	-14.91864
78.000	-19.31955	51.47407	-55.46714	-13.53752	-13.53750
78.500	-20.69465	52.97926	-65.72224	-12.04833	-12.04831
79.000	-22.13233	54.66097	-65.26638	-10.36677	-10.36675
79.500	-23.62411	55.49029	-65.11401	-8.53731	-8.53730
80.000	-25.16613	58.37037	-65.28772	-6.67751	-6.67751
80.500	-26.75176	60.04746	-65.80925	-4.99013	-4.99013
81.000	-28.37833	61.50598	-66.74597	-3.47162	-3.47162
81.500	-30.04537	62.81070	-68.18696	-2.21600	-2.21600
82.000	-31.75086	67.79171	-70.28845	-1.33589	-1.33589
82.500	-33.49643	64.40096	-73.27402	-0.53663	-0.53663

87.000	-11.89087	64.90443	-76.90846	-0.12316	-0.12316
88.000	-12.40537	65.02759	-77.43296	0.0	-0.00920
89.000	-8.02249	64.85270	-73.95008	-0.17489	-0.17489
90.000	-5.78302	64.36657	-70.81062	-0.66103	-0.66103
91.000	-3.54816	63.54305	-68.57575	-1.47954	-1.47954
92.000	-1.99907	62.36440	-67.02166	-2.66320	-2.66320
93.000	-0.94722	60.76494	-65.57482	-4.25265	-4.25265
94.000	-0.30321	58.66931	-65.27042	-6.35929	-6.35929
95.000	0.0	55.94315	-65.02759	-9.08445	-9.08445
96.000	-0.00019	52.34339	-65.02778	-12.60420	-12.60420
97.000	-0.28051	47.30575	-65.76810	-17.53184	-17.53184
98.000	-0.82390	40.60003	-65.95149	-24.42757	-24.42757
99.000	-1.61153	38.65916	-66.63917	-26.36840	-26.36840
100.000	-2.61247	41.94636	-67.64006	-23.08023	-23.08023
101.000	-3.75555	43.24330	-68.75614	-21.78724	-21.78724
102.000	-4.97992	42.93600	-70.00752	-22.19159	-22.19159
103.000	-6.10725	40.93554	-71.12485	-24.09206	-24.09206
104.000	-7.01840	37.18339	-72.04600	-27.84421	-27.84421
105.000	-7.66179	36.54813	-72.68398	-35.43947	-35.43947
106.000	-8.07242	34.84399	-73.10002	-47.18301	-47.18301
107.000	-8.28401	31.10781	-73.31250	-33.91979	-33.91979
108.000	-8.24123	34.26533	-73.26883	-30.76226	-30.76226
109.000	-7.82197	34.75537	-72.94956	-30.27202	-30.27202
110.000	-6.99370	33.31356	-72.02139	-31.61333	-31.61333
111.000	-5.84446	30.14511	-70.92205	-34.88140	-34.88140
112.000	-4.73615	25.31822	-69.76374	-39.70737	-39.70737
113.000	-3.68429	26.73800	-68.71188	-38.29869	-38.29869
114.000	-2.82785	30.74910	-67.85544	-34.27840	-34.27840
115.000	-2.20077	32.83453	-67.22936	-32.19306	-32.19306
116.000	-1.80597	32.39043	-66.87157	-31.47716	-31.47716
117.000	-1.62296	32.65931	-66.65745	-32.76828	-32.76828

MAXIMUM FIELD VALUES-


20LOG(MAX(FIELD-Z))=20LOG(8.90243310-03)= -41.0098256

20LOG(MAX(FIELD-Y))=20LOG(1.65813889-03)= -34.7891389

INTERPOLATION NUMBER USED FOR INTEGRATION IS..... 7

PRINCIPAL PLANE = PHI 0.0 DEGREES

NORMALIZED POWER PATTERN (DB)






TABLE OF ELECTRIC FIELD STRENGTHS (DB)

PRINCIPAL PLANE OF CUT IS THETA = 83.000 DEG

ANGLE PHI FROM -15.000 TO 15.000 BY 0.500 DEG

PHI	DB(Z/Z)	LR(Y/Z)	DR(Z/Y)	DR(Y/Y)	PWDR
-15.000	-27.29265	-13.64241	-50.97847	-42.32823	-41.79127
-14.500	-28.38453	-13.26940	-52.07036	-36.95522	-36.84204
-14.000	-31.66610	-13.47075	-55.65103	-34.15617	-34.14405
-13.500	-41.86292	-9.21688	-65.54874	-32.90270	-32.91889
-13.000	-34.46500	-6.77388	-58.15092	-32.65970	-32.56517
-12.500	-27.95137	-10.79473	-51.63719	-34.48055	-34.41631
-12.000	-25.02955	-14.53100	-48.71538	-33.21772	-37.85530
-11.500	-24.09219	-22.73893	-47.77802	-46.42475	-44.05713
-11.000	-24.00007	-19.54107	-48.67589	-42.22685	-41.75867
-10.500	-28.65664	-12.77606	-52.34247	-35.46278	-36.37060
-10.000	-44.05017	-10.63547	-67.72596	-34.32129	-34.37786
-9.500	-30.10404	-10.99017	-53.78987	-34.67599	-34.64160
-9.000	-23.33700	-14.76784	-47.02342	-38.45366	-37.90655
-8.500	-20.37857	-30.18346	-44.06439	-53.86929	-43.65091
-8.000	-16.53050	-12.22620	-47.22541	-35.01218	-35.19119
-7.500	-20.75751	-6.13551	-44.44333	-29.82133	-29.69258
-7.000	-23.57106	-7.20838	-47.25770	-25.89420	-26.87299
-6.500	-19.61389	-2.25248	-43.29971	-25.03831	-25.87784
-6.000	-13.24790	-7.14250	-36.91372	-26.82837	-26.44247
-5.500	-8.72402	-4.31809	-32.40984	-28.00392	-26.67883
-5.000	-5.48583	6.47987	-29.17264	-23.20599	-22.24459
-4.500	-3.14572	6.43414	-26.83154	-17.25168	-16.81638
-4.000	-1.50477	10.09315	-25.10060	-12.70267	-12.48297
-3.500	-0.46801	14.46245	-24.15384	-9.28337	-9.10450
-3.000	0.0	17.17620	-23.68582	-6.09960	-6.44573
-2.500	0.11512	19.30166	-23.80094	-4.38416	-4.35332
-2.000	-0.88826	20.04442	-24.57409	-2.74140	-2.73157
-1.500	-2.59095	22.17018	-26.16677	-1.61504	-1.61940
-1.000	-5.35793	23.02052	-28.08376	-0.66530	-0.67760
-0.500	-11.03789	23.52107	-34.72371	-0.16475	-0.18178

0.0	-53.70918	22.68582	-76.78530	0.0	-0.01855
0.500	-11.08928	23.51918	-34.77510	-0.16664	-0.16369
1.000	-5.42610	23.01661	-20.11193	-0.66921	-0.68155
1.500	-2.52261	22.16399	-26.20843	-1.52183	-1.52564
2.000	-0.90775	20.97548	-24.59257	-2.75074	-2.74057
2.500	-0.13437	19.28917	-23.82019	-4.39665	-4.36599
3.000	-0.02027	17.15378	-23.70609	-6.52705	-6.48321
3.500	-0.49040	14.43740	-24.17622	-9.24837	-9.12953
4.000	-1.57049	10.04495	-25.21672	-12.74087	-12.52050
4.500	-3.17636	6.36946	-26.86219	-17.31636	-16.87769
5.000	-5.62463	0.35675	-29.21046	-23.72907	-22.55032
5.500	-8.77198	-4.42874	-32.45781	-28.11456	-26.77271
6.000	-13.30574	-7.12017	-36.99156	-28.80600	-26.42716
6.500	-19.61910	-2.19822	-43.30492	-25.88404	-25.82464
7.000	-23.25733	-3.12792	-46.94321	-26.81174	-26.76034
7.500	-20.53589	-5.97344	-44.22571	-20.65926	-29.52864
8.000	-16.36912	-11.58026	-43.08494	-35.26611	-34.62050
8.500	-20.27377	-19.59499	-43.95960	-43.28082	-40.61521
9.000	-27.25476	-17.63730	-46.94018	-37.32712	-38.89150
9.500	-20.02842	-10.53902	-53.71431	-34.22485	-34.19482
10.000	-42.11906	-10.33115	-65.80489	-34.01697	-34.03264
10.500	-28.39192	-13.52976	-52.07774	-36.21558	-36.12296
11.000	-24.76639	-18.48023	-48.45221	-42.17505	-41.27461
11.500	-23.94659	-24.09234	-47.53542	-47.77786	-44.66358
12.000	-24.72930	-14.65099	-48.41512	-38.34581	-37.95668
12.500	-27.52711	-10.72734	-51.21293	-34.41316	-34.34190
13.000	-32.77595	-8.10379	-57.46167	-32.78361	-32.79338
13.500	-48.22545	-8.03770	-71.91127	-32.62352	-32.64156
14.000	-33.00617	-10.03127	-56.69209	-33.70709	-33.70385
14.500	-20.83403	-12.46939	-52.61985	-36.15520	-36.07681
15.000	-27.67500	-16.77521	-51.31482	-40.46203	-40.14140


MAXIMUM FIELD VALUES-


20LOG(MAX(FIELD-Z))=20LOG(1.0243280D 00)= 0.2087809

20LOG(MAX(FIELD-Y))=20LOG(1.5687779D 00)=

INTERPOLATION NUMBFR USED FOR INTEGRATION IS..... 7

PRINCIPAL PLANE = THETA 83.000 DEGREES






RECEIVED PAGE 15
11/17


CASE I

APERTURE PLANE AFTER QUANTIZING




CASE II

APERTURE PLANE AFTER QUANTIZING




CASE II

MAP OF PANEL PROJECTIONS




ORIGINAL PAGE IS
OF POOR QUALITY

APERTURE PLANE AFTER QUANTIZING



APERTURE PLANE AFTER QUANTIZING

162




CASE III

APERTURE PLANE AFTER QUANTIZING

CASE III

163



CASE III

MAP OF PANEL PROJECTIONS

